

SERVICE MANUAL

AA-2D CHASSIS

<u>MODEL</u>	<u>DEST.</u>	<u>COMMANDER</u>	<u>CHASSIS NO.</u>
KV-32S40	US	RM-Y165	SCC-S07A-A
KV-32S40	CND	RM-Y165	SCC-S08A-A
KV-32S45	US	RM-Y165	SCC-S07B-A
KV-32S45	CND	RM-Y165	SCC-S08B-A
KV-34SL40T	TAIWAN	RM-Y165	SCC-S16A-A
KV-34SL40C	E	RM-Y165	SCC-S09A-A
KV-34SL40	E	RM-Y165	SCC-S09B-A
KV-34SL45	E	RM-Y167	SCC-S09C-A
KV-35S40	US	RM-Y165	SCC-S07D-A
KV-35S40	CND	RM-Y165	SCC-S08E-A
KV-35S45	US	RM-Y167	SCC-S07E-A
KV-35S45	CND	RM-Y167	SCC-S08F-A
KV-37SL45	E	RM-Y167	SCC-S09F-A
KV-32V40	US	RM-Y165	SCC-S07C-A
KV-32V40	CND	RM-Y165	SCC-S08C-A
KV-32V65	CND	RM-Y167	SCC-S08D-A
KV-34VL65	E	RM-Y167	SCC-S09E-A
KV-34VL65C	E	RM-Y167	SCC-S09D-A
KV-35V65	CND	RM-Y167	SCC-S08G-A
KV-37VL65	E	RM-Y167	SCC-S09G-A
KV-37VL65C	E	RM-Y167	SCC-S09H-A



KV-35V65



RM-Y167



TRINITRON® COLOR TV
SONY®

SPECIFICATIONS

	KV-32S40 KV-34SL40/40T	KV-34SL40C	KV-32S45 KV-34SL45	KV-32V40	KV-32V65 KV-34VL65/65C	KV-35S40/45 KV-37SL45	KV-35V65 KV-37VL65	KV-37VL65C
Power requirements	120V,60Hz	220V,50/60Hz	120V,60Hz	120V,60Hz	120V,60Hz(65) 220V,50/60Hz(65C)	120V,60Hz	120V,60Hz	220V,50/60Hz
Number of inputs/outputs								
Video ¹⁾	1	1	2	3	3	2	3	3
S Video ²⁾	1	1	1	1	2	1	2	2
Audio ³⁾	1	1	2	3	3	2	3	3
Audio Out ⁴⁾	1	1	1	1	1	1	1	1
Monitor Out	-	-	-	1	1	-	1	1
TV out	-	-	-	-	1	-	1	1
S-Link	-	-	-	-	YES	-	YES	YES
Speaker output(W)	5W x 2	5W x 2	5W x 2	5W x 2	10W x 2	5W x 2	10W x 2	10W x 2
Power Consumption(W)								
In use(Max)	180W	175W	180W	180W	200W(65), 195W(65C)	210W	230W	225W
In standby	2W	3W	2W	2W	2W(65), 3W(65C)	2W	2W	3W
Dimensions(W/H/D)								
(mm)	791 x 707 x 604.5mm			821 x 675.3 x 587mm		870 x 761 x 653mm	920 x 730.8 x 641.8mm	
(in)	31 x 27 ^{13/16} x 23 ^{3/4}			32 ^{3/8} x 26 ^{5/8} x 23 ^{1/8}		34 ^{1/4} x 30 x 25 ^{5/8}	36 ^{1/4} x 28 ^{3/4} x 25 ^{1/4}	
Mass								
(kg)	71.4kg		72.7kg	70kg		83kg	90kg	
(lbs)	157lbs		160lbs	154lbs		183lbs	203lbs	

- ¹⁾ 1 Vp-p 75 ohms unbalanced, sync negative
²⁾ Y: 1 Vp-p 75 ohms unbalanced, sync negative
C: 0.286 Vp-p (Burst signal), 75 ohms
³⁾ 500 mVrms (100% modulation), Impedance: 47 kilohms
⁴⁾ More than 408 mVrms at the maximum volume setting (variable)

Television system

American TV standard

Channel coverage

VHF:2-13/UHF:14-69/CATV:1-125

Visible screen size

32-inch picture measured (KV-32S40/32S45/32V65/34SL40/34SL40C/34SL40T/34SL45/32V40/34VL65/34VL65C)

35-inch picture measured (KV-35S40/35S45/37SL45/35V65/37VL65/37VL65C)

Actual screen size

34-inch picture measured (KV-32S40/32S45/32V65/34SL40/34SL40C/34SL40T/34SL45/32V40/34VL65/34VL65C)

37-inch picture measured (KV-35S40/35S45/37SL45/35V65/37VL65/37VL65C)

Antenna

75 ohm external terminal for VHF/UHF

Supplied Accessories

Remote commander (w/2 size AA (R6) batteries)

RM-Y165: (KV-32S40/32S45/34SL40/34SL40T/34SL40C/35S40/32V40)

RM-Y167: (KV-34SL45/35S45/37SL45/32V65/34VL65/
34VL65C/35V65/37VL65/37VL65C)

Optional Accessory

Connecting Cables: VMC-810S/820S

VMC-720M,YC-15V/30V,RK-74A

TV-Stand: SU-32A3,SU-35A3

VHF/UHF Mixer: EAC-66

(●)[®] SRS (SOUND RETRIEVAL SYSTEM)

The (●) SRS (SOUND RETRIEVAL SYSTEM) is manufactured by Sony Corporation under license from SRS Labs, Inc. It is covered by U.S. Patent No. 4,748,669. Other U.S. and foreign patents pending.

The word 'SRS' and the SRS symbol (●) are registered trademarks of SRS Labs, Inc.

BBE and BBE symbol are trademarks of BBE Sound, Inc. and are licensed by BBE Sound, Inc. under USP 4638258 and USP 4482866.

Design and specifications are subject to change without notice.

TABLE OF CONTENTS

<i>Section</i>	<i>Title</i>	<i>Page</i>	<i>Section</i>	<i>Title</i>	<i>Page</i>
1. GENERAL					
	Connecting and Installing the TV	5		• A Board.....	35
	Operating Video Equipment.....	7		• AV Board.....	48
	Operating a Cable Box or DBS Receiver.....	8		• B Board	48
	Troubleshooting.....	8		• C Board	51
2. DISASSEMBLY				• G Board	52
	2-1.Rear Cover Removal	9		• HV Board.....	55
	2-2.Chassis Assembly Removal	10		• HS Board	55
	2-3.Service Position	10		• K Board.....	56
	2-4.Control Switch Removal	10		• P Board.....	57
	2-5-1. Picture Tube Removal (32"/34").....	11		• WB Board.....	58
	2-5-2. Picture Tube Removal (35"/37").....	11		• UV Board.....	59
				• WA Board.....	63
3. SET-UP ADJUSTMENTS			6-5.Semiconductors.....		65
	3-1.Beam Landing.....	12	7. EXPLODED VIEWS		
	3-2.Convergence.....	13		7-1. Chassis	66
	3-3.Focus.....	14		(KV-32S40/34SL40/34SL40C/32S45/34SL45/34SL40T)	
	3-4.Screen (G2).....	14		7-2. Chassis.....	67
	3-5.White Balance Adjustments.....	14		(KV-35S40/35S45/37SL45)	
4. SAFETY RELATED ADJUSTMENTS		15		7-3. Chassis.....	68
5. CIRCUIT ADJUSTMENTS		16		(KV-32V40/32V65/34VL65/35VL65C/ 35V65/37VL65/37VL65C)	
6. DIAGRAMS				7-3. Picture Tube	69
	6-1. S Series Block Diagram.....	23		(KV-32V40/32V65/34VL65)	
	6-2. V Series Block Diagrams	27		7-3. Picture Tube	70
	6-3. Circuit Boards Location.....	34		(KV-35VL65C/35V65/37VL65/37VL65C)	
	6-4.Printed Wiring Boards and Schematic Diagrams	34	8. ELECTRICAL PARTS LIST		
				• Table of Contents for Parts List.....	71
				• Parts Listings.....	72

WARNINGS AND CAUTIONS


CAUTION!

AFTER REMOVING THE ANODE, SHORT CIRCUIT THE ANODE OF THE PICTURE TUBE AND THE ANODE CAP TO THE METAL CHASSIS, CRT SHIELD, OR CARBON PAINTED ON THE CRT.

WARNING!!

AN ISOLATION TRANSFORMER SHOULD BE USED DURING ANY SERVICE TO AVOID POSSIBLE SHOCK HAZARD, BECAUSE OF LIVE CHASSIS.THE CHASSIS OF THIS RECEIVER IS DIRECTLY CONNECTED TO THE AC POWER LINE.

SAFETY-RELATED COMPONENT WARNING!!

COMPONENTS IDENTIFIED BY SHADING AND MARK  ON THE SCHEMATIC DIAGRAMS, EXPLODED VIEWS AND IN THE PARTS LIST ARE CRITICAL FOR SAFE OPERATION. REPLACE THESE COMPONENTS WITH SONY PARTS WHOSE PART NUMBERS APPEAR AS SHOWN IN THIS MANUAL OR IN SUPPLEMENTS PUBLISHED BY SONY. CIRCUIT ADJUSTMENTS THAT ARE CRITICAL FOR SAFE OPERATION ARE IDENTIFIED IN THIS MANUAL. FOLLOW THESE PROCEDURES WHENEVER CRITICAL COMPONENTS ARE REPLACED OR IMPROPER OPERATION IS SUSPECTED.


ATTENTION

APRES AVOIR DECONNECTE LE CAP DE L'ANODE, COURT-CIRCUITER L'ANODE DU TUBE CATHODIQUE ET CELUI DE L'ANODE DU CAP AU CHASSIS METALLIQUE DE L'APPAREIL, OU AU COUCHE DE CARBONE PEINTE SUR LE TUBE CATHODIQUE OU AU BLINDAGE DU TUBE CATHODIQUE.

ATTENTION!!

AFIN D'EVITER TOUT RESQUE D'ELECTROCUTION PROVENANT D'UN CHÂSSIS SOUS TENSION, UN TRANSFORMATEUR D'ISOLEMENT DOIT ETRE UTILISÉ LORS DE TOUT DÉPANNAGE. LE CHÂSSIS DE CE RÉCEPTEUR EST DIRECTEMENT RACCORDÉ À L'ALIMENTATION SECTEUR.

ATTENTION AUX COMPOSANTS RELATIFS A LA SECURITE!!

LES COMPOSANTS IDENTIFIES PAR UNE TRAME ET PAR UNE MARQUE  SUR LES SCHEMAS DE PRINCIPE, LES VUES EXPLOSEES ET LES LISTES DE PIECES SONT D'UNEIMPORTANCE CRITIQUE POUR LA SECURITE DU FONCTIONNEMENT. NE LES REMPLACER QUE PAR DES COMPOSANTS SONY DONT LE NUMERO DE PIECE EST INDIQUE DANS LE PRESENT MANUEL OU DANS DES SUPPLEMENTS PUBLIES PAR SONY. LES REGLAGES DE CIRCUIT DONT L'IMPORTANCE EST CRITIQUE POUR LA SECURITE DU FONCTIONNEMENT SONT IDENTIFIES DANS LE PRESENT MANUEL. SUIVRE CES PROCEDURES LORS DE CHAQUE REMPLACEMENT DE COMPOSANTS CRITIQUES, OU LORSQU'UN MAUVAIS FONCTIONNEMENT SUSPECTE.

SAFETY CHECK-OUT

After correcting the original service problem, perform the following safety checks before releasing the set to the customer:

1. Check the area of your repair for unsoldered or poorly-soldered connections. Check the entire board surface for solder splashes and bridges.
2. Check the interboard wiring to ensure that no wires are "pinched" or contact high-wattage resistors.
3. Check that all control knobs, shields, covers, ground straps, and mounting hardware have been replaced. Be absolutely certain that you have replaced all the insulators.
4. Look for unauthorized replacement parts, particularly transistors, that were installed during a previous repair. Point them out to the customer and recommend their replacement.
5. Look for parts which, though functioning, show obvious signs of deterioration. Point them out to the customer and recommend their replacement.
6. Check the line cords for cracks and abrasion. Recommend the replacement of any such line cord to the customer.
7. Check the B+ and HV to see if they are specified values. Make sure your instruments are accurate; be suspicious of your HV meter if sets always have low HV.
8. Check the antenna terminals, metal trim, "metallized" knobs, screws, and all other exposed metal parts for AC Leakage. Check leakage as described below.

LEAKAGE TEST

The AC leakage from any exposed metal part to earth ground and from all exposed metal parts to any exposed metal part having a return to chassis, must not exceed 0.5 mA (500 microampere). Leakage current can be measured by any one of three methods.

1. A commercial leakage tester, such as the Simpson 229 or RCA WT-540A. Follow the manufacturers' instructions to use these instructions.
2. A battery-operated AC milliammeter. The Data Precision 245 digital multimeter is suitable for this job.
3. Measuring the voltage drop across a resistor by means of a VOM or battery-operated AC voltmeter. The "limit" indication is 0.75 V, so analog meters must have an accurate low voltage scale. The Simpson's 250 and Sanwa SH-63Trd are examples of passive VOMs that are suitable. Nearly all battery operated digital multimeters that have a 2V AC range are suitable. (See Fig. A)

HOW TO FIND A GOOD EARTH GROUND

A cold-water pipe is guaranteed earth ground; the cover-plate retaining screw on most AC outlet boxes is also at earth ground. If the retaining screw is to be used as your earth-ground, verify that it is at ground by measuring the resistance between it and a cold-water pipe with an ohmmeter. The reading should be zero ohms. If a cold-water pipe is not accessible, connect a 60-100 watts trouble light (not a neon lamp) between the hot side of the receptacle and the retaining screw. Try both slots, if necessary, to locate the hot side of the line, the lamp should light at normal brilliance if the screw is at ground potential. (See Fig. B)




Fig. A. Using an AC voltmeter to check AC leakage.




Fig B. Checking for earth ground.

SECTION 1 GENERAL

The instructions mentioned here are partial abstracts from the Operating Instruction Manual. The page numbers shown reflect those of the Operating Instruction Manual.

Welcome!

Thank you for purchasing the Sony Trinitron® Color TV. This manual is written for the models listed below. Before reading, check the model number located on the front of this manual or on the rear of your TV.

Model KV-35S45 is used for menu and illustration purposes. Differences in operation are indicated in the text; for example, "KV-35S45 only".

Model Number	Single User CPS required for PIP	Dual User CPS required for PIP	PIP (Ready to Use)	PIP (Ready to Use)	FM/AM/HD Tuner	FM/AM/HD Tuner	FM/AM/HD Tuner	FM/AM/HD Tuner	FM/AM/HD Tuner
KV-32S40									
KV-32S45									
KV-32S65									
KV-32V40									
KV-32V65									
KV-35S40									
KV-35S45									
KV-35S65									
KV-35V65									

Precautions

Safety

- Operate the TV only with 120 V AC.
- The plug is designed, for safety purposes, to fit in the wall outlet only one way. If you are unable to insert the plug fully into the outlet, contact your dealer.
- If any liquid or solid object should fall inside the cabinet, unplug the TV immediately and have it checked by qualified personnel before operating it further.
- If you will not be using the TV for several days, disconnect power by pulling the plug itself. Never pull on the cord.

For details concerning safety precautions, see the supplied leaflet "IMPORTANT SAFEGUARDS".

Installing

- To prevent internal heat build-up, do not block the ventilation openings.
- Do not install the TV in a hot or humid place, or in a place subject to excessive dust or mechanical vibration.

Using This Manual

This manual is divided into four major sections. We recommend that you carefully review the contents of each section in the order presented to ensure that you fully understand the operation of your new TV.

- Connecting and Installing the TV**
This section guides you through your initial set up. It shows how to connect your antenna or cable, and connect any accessories or components.
- Basic Set Up**
This section teaches you the basic skills needed to operate your new TV. It shows you how to operate special functions of the remote control.
- Using your New TV**
This section shows you how to begin using your new TV. It shows how to use the Easy Set Up Guide feature, and how to use your remote control.
- Using your Menus**
This section teaches you how to access on-screen menus and adjust your TV's settings.

Instructions in this manual are written for the remote control. Similar controls may be found on the TV console.

3

Connecting and Installing the TV

Making Connections

Refer to the table below, it will direct you to the diagram suitable to the components you will be connecting.


If you will be connecting	See page
Cable or antenna only	5
Cable and antenna (KV-32S65, 32V65, 35S65, 35V65 only)	5
Cable box	6
Cable box and cable to view scrambled channels (KV-32S65, 32V65, 35S65, 35V65 only)	6
VCR and cable or antenna	7
VCR and cable box	7
Direct Broadcast Satellite Receiver (DBS)	8
VCR and Direct Broadcast Satellite Receiver (DBS)	8
Digital Versatile Disc player (DVD)	9
Audio system	9
A/V receiver	10
Two VCR's for tape editing (KV-32V40, 32V65, 35V65 only)	10
Camcorder to view tapes	11
S-Link connections (KV-32S65, 32V65, 35S65, 35V65 only)	12


4


Cable or Antenna Connections

Connecting directly to cable or an antenna

The connection you choose will depend on the cable found in your home. Newer homes will be equipped with standard coaxial cable (see A); older homes will probably have 300-ohm twin lead cable (see B); still other homes may contain both (see C).

- A
- VHF only or VHF/UHF or Cable
- 

- B
- VHF only or UHF only or VHF/UHF
- 


- C
- VHF and UHF
- 

Cable and antenna

- KV-32S65, 32V65, 35S65, 35V65 only

If your cable provider does not feature local channels, you may find this set up convenient for viewing both local and cable channels.

Select cable or antenna mode by pressing ANT on the remote control. You will be able to alternate between the two input sources.



Note

- In order to receive channels with an antenna, you will need to turn your CABLE to OFF (see page 26) and perform the AUTO PROGRAM function.

5

Connecting and Installing the TV (continued)


Cable Box Connections

Some pay cable TV systems use scrambled or encoded signals that require a cable box to view all channels.

Cable box

- Connect the coaxial connector from your cable to the IN on your cable box.
- Using a coaxial cable, connect OUT on your cable box to VHF/UHF on your TV.

If you will be controlling all channel selection through your cable box, you should consider using the CHANNEL FIX feature discussed on page 26.



Cable box and cable

- KV-32S65, 32V65, 35S65, 35V65 only


For this set up, you can switch between scrambled channels (through your cable box), and normal (CATV) channels by pressing ANT on your remote control.

Notes

- Your Sony remote control can be programmed to operate your cable box. (see page 32)
- When using PIP, you cannot view the AUX input in the window picture.

Tip Pressing ANT switches between these inputs.

If you are connecting a cable box through the AUX input and would like to switch between the AUX and normal (CATV) input you should consider using the CHANNEL FIX feature discussed on page 26.



6

VCR Connections

Connecting an antenna/cable TV system with a VCR

- 1 Attach the coaxial connector from your cable or antenna to IN on your VCR.
- 2 Using A/V connectors, connect AUDIO and VIDEO OUT on your VCR to AUDIO and VIDEO IN on your TV.*
- 3 Using a coaxial connector, connect OUT on your VCR to VHF/UHF on your TV.



* If you are connecting a monaural VCR, connect only the single white audio output to the left input on your TV.

Connecting a VCR and TV with a cable box

You will need a splitter (not supplied) for the following connection.

- 1 Connect the single (input) jack of the splitter to your incoming cable connection. Connect the other two (output) jacks (using coaxial cable) to IN on your cable box and VHF/UHF on your TV.
- 2 Using a coaxial connector, connect OUT on your cable box to IN on your VCR.
- 3 Using A/V connectors, connect AUDIO and VIDEO OUT on your VCR to AUDIO and VIDEO IN on your TV.

Disconnect all power sources before making any connections.



7


Additional Connections

The following connections are for accessories that will enhance your viewing options.

Connecting a DVD Player

- 1 Using A/V connectors, connect LINE OUT on your DVD to VIDEO IN on your TV.


Disconnect all power sources before making any connections.



Connecting an audio system

For enhanced sound, connect your audio system to your TV.

- 1 Using AUDIO connectors, connect AUDIO OUT on your TV to one of the unused line inputs (e.g. TV, AUX, TAPE 2) on your stereo.
- 2 Set your stereo to the chosen line input. Refer to page 24 of this manual for additional audio setup instructions.



9

Connecting and Installing the TV (continued)

DBS Connections

Connecting a DBS (Direct Broadcast Satellite) receiver



- 1 Connect the cable from your satellite antenna to your DBS receiver.
- 2 Attach the coaxial connector from your cable or antenna to VHF/UHF IN on your TV.
- 3 Using A/V connectors, connect AUDIO and VIDEO OUT on your DBS receiver to AUDIO and VIDEO IN on your TV.

Connecting a DBS (Direct Broadcast Satellite) receiver and a VCR

- 1 Connect the cable from your satellite antenna to your DBS receiver.
- 2 Attach the coaxial connector from your cable or antenna to VHF/UHF IN on your VCR.
- 3 Using a coaxial connector, connect VHF/UHF OUT on your VCR to VHF/UHF on your TV.
- 4 Using A/V connectors, connect AUDIO and VIDEO OUT on your DBS receiver to AUDIO and VIDEO IN on your VCR.
- 5 Using A/V connectors, connect AUDIO and VIDEO OUT on your VCR to AUDIO and VIDEO IN on your TV.

8

Disconnect all power sources before making any connections.



Connecting and Installing the TV (continued)

Connecting an A/V receiver


- KV-32V65, 35V65 only

- 1 Using A/V cables, connect TV OUT on your TV to TV IN on your A/V receiver.
- 2 Using a single video connector, connect Monitor OUT on your A/V receiver to VIDEO 1 IN on your TV.

Tip

You may want to use CHANNEL FIX to set your TV's input to the A/V receiver. See page 26.

Disconnect all power sources before making any connections.




Connecting two VCRs

- KV-32V40, 32V65, 35V65 only

MONITOR OUT gives you the ability to use a second VCR to record a program being played by the primary VCR or to perform tape editing and dubbing.

- 1 Connect the VCR intended for playback using the setup instructions on page 7 of this manual.
- 2 Using A/V connectors, connect AUDIO and VIDEO IN on your VCR intended for recording to MONITOR AUDIO and VIDEO OUT on your TV.



10

Connecting a camcorder


This connection is convenient for viewing a picture directly from your camcorder.

Using A/V connectors, connect AUDIO and VIDEO OUT on your camcorder to AUDIO and VIDEO IN on your TV.

Connection can also be made directly to your A/V input located on the rear of your TV.

Note

- If you are connecting a monaural camcorder, connect only the single white audio output to the left input on your TV.



11

Connecting and Installing the TV (continued)

S-Link connections

- KV-32S65, 32V65, 35S65, 35V65 only

S-Link is designed to allow your Sony components to "communicate".

Connecting S-Link to a VCR


S-Link will automatically power on the TV and switch to the correct video input when a tape is inserted in the VCR.

- Using A/V connectors, connect AUDIO and VIDEO OUT on your VCR to AUDIO and VIDEO IN on your TV.
- Using an S-Link connector (mono mini plug), connect S-LINK/CONTROL S-IN on your VCR to S-LINK on your TV.

Connecting S-Link to a DBS

S-Link will automatically power on the TV and switch to the correct video input when you power on the DBS.

- Using A/V connectors, connect AUDIO and VIDEO OUT on your DBS to AUDIO and VIDEO IN on your TV.
- Using an S-Link connector (mono mini plug), connect S-LINK on your DBS to S-LINK on your TV.



12

Operating Video Equipment

Programming the remote

You can use the supplied remote control to operate Sony or non-Sony video equipment.

- Press CODE SET.
- Press VTR/DVD (FUNCTION).
- Use the 0-9 buttons to key in the manufacturer's code number from the following chart.
- Press ENTER.

VCR code numbers

Manufacturer	Code
Sony	301, 302, 303
Admiral (M. Ward)	327
Aiwa	338, 344
Audio Dynamic	314, 337
Broksonic	319, 317
Canon	309, 308
Citizen	332
Craig	302, 332
Criterion	315
Curtis Mathis	304, 338, 309
Daewoo	341, 312, 309
DBX	314, 336, 337
Dimensia	304
Emerson	319, 320, 316, 317, 318, 341
Fisher	330, 335
Funai	338
General Electric	329, 304, 309
Go Video	322, 339, 340
Goldstar	332
Hitachi	306, 304, 305, 338
Instant Replay	309, 308
JC Penney	309, 305, 304, 330, 314, 336, 337
JVC	314, 336, 337, 345, 346, 347
Kenwood	314, 336, 332, 337
LXI (Sears)	332, 305, 330, 335, 338
Magnavox	308, 309, 310
Marantz	314, 336, 337
Marta	332
Memorex	309, 335
Minolta	305, 304
Mitsubishi/MGA	323, 324, 325, 326
Multitech	325, 338, 321
NEC	314, 336, 337
Olympic	309, 308
Optimus	327
Panasonic	308, 309, 306, 307
Pentax	305, 304
Philco	308, 308
Philips	308, 309, 310
Pioneer	308
Quasar	308, 309, 306
RCA/PROSCAN	304, 305, 308, 309, 311, 312, 313, 310, 329
Realistic	309, 330, 328, 335, 324, 338
Sansui	314
Samsung	322, 313, 321
Sanyo	330, 335
Scott	312, 313, 321, 335, 323, 324, 325, 326
Sharp	327, 328
Shintom	315
Signature 2000 (M. Ward)	338, 327
SV2000	338
Sylvania	308, 309, 338, 310
Symphonic	338
Tashiro	332
Tatung	314, 336, 337
Teac	314, 336, 338, 337
Technics	309, 308
Toshiba	312, 311
Wards	327, 328, 335, 331, 332
Yamaha	314, 330, 336, 337
Zenith	331

Operating a VCR Buttons on the remote control

To turn on or off	Press VTR/DVD (POWER).
To select a channel directly	Press the 0 - 9 buttons.
To change channels	Press CH +/-.
To record	Press and simultaneously.
To play	Press .
To stop	Press .
To fast forward	Press .
To rewind the tape	Press .
To pause	Press .
To scan	To resume normal playback, press again or press .
To change input mode	Press TV/VTR.

Tips

- In some rare cases, you may not be able to operate your non-Sony video equipment with the supplied remote control. In this case, please use the equipment's own remote control.
- When you remove the batteries, the code number may revert to the factory setting.
- The code numbers for Sony VCR's are assigned at the factory as follows:

VHS VCR	301
8 mm VCR	302
Beta, ED Beta VCRs	303

MDP (Multi Disc Player) code numbers

Manufacturer	Code
Sony	701
Panasonic	704, 710
Pioneer	702

Operating an MDP Buttons on the remote control

To turn on or off	Press VTR/DVD (POWER).
To play	Press .
To stop	Press .
To pause	Press .
To scan	Press or during playback.
To search the chapter forward or backward	Press CH +/-.

Tip

If you will not be programming a DBS or cable box into the DBS/CABLE input, you can use it to program other video equipment (e.g. DVD, MDP, or second VCR). (see page 30)

DVD (Digital Versatile Disc) code numbers

Manufacturer	Code
Sony	751
Panasonic	753
Pioneer	752
RCA	755
Toshiba	754

Operating a DVD player Buttons on the remote control

To turn on or off	Press VTR/DVD (POWER).
To play	Press .
To stop	Press .
To pause	Press .
To scan	Press or during playback.
To search the chapter forward or backward	Press CH +/-.
To select chapters directly	0-9 + ENTER.
MENU	Press to display DVD menu.
To move cursor in menu	Use your arrow buttons .

Operating a Cable Box or DBS Receiver

Programming the remote

You can program the supplied remote control to operate a cable box or DBS receiver.

- 1 Press CODE SET.
- 2 Press DBS/CABLE (FUNCTION).
- 3 Use the 0-9 buttons to key in the manufacturer's code number from the following chart.
- 4 Press ENTER.

For more details on operating the cable box or DBS receiver

Refer to the operating instructions that were supplied with the equipment.

If the remote control doesn't work

- First, try repeating the setup procedures using the other codes listed for your equipment.

Tips

- If more than one code number is listed, try entering them one by one until you come to the correct code for your equipment.
- If you enter a new code number, the code number you previously entered at that setting is erased.
- In some rare cases, you may not be able to operate your equipment with the supplied remote control. In this case, use the equipment's supplied remote control.
- Whenever you remove the batteries the code numbers may revert to the factory setting.

Cable box code numbers

Manufacturer	Code
Hamlin/Regal	222, 223, 224, 225, 226
Jerrold/G. I.	201, 202, 203, 204, 205, 206, 207, 208, 218
Oak	227, 228, 229
Panasonic	219, 220, 221
Pioneer	214, 215
Scientific Atlanta	209, 210, 211
Tocom	216, 217
Zenith	212, 213

DBS receiver code numbers

Manufacturer	Code
Sony	801 (preset code for remote control)
General Electric	802
Hitachi	805
Hughes	804
Panasonic	803
RCA/PROSCAN	802, 808
Toshiba	806, 807

Troubleshooting

Consult the table below; it suggests solutions to specific problems.

Problem	What it could be	What you can do
Cannot operate single tuner PIP (KV-32SA5, 35SA5)	<ul style="list-style-type: none"> VCR may not be connected to your TV properly. VCR may not be turned on. The remote control may not be programmed to operate the VCR. 	<ul style="list-style-type: none"> Ensure that you have set your VCR correctly. (see page 7) Program your remote control to operate the VCR. (see page 30)
A red light keeps flashing on the TV for more than a few seconds	<ul style="list-style-type: none"> Your TV may need service. 	<ul style="list-style-type: none"> Call your local Sony service center.
TV makes a noise when turned on	<ul style="list-style-type: none"> This is a normal function of your TV. 	
Screen is not lit and there is no sound	<ul style="list-style-type: none"> Power cord may not be plugged in. Batteries may not have been placed with the correct polarity. TV/VIDEO setting may be incorrect. 	<ul style="list-style-type: none"> Press TV/VIDEO until you receive a channel.
Poor or no picture (screen lit), good sound	<ul style="list-style-type: none"> VIDEO menu settings may not be adjusted correctly. Antenna/cable connections may be faulty. VIDEO LABEL inputs may be set to WEB. (This label darkens the screen for ideal WebTV viewing) 	<ul style="list-style-type: none"> Readjust your VIDEO menu settings. (see page 22) Check your VIDEO LABEL settings. (see page 28)
Good picture, no sound	<ul style="list-style-type: none"> Sound may be set to MUTE. Your TV may be set to SAP. Speaker may not be set correctly. 	<ul style="list-style-type: none"> Press MUTE. Check the MTS setting in the AUDIO menu. (see page 23) Check your SPEAKER settings. (see page 23)
No color	<ul style="list-style-type: none"> Color settings may not be adjusted correctly. 	<ul style="list-style-type: none"> Adjust the COLOR settings in the VIDEO menu. (see page 22)


Problem	What it could be	What you can do
Only snow and noise appear on the screen	<ul style="list-style-type: none"> CABLE may not be set correctly in the SET UP menu. Antenna/cable connections may not be correct. TV may be set to AUX mode. 	<ul style="list-style-type: none"> Ensure that you have selected the correct CABLE mode in the SET UP menu. (see page 26) Press ANT on your remote control to change the input mode. (see page 16)
Cannot receive upper channels (UHF) when using an antenna	<ul style="list-style-type: none"> CABLE setting may not be correct in the SET UP menu. 	<ul style="list-style-type: none"> Ensure that CABLE is set to OFF in the SET UP menu. (see page 26) Use AUTO PROGRAM to add receivable channels that are not presently in TV memory. (see page 26)
Cannot receive any channels when using cable	<ul style="list-style-type: none"> CABLE setting may not be set correctly in the SET UP menu. 	<ul style="list-style-type: none"> Ensure that CABLE is set to ON in the SET UP menu. (see page 26) Use AUTO PROGRAM to add receivable channels that are not presently in TV memory. (see page 26)
Cannot gain enough volume when using a cable box	<ul style="list-style-type: none"> Volume may not be adjusted on your cable box. 	<ul style="list-style-type: none"> Press TV (FUNCTION) and adjust the TV's volume.
TV is fixed to one channel	<ul style="list-style-type: none"> CHANNEL FIX settings may not be correct. 	<ul style="list-style-type: none"> Check your CHANNEL FIX settings. (see page 26)

If, after reading these operating instructions, you have additional questions related to the use of your Sony television, please call our Direct Response Center at 1-800-222-SONY (7669). (U.S. residents only)


SECTION 2 DISASSEMBLY

2-1. REAR COVER REMOVAL

(KV-32S40/34SL40/34SL40C/32S45/34SL45/34SL40T/
32V40/32V65/34VL65/34VL65C)




(KV-35S40/35S45/37SL45/37VL65/37VL65C)




2-2. CHASSIS ASSEMBLY REMOVAL


(KV-32S40/34SL40/34SL40C/32S45/
34SL45/35S40/35S45/37SL45/34SL40T)




(KV-32V40/32V65/34VL65/34VL65C/35V65/
37VL65/37VL65C)



2-3. SERVICE POSITION



2-4. CONTROL SWITCH REMOVAL (KV-32V65/34VL65/34VL65C/35VL65/35VL65C/37VL65C)




ANODE-CAP REMOVAL

WARNING: High voltage remains in the CRT even after the power is disconnected. To avoid electrical shock, discharge CRT before attempting to remove the anode cap. Short between anode and coated earth ground strap of CRT.

NOTE: After removing the anode, short circuit the anode of the picture tube and the anode cap to either the metal chassis, CRT shield or carbon painted on the CRT.

REMOVAL PROCEDURES




① Turn up one side of the rubber cap in the direction indicated by arrow (a).

② Use your thumb to pull the rubber cap firmly in the direction indicated by arrow (b).

③ When one side of the rubber cap separates from the anode button, the anode-cap can be removed by turning the rubber cap and pulling it in the direction of arrow (c).

HOW TO HANDLE AN ANODE-CAP

- ① Do not use sharp objects which may cause damage to the surface of the anode-cap.
- ② Do not squeeze the rubber covering too hard to avoid damaging the anode-cap. A material fitting called a shatter-hook terminal is built into the rubber.
- ③ Do not force turn the foot of the rubber cover. This may cause the shatter-hook terminal to protrude and damage the rubber.





2-5-1. PICTURE TUBE REMOVAL (KV-32S40/34SL40/34SL40C/32S45/34SL45/34SL40T/32V40/32V65/34VL65/34VL65C)

WARNING -- Before removing anode cap:

High voltage remains in the CRT even after the power is disconnected.

To avoid electrical shock, discharge CRT before attempting to remove the anode cap. Short between anode and coated earth ground strap of CRT.





2-5-2. PICTURE TUBE REMOVAL (KV-35S40/35S45/37SL45/37VL65/37VL65C)

WARNING -- Before removing anode cap:

High voltage remains in the CRT even after the power is disconnected.

To avoid electrical shock, discharge CRT before attempting to remove the anode cap. Short between anode and coated earth ground strap of CRT.



SECTION 3 SET-UP ADJUSTMENTS

The following adjustments should be made when a complete realignment is required or a new picture tube is installed.

These adjustments should be performed with rated power supply voltage unless otherwise noted.

The controls and switch should be set as follows unless otherwise noted:

PICTURE control normal

BRIGHTNESS control normal

Perform the adjustments in order as follows:

1. Beam Landing
2. Convergence
3. Focus
4. Screen (G2)/White Balance

Note: Test Equipment Required

1. Color Bar Pattern Generator
2. Degausser
3. DC Power Supply
4. Digital Multimeter


3-1. BEAM LANDING

Preparation:


- Input a white pattern signal.
- Face the picture tube in a East or West direction to reduce the influence of geomagnetism.

NOTE: Do not use the hand degausser because it magnetizes the CRT .


1. Input white pattern from pattern generator.
2. Loosen the deflection yoke mounting screw, and set the purity control to the center as shown below:




3. Input green pattern from pattern generator.
4. Move the deflection yoke backward, and adjust with the purity control so that green is in the center and red and blue are even on both sides.



5. Move the deflection yoke forward, and adjust so that the entire screen becomes green.



6. Switch over the raster signal to red and blue and confirm the condition.
7. When the position of the deflection yoke is determined, tighten it with the deflection yoke mounting screw.
8. When landing at the corner is not right, adjust by using the disk magnets.




3-2. CONVERGENCE

Preparation:


- Before starting, perform FOCUS, V. LIN and V. SIZE adjustments.
- Set BRIGHTNESS control to minimum.
- Input dot pattern.

(1) Vertical and Horizontal Static Convergence


1. Adjust V. STAT magnet to converge red, green and blue dots in the center of the screen. (Vertical movement)



Tilt the V. STAT magnet and adjust static convergence to open or close the V. STAT magnet.




2. When the V. STAT magnet is moved in the direction of arrow (a) and (b), red, green, and blue dots move as shown below:



Operation of BMC (Hexapole) Magnet


The respective dot positions resulting from moving each magnet interact, so perform adjustment while tracking.

Use the VSTAT tabs to adjust the red, green, and blue dots so they line up at the center of the screen (move the dots in a horizontal direction.)



Y Separation Axis Correction Magnet Adjustment


1. Input cross-hatch pattern, adjust PICTURE to minimum and BRIGHTNESS to normal.
2. Adjust the deflection yoke upright so it touches the CRT.
3. Adjust so that the Y separation axis correction magnet on the neck assembly is symmetrical from top to bottom (open state).



4. Return the deflection yoke to its original position.

(2) Dynamic Convergence Adjustment


- Before starting, perform Horizontal and Vertical Static Convergence Adjustment.
- Slightly loosen deflection yoke screw.
 - Remove deflection yoke spacers.
 - Move the deflection yoke for best convergence as shown below:



- Tighten the deflection yoke screw.
- Install the deflection yoke spacers.


(3) Screen-corner Convergence

Affix a permalloy assembly corresponding to the misconverged areas:




3-3. FOCUS

Adjust FOCUS control for best picture.



3-4. SCREEN (G2)

- Input dot pattern from the pattern generator.
- Set the PICTURE and BRIGHT controls at normal.
- Adjust S BRT, G CUT, B CUT in service mode with an oscilloscope so that voltages on the red, green, and blue cathodes are 170Vdc for 35"/37" and 180Vdc for 32"/34".
- Observe the screen and adjust SCREEN (G2) VR to obtain the faintly visible background of dot signal.



3-5. WHITE BALANCE ADJUSTMENTS

NO.	Disp.	Item	Avg/32"	Avg/35"
16	GDRV	Green Drive	33	45
17	BDRV	Blue Drive	33	45
18	GCUT	Green Cut-off	3	6
19	BCUT	Blue Cut-off	2	6
23	SBRT	Sub Bright	14	10

- Input an entire white signal.
- Set to Service adjustment Mode.
- Set DCOL to "0"
- Set the PICTURE and BRIGHT to minimum.
- Adjust with SBRT if necessary.
- Select GCUT and BCUT with [1] and [4] .
- Adjust with [3] and [6] for the best white balance.
- Set the PICTURE and BRIGHT to maximum.
- Select GDRV and BDRV with [1] and [4] .
- Adjust with [3] and [6] for the best white balance.
- Reset DCOL to "1".
- Write into the memory by pressing [MUTING] then [ENTER] **.

SECTION 4

SAFETY RELATED ADJUSTMENTS

✦ R530, R531 CONFIRMATION METHOD (HOLD-DOWN CONFIRMATION) AND READJUSTMENTS

Always perform the following adjustments when replacing the following components marked with a ✦ mark on the schematic diagram:

A BOARD: IC351, IC501, D519, D520, D521, C531, C532, R387, R529, R530, R531, R532, R533, R550, T503

G BOARD: IC643, R661

Step 1 Preparation before Confirmation

Turn the POWER switch ON.

Input a white signal and set the PICTURE and BRIGHT controls to maximum.


Confirm that the voltage at the check terminal of TP85 is more than 18.0 V DC when the set is operating normally.

At AC input: 120.0 ± 2.0 VAC
or 220.0 ± 2.0 VAC (for 34SL40C/34VL65C/37VL65C only)

Step 2

Input a white signal and verify that I ABL is within the specified range: 2160 ± 100 μ A.

At AC input: 120.0 ± 2.0 VAC
or 220.0 ± 2.0 VAC (for 34SL40C/34VL65C/37VL65C only)



Step 3


Record the voltage between TP85 and ground.

Step 4

Using an external DC power supply, apply voltage between TP85 and ground.

Increase the voltage gradually and confirm that the holdown works (raster disappears) at lower than the voltage recorded in Step 3.

Lower than 22.05 V DC
At AC input: 120.0 ± 2.0 VAC
or 220.0 ± 2.0 VAC (for 34SL40C/34VL65C/37VL65C only)



A BOARD - CONDUCTOR SIDE

Step 5

Confirm that a voltage of more than 18.0 V DC appears between TP85 and ground.

At AC input: 120.0 ± 2.0 VAC
or 220.0 ± 2.0 VAC (for 34SL40C/34VL65C/37VL65C only)

B+ VOLTAGE CONFIRMATION AND ADJUSTMENT

Always perform the following adjustments when replacing the following components marked with ✦ on the schematic diagram:

G BOARD: IC643, R661

- 1) Using Variac, apply AC input voltage: 130 ± 2.0 VAC (or 220.0 ± 2.0 VAC for 34SL40C/34VL65C/37VL65C only)
- 2) Input a monoscope signal.
- 3) Set the PICTURE control and the BRIGHT control to initial reset value.
- 4) Confirm the voltage of G BOARD CN641 between pin ① to ground is less than 135.5 ± 1.0 V DC.
- 5) If step 4 is not satisfied, replace the R661 and repeat the above steps.

SECTION 5 CIRCUIT ADJUSTMENTS

ELECTRICAL ADJUSTMENT BY REMOTE COMMANDER

Use Remote Commander (RM-Y167) to perform the following circuit adjustments:

NOTE : Test Equipment Required:


1. Pattern Generator
2. Frequency Counter
3. Digital Multimeter
4. Audio OSC

(1) Method of Setting the Service Adjustment Mode

SERVICE MODE PROCEDURE


1. Standby mode. (Power off)
2. [DISPLAY] → [5] → [VOL (+)] → [POWER] on the Remote Commander.
(Press each button within a second.)

SERVICE ADJUSTMENT MODE IN




3. The CRT displays the item being adjusted.
4. Press [1] or [4] on the Remote Commander to select the item.
5. Press [3] or [6] on the Remote Commander to change the data.
6. Press [MUTING] then [ENTER] to write into memory**.

SERVICE ADJUSTMENT MODE MEMORY



7. Press [8] then [ENTER] on the Remote Commander to initialize.




Carry out step 7 when adjusting IDs 0 to 4 and when replacing and adjusting IC002.

8. Turn set off and on to exit. * CAUTION: Wait at least 10 seconds before turning off set.

(2) Memory Write Confirmation Method

1. After adjustment, pull out the plug from the AC outlet, then replace the plug in the AC outlet again.
2. Turn the power switch ON and set to Service Mode.
3. Call the adjusted items again to confirm they were adjusted.

(3) Adjust Buttons and Indicator



**WARNING: Do NOT turn off the power or AC immediately after pressing [MUTING] then [ENTER]. Wait at least 10 seconds.

(4) Service Data

No.	Register Name	Description	Data Range	Adj/Fix	Initial Data	Average Data**					Comments
						32"			35"		
						A	B	C	D	E	
VP CXA2095S											
1	VPOS	V-Position	0-63	Adj	20	23		27			0:Down, 63:Up
2	VSIZ	V-Size	0-63	Adj	20	27		26			0:Min, 63:Max
3	VCOM	V-Compensation	0-3	Fix	1		1				0:Min, 3:Max
4	VLIN	V-Linearity	0-15	Adj	7		9				0:Min, 15:Max
5	VSCO	S-Correction	0-15	Adj	7	6		9			0:Min, 15:Max
6	HPOS	H-Position	0-15	Adj	7	11		10			0:Right, 15:Left
7	HSIZ	H-Size	0-63	Adj	20	23		28			0:Min, 63:Max
8	PAMP	Pin Compensation	0-63	Adj	31	27		24			0:Min, 63:Max
9	UPIN	Upper Corner Pin	0-15	Adj	7	4		7			0:Min, 15:Max
10	LPIN	Lower Corner Pin	0-15	Adj	7	6		10			0:Min, 15:Max
11	PPHA	Pin Phase	0-15	Adj	7	4		5			0:Min(small picture), 15:Max
12	AFC	AFC	0-3	Fix	2		2				0:Freerun, 1:Min, 3:Max
13	VBOW	AFC Bow	0-15	Adj	7	6		5			0:Right, 15:Left
14	VANG	AFC Angle	0-15	Adj	7	6		4			0:Right, 15:Left
15	REF	Reference Line	0-3	Fix	2		2				0:22H(Rch), 3:16H(Rch)
16	GDRV	Green Drive	0-63	Adj	31	22		35			0:Min, 63:Max
17	BDRV	Blue Drive	0-63	Adj	31	30		26			0:Min, 63:Max
18	GCUT	Green Cutoff	0-15	Adj	7	5		8			0:Min, 15:Max
19	BCUT	Blue Cutoff	0-15	Adj	7	7		6			0:Min, 15:Max
20	SCON	Sub Contrast	0-15	Adj	7	10		8			0:Min, 15:Max
21	SHUE	Sub Hue (RF only)	0-15	Adj	7	7 (flat-1)		8 (flat-1)			0:+10deg, 15:-10deg
22	1SHU	Sub Hue (composite & S-video)	0-15	Adj	7	7		7			0:+10deg, 15:-10deg
23	SCOL	Sub Color (RF only)	0-15	Adj	7	11 (flat+2)		9 (flat+2)			0:Min, 15:Max
24	1SCO	Sub Color (composite & S-video)	0-15	Adj	7	14		13			0:Min, 15:Max
25	SBRT	Sub Brightness	0-63	Adj	31		26				0:Min, 63:Max
26	SSHP	Sub Sharpness (RF & Composite video)	0-15	Fix by model	7	8		8			0:Min, 15:Max
27	1SSP	Sub Sharpness (S-video only)	0-15	Fix by model	7	10		10			0:Min, 15:Max
28	GMMA	Gamma Correction	0-3	Fix by model	1	0		0			0:Off, 1:Min, 3:Max
29	CDM2	Countdown Mode 2	0-1	Fix	0		0				0: Normal 1: High Speed Countdown Response
30	EYSW	External Y Switch	0-1	Fix	0		0				0: Normal 1: EYin disabled
31	DPIX	Dynamic Picture	0,1	Fix	1		1				0:Off, 1:On
32	Y-DC	DC Transmission Ratio	0,1	Fix	1		1				0:100%, 1:82%
33	ABLM	ABL Mode	0,1	Fix	1		1				0:PictureABL, 1:Picture/BrightnessABL
34	AXIS	Color Demodulation Axis	0,1	Fix	1		1				0:Japan, 1:US
35	NOTC	Chroma Trap Filter	0,1	Fix	0		0				0:Off, 1:On
36	CROM	Chroma Trap Adjust	0-15	Fix	7		7				0:+300kHz, 1:-300kHz
37	TOT	TOT Filter (RF only)	0,1	Fix	1		1				0:Off, 1:On
38	1TOT	TOT Filter (Composite & S-video)	0,1	Fix	1		0				0:Off, 1:On
39	PREL	Pre/Overshoot Ratio (RF & Composite)	0-3	Fix by model	3		1				0: 2:1, 3: 5:1
40	1PRE	Pre/Overshoot Ratio (S-video only)	0-3	Fix by model	3		3				0: 2:1, 3: 5:1
41	SHPF	Sharpness fo (RF & Composite)	0-3	Fix by model	2		1				0:2.5MHz, 3:4.0MHz
42	1SPF	Sharpness fo (S-video only)	0-3	Fix by model	2		3				0:2.5MHz, 3:4.0MHz
43	RON	Red Off	0,1	Fix	1		1				0:Off, 1:On
44	GON	Green Off	0,1	Fix	1		1				0:Off, 1:On
45	BON	Blue Off	0,1	Fix	1		1				0:Off, 1:On
46	DCOL	Dynamic Color	0,1	Fix	0		1				0:Off, 1:On
47	CDMD	V Countdown Mode	0,1	Fix	0		0				0:Auto, 1:Fix
48	HBSW	H Blanking Switch	0,1	Fix	0		0				0:Off, 1:On
49	LBLK	Left Blanking	0-15	Fix	0		7				0:Min, 15:Max
50	RBLK	Right Blanking	0-15	Fix	0		7				0:Min, 15:Max
AP CXA2021											
51	SVOL	Sub Volume	0-15	Fix	0		6				0:-0 Volume steps, 15:-15 Volume steps
52	SBAL	Sub Balance	0-15	Adj	7		7				0: +Right, 15:+Left
53	SBAS	Sub Bass	0-15	Fix by model	7	10	8	10	8		0:-7 Steps, 15: +8 steps
54	STRE	Sub Treble	0-15	Fix by model	7	7	10	7	10		0:-7 Steps, 15: +8 steps
MM1311/1313											
55	AUSW	Audio Att Sw	0,1	Fix	1		1				0:-6dB, 1:0dB (Only for VIDEO input)

**AVERAGE DATA MODEL GROUPINGS:

32"/34" A: KV-32S40/32S45/34SL40/34SL40C/34SL40T/34SL45 B: KV-32V40 C: KV-32V65/32VL65/34VL65C	35"/37" D: KV-35S40/35S45/37SL45 E: KV-35V65/37VL65/37VL65C
--	--

Service Data (cont.)

No.	Register Name	Description	Data Range	Adj/Fix	Initial Data	Average Data**					Comments
						32"			35"		
						A	B	C	D	E	
PI SDA9288											
56	PYSD	Select Delay	0-15	Fix by P-bd	3	3			0:Right, 15:Left		
57	PIPH	PIP H-position	0-127	Fix	78	78			0:Right, 127:Left		
58	PIPV	PIP V-position	0-63	Fix	18	18			0:Up, 63:Down		
59	PYDL	PIP Y-delay	0-7	Fix	0	0			0:Right, 7:Left		
60	PHDL	H-pulse delay	0-15	Fix by P-bd	3	0			0:Right, 15:Left		
61	PMVD	Main V-pulse delay	0-31	Fix	16	16			7-21: Available (1-6/22-31 Not Avail)		
62	PIVD	Inset V-pulse delay	0-31	Fix	22	22			16-28 Available (1-15/29-31 Not Avail)		
63	PCON	Inset Contrast	0-15	Fix	7	7			0:Min, 15:Max		
64	FRMY	Frame Y	0-15	Fix	7	7			0:Dark, 15:Bright		
65	CHRI	Input Polarity	0,1	Fix by P-bd	1	1			0:+(B-Y)+(R-Y), 1:-(B-Y)-(R-Y)		
66	CHRO	Output Polarity	0,1	Fix	1	1			0:+(B-Y)+(R-Y), 1:-(B-Y)-(R-Y)		
67	IPER	Inset Pedestal R-Y	0-15	Fix	0	0			0:Center, 7:Max, 8:Min		
68	IPEB	Inset Pedestal B-Y	0-15	Fix	0	0			0:Center, 7:Max, 8:Min		
69	PCPS	CLPS Bit Control	0,1	Fix	0	0			0:Depend on HSIDEL, 1:Not depend		
70	PCPF	CLPFIX Bit Control	0,1	Fix	0	0			0: 3Clamp line, 1: 2Clamp line		
71	PSEL	SELDOWN Bit Control	0,1	Fix by P-bd	1	1			0:Open out, 1:TTL out		
72	PPLL	PLL Filter Bits	0-3	Fix	0	0			Fixed value only		
73	PVNR	VSPISQ VSP NR	0-1	Fix	0	1			SDA9288 IC bypass use 1		
IC CXA2019											
74	ISCO	CDec Sub Contrast	0-15	Fix	7	15			PiP sub contrast		
75	ISHP	CDec Sharpness	0-15	Fix	7	8			PiP sharpness		
76	ISCL	CDec Sub Color	0-15	Fix	7	9			PiP sub color		
77	ISHU	CDec Sub Hue	0-15	Fix	7	6			PiP sub hue		
78	ITOT	CDec TOT on	0,1	Fix	0	1			PiP TOT 0:Off, 1:On		
79	IAFC	CDec AFC	0-3	Fix	2	2			0:Max, 2:Min, 3:Freerun		
80	ICD2	CDec Countdown Mode2	0,1	Fix	0	0			0:Standard, 1:Fast		
81	IYDR	CDec Y drive	0-31	Fix	15	7			PiP Y-drive gain		
82	IVPE	CDec V pedestal	0-15	Fix	7	6			PiP V-ped DC		
83	IUPE	CDec U pedestal	0-15	Fix	7	6			PiP U-ped DC		
84	IRVP	CDec RV pedestal	0-15	Fix	7	6			PiP V-ped DC (re-input)		
85	IRUP	CDec RU pedestal	0-15	Fix	7	6			PiP U-ped DC (re-input)		
86	IDCT	CDec DC transfer	0-7	Fix	2	0			PiP DC transfer 0:Max, 7:Min		
87	IRYD	CDec RY drive	0-31	Fix	15	20			PiP RY Drive (re-input)		
88	IABO	CDec ABL off	0,1	Fix	1	1			PiP ABL (RY-OUT) 0:On, 1:Off		
89	IPRE	CDec Pre/Over shoot	0-3	Fix	3	3			PiP Pre/over shoot 0: 1:1, 1: 4:1		
90	IRUD	CDec RU Drive	0-31	Fix	15	20			PiP RU-gain out 0:-6dB, 31:+3.3bD		
91	IABL	CDec ABL	0,1	Fix	1	1			PiP ABL gain 0:Std, 1:Min		
92	IABC	CDec ABL Cent	0-3	Fix	1	1			PiP ABL Center 0:Min, 1:Max		
93	IRVD	CDec RV drive	0-31	Fix	15	17			PiP RY Drive (re-input)		
94	IDLY	CDec Delay	0-3	Fix	0	0			PiP Y-delay 0:0ns, 1:60ns, 2:120ns, 3:180ns		
95	ISCR	CDec SCP BGR	0-3	Fix	0	0			PiP SCP riseup phase 0:+0.4us, 1:cent, 2:-0.8us		
96	ISCF	CDec SCP BGF	0-3	Fix	0	0			PiP SCP falldown phase 0:+0.4us, 1:cent, 2:-0.8us		
CC CXP8584a-011s											
97	CRIL	CC CRI count low	0-15	Fix	2	2			7 Clock Run-In Lower Limit (field 1)		
98	CFLD	CC Caption Fixed Field Count		Fix	5	5			Fixed value only		
99	CCDI	CC CCD int	0-7	Fix	3	3			Fixed value only		
100	CRIP	CC CRI & polarity	0-7	Fix	4	4			Fixed value only		
101	CRIT	CC CRI time constant	0-3	Fix	1	1			Fixed value only		
102	CSB1	CC Sync Slice Bias 1	0-3	Fix	3	3			Fixed value only		
103	CSB2	CC Synce Slice Bias 2	0-7	Fix	4	4			Fixed value only		
104	CREP	CC CRI signal end position	0-255	Fix	142	142			Fixed value only		
105	CDSD	CC Data start delay	0-31	Fix	8	8			Fixed value only		
106	CCDS	CC Caption data threshold	0-31	Fix	9	9			Fixed value only		
107	CHMK	CC P8_HMASK	0-63	Fix	42	42			Hmask		
108	CHSY	CC P8_HSYC	0-255	Fix	136	136			Hsync		
109	DISP	TV OSD H Position	0-63	Adj	1	23			0:Off, 1:Left, 63: Right		
110	RTCO	Rotation Coil	0-63	Fix	32	32			Fixed value only		

**AVERAGE DATA MODEL GROUPINGS:

32"/34" A: KV-32S40/32S45/34SL40/34SL40C/34SL40T/34SL45 B: KV-32V40 C: KV-32V65/32VL65/34VL65C	35"/37" D: KV-35S40/35S45/37SL45 E: KV-35V65/37VL65/37VL65C
--	--

Service Data (cont.)

No.	Register Name	Description	Data Range	Adj/Fix	Initial Data	Average Data**					Comments
						32"			35"		
						A	B	C	D	E	
ID MAP											
111	ID-0	ID-0 (Language/Color Systems)	0-255	Fix by model	89	refer to NVM ID Chart					See ID map
112	ID-1	ID-1 (Input/Output Configuration)	0-255	Fix by model	55						See ID map
113	ID-2	ID-2 (Audio)	0-255	Fix by model	175						See ID map
114	ID-3	ID-3 (OSD/Timer/V-chip/Ch Fix)	0-255	Fix by model	0						See ID map
115	ID-4	ID-4 (CC/Spot Killer/etc)	0-255	Fix by model	155						See ID map
116	ID-5	ID-5 (V-series Features/etc)	0-255	Fix by model	141						See ID map
117	ID-6	ID-6 (PiP/Ant Sw related)	0-255	Fix by model	6						See ID map
118	ID-7	ID-7 (Special Models/etc)	0-255	Fix by model	0						See ID map

****AVERAGE DATA MODEL GROUPINGS:**

32"/34" A: KV-32S40/32S45/34SL40/34SL40C/34SL40T/34SL45 B: KV-32V40 C: KV-32V65/32VL65/34VL65C	35"/37" D: KV-35S40/35S45/37SL45 E: KV-35V65/37VL65/37VL65C
--	--

SERVICE IDO 25


Note: Items 1-118 show adjustment order

(5) Feature ID Map

	KV-	DESTINATION	ID-0	ID-1	ID-2	ID-3	ID-4	ID-5	ID-6	ID-7
1	32S40	(US/CND)	89	17	31	10	27	129	0	0
2	32S45	(US/CND)	89	21	31	10	27	129	1	0
3	32V40	(US/CND)	89	23	175	10	27	129	0	0
4	32V65	(CND)	89	55	175	10	27	141	6	0
6	35S40	(US/CND)	89	21	31	10	155	129	6	0
7	35S45	(US/CND)	89	21	31	10	155	129	1	0
8	35V65	(CND)	89	55	175	10	155	141	6	0
9	34SL40C	(E)	25	17	159	74	59	129	0	0
10	34VL65C	(E)	25	55	175	74	59	141	6	0
11	37VL65C	(E)	25	55	175	74	187	141	6	0
12	34SL40	(E)	25	17	159	74	59	129	0	0
13	34SL45	(E)	25	21	159	74	59	129	1	0
14	34VL65	(E)	25	55	175	74	59	141	6	0
15	37SL45	(E)	25	21	159	74	187	129	1	0
16	37VL65	(E)	25	55	175	74	187	14	6	0
17	34SL40T	(TAIWAN)	9	17	159	10	27	129	0	0

SUB BRIGHT ADJUSTMENT (SBRT)

1. Set to Service adjustment Mode.
2. Input a gray scale pattern signal.
3. Set the PICTURE to minimum, and BRIGHT to normal.
4. Select SBRT with **[1]** and **[4]**.
5. Adjust SUB BRIGHT level with **[3]** and **[6]** so that the stripe second from the right is faintly visible.
6. Write into the memory by pressing **[MUTING]** then **[ENTER]****.




SUB CONTRAST ADJUSTMENT (SCON)


1. Input a color-bar signal.
2. Set to Service adjustment Mode.
3. Select the item DCOL to "0" level.
4. Set the conditions as follows.

PICTURE MAX
COLOR MIN
BRIGHT CENTER

R ON ON (1)
G ON OFF (0)
B ON OFF (0)



5. Connect an oscilloscope probe to C Board, CN1761 pin ① (RED OUT).
6. Select SCON with **[1]** and **[4]**.
7. Adjust with **[3]** and **[6]** for: 2.10 ± 0.01 Vp-p.



8. Reset the item DCOL to "1" level.
9. Write the memory by pressing **[MUTING]** then **[ENTER]****.


10. Return the following back to normal after adjustment.

PICTURE MAX
COLOR CENTER
BRIGHT CENTER

R ON ON (1)
G ON ON (1)
B ON ON (1)


DISPLAY POSITION ADJUSTMENT (DISP)

1. Input a color-bar signal.
2. Set to Service adjustment Mode.
3. Select DISP with **[1]** and **[4]**.
4. Adjust with **[3]** and **[6]** for adjustment of characters to center.
5. Write the memory by pressing **[MUTING]** then **[ENTER]****.



SUB HUE, SUB COLOR ADJUSTMENT (SHUE, SCOL)

1. Input a color-bar signal.
2. Set to Service adjustment Mode.
3. Connect oscilloscope probe to C Board, CN1761 Pin③ (BLUE OUT).
4. Select SHUE and SCOL with **[1]** and **[4]**.
5. Adjust with **[3]** and **[6]** for the $V1 = V4 \pm 0.1$ Vp-p (SCOL) and $V2 = V3 \pm 0.1$ Vp-p (SHUE).



6. Change data according to the following table;

	SCOL	SHUE
32"	+2 steps	-1 steps
35"	+2 steps	-1 steps


7. Write into the memory by pressing **[MUTING]** then **[ENTER]****.

****WARNING:** Do NOT turn off the power or AC immediately after pressing **[MUTING]** then **[ENTER]**. Wait at least 10 seconds.

V. SIZE ADJUSTMENT (VSIZ)


1. Input a cross-hatch signal.
2. Set to Service adjustment mode.
3. Select VSIZ with **[1]** and **[4]**.
4. Adjust with **[3]** and **[6]** for the best vertical size.
5. Write into the memory by pressing **[MUTING]** then **[ENTER]****.

V. SIZE

**V. POSITION ADJUSTMENT (VPOS)**


1. Input a cross-hatch signal.
2. Set to Service adjustment Mode.
3. Select VPOS with **[1]** and **[4]**.
4. Adjust with **[3]** and **[6]** for the best vertical center.
5. Write into the memory by pressing **[MUTING]** then **[ENTER]****.

V. POSITION

**H. POSITION ADJUSTMENT (HPOS)**


1. Input a cross-hatch signal.
2. Set the Service adjustment Mode.
3. Select HPOS with **[1]** and **[4]**.
4. Adjust with **[3]** and **[6]** for the best horizontal center.
5. Write into the memory by pressing **[MUTING]** then **[ENTER]****.

H. POSITION


**V LINEARITY (VLIN), V CORRECTION (VSCO), PIN AMP (PAMP) AND PIN PHASE (PPHA) ADJUSTMENTS**

1. Input a cross-hatch signal.
2. Set to Service adjustment Mode.
3. Select VLIN, VSCO, PAMP, and PPHA with **[1]** and **[4]**.
4. Adjust with **[3]** and **[6]** for the best picture.
5. Write the memory by Pressing **[MUTING]** then **[ENTER]****.


V LINEARITY (VLIN)




VS CORRECTION (VSCO)



PIN AMP (PAMP)




PIN PHASE (PPHA)


**V ANGLE (VANG), V BOW (VBOW), UPPER PIN (UPIN) AND LOW PIN (LPIN) ADJUSTMENTS**

1. Input a cross hatch signal.
2. Set to Service adjustment Mode.
3. Select VVANG, VBOW, UPIN, and LPIN with **[1]** and **[4]**.
4. Adjust with **[3]** and **[6]** for the best picture.
5. Write the memory by Pressing **[MUTING]** then **[ENTER]****.


V ANGLE (VANG)




V BOW (VBOW)



UPPER PIN (UPIN)




LOW PIN (LPIN)

**P BOARD ADJUSTMENTS****PIP V. POSITION (PIPV), PIP H. POSITION (PIPH)**

1. Input a color bar signal.
2. Set to service adjustment mode.
3. Select PHOP with **[1]** and **[4]**.
4. Adjust with **[3]** and **[6]** for the best balanced position at four corner P in P display position.
5. Adjust P in P put at lower right position.
6. Write the memory by Pressing **[MUTING]** then **[ENTER]****.

6-3. CIRCUIT BOARDS LOCATION



6-4. PRINTED WRING BOARDS AND SCHEMATIC DIAGRAMS

- All capacitors are in μF unless otherwise noted. pF : μF 50VV or less are not indicated except for electrolytics and tantalums.
- All electrolytics are in 50V unless otherwise specified.
- All resistors are in ohms.
 $\text{K}\Omega=1000\Omega$, $\text{M}\Omega=1000\text{K}\Omega$
- Indication of resistance, which does not have one for rating electrical power, is as follows.

Pitch : 5mm
 Rating electrical power : $\frac{1}{4}\text{W}$

- $\frac{1}{4}\text{W}$ in resistance, $\frac{1}{10}\text{W}$ and $\frac{1}{8}\text{W}$ in chip resistance.
- : nonflammable resistor.
- : fusible resistor.
- Δ : internal component.
- : panel designation and adjustment for repair.
- All variable and adjustable resistors have characteristic curve B, unless otherwise noted.
- The components identified by in this basic schematic diagram have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation.
 Should replacement be required, replace only with the value originally used.
- When replacing components identified by , make the necessary adjustments indicated. If results do not meet the specified value, change the component identified by and repeat the adjustment until the specified value is achieved. (Refer to R530 and R531 adjustment on Page 15.)
- When replacing the part in below table, be sure to perform the related adjustment.
- Readings are taken with a color-bar signal input.
- Readings are taken with a $10\text{M}\Omega$ digital multimeter.
- Voltages are DC with respect to ground unless otherwise noted.
- Voltage variations may be noted due to normal production tolerances.

Part replaced()	Adjustment()
IC351,IC501,D519,D520,D521 C531,C532,R387,R529,R530,R531, R532,R533,R550,T503.....A BOARD IC643,R661.....G BOARD	R530,R531


- All voltages are in V.
- S : Measurement impossibility.
- : B+line.
- : B-line.
- (Actual measured value may be different).
- : signal path. (RF)
- Circled numbers are waveform references.


Reference information

RESISTOR	: RN	METAL FILM
	: RC	SOLID
	: FPRD	NONFLAMMABLE CARBON
	: FUSE	NONFLAMMABLE FUSIBLE
	: RW	NONFLAMMABLE WIREWOUND
	: RS	NONFLAMMABLE METAL OXIDE
	: RB	NONFLAMMABLE CEMENT
	:	ADJUSTMENT RESISTOR
COIL	: LF-8L	MICRO INDUCTOR
CAPACITOR	: TA	TANTALUM
	: PS	STYROL
	: PP	POLYPROPYLENE
	: PT	MYLAR
	: MPS	METALIZED POLYESTER
	: MPP	METALIZED POLYPROPYLENE
	: ALB	BIPOLAR
	: ALT	HIGH TEMPERATURE


The symbol display is on the component side.
 The components identified by shading and mark are critical for safety. Replace only with part number specified.
 The symbol indicate fast operating fuse.
 Replace only with fuse of same rating as marked.


Les composants identifiés par un tramé et une marque sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.
 Le symbole indique une fusible a action rapide. Doit être remplacée par une fusible de même valeur, comme marqué.






MICON
YIC/J
TUNER
VOL-CTL
AUDIO-AMP
PIN-MOD
V.DEF
H.DEF
AV-SW









FOR KV-
34VL65C, 32VL65CNA,
34VL65, 33VL65CNA,
37VL65, 37VL65C
ONLY

FOR KV-
32V40,
34VL65C, 32VL65CND,
34VL65, 35VL65CNA,
37VL65, 37VL65C
ONLY

FOR KV-
32S40CNB, 34SL40,
34SL40C, 32S45,
34SL45, 35S40,
35S45, 37SL45,
34SL40T
ONLY

1	2-BET
2	2-L
3	2-R
4	E
5	M-IN1
6	M-IN3
7	M-OUT
8	E
9	E
10	STBY 5V
11	9V
12	
13	
14	2-BET
15	2-L
16	2-R
17	E
18	M-IN1
19	M-IN3
20	M-OUT
21	9V
22	FSC
23	E
24	Y OUT
25	E
26	C OUT
27	E
28	V OUT
29	
30	
31	
32	
33	
34	
35	
36	
37	
38	
39	
40	
41	
42	
43	
44	
45	
46	
47	
48	
49	
50	
51	
52	
53	
54	
55	
56	
57	
58	
59	
60	
61	
62	
63	
64	
65	
66	
67	
68	
69	
70	
71	
72	
73	
74	
75	
76	
77	
78	
79	
80	
81	
82	
83	
84	
85	
86	
87	
88	
89	
90	
91	
92	
93	
94	
95	
96	
97	
98	
99	
100	





1

2

3

4

5

A

B

C

D

E

TO HS BOARD
CN2102

JW2231
JUMPER (20MM)

7 E
FRONT C JW2232
JUMPER (20MM)

8 FRONT Y JW2233
JUMPER (20MM)

4 FRONT-SW JW2235
JUMPER (20MM)

6 FRONT V JW2234
JUMPER (20MM)

3 FRONT L JW2236
JUMPER (20MM)

2 FRONT R JW2238
JUMPER (20MM)

1 E JW2237
JUMPER (20MM)

7 E JW2231
JUMPER (20MM)

8 FRONT Y JW2233
JUMPER (20MM)

4 FRONT-SW JW2235
JUMPER (20MM)

6 FRONT V JW2234
JUMPER (20MM)

3 FRONT L JW2236
JUMPER (20MM)

2 FRONT R JW2238
JUMPER (20MM)

1 E JW2237
JUMPER (20MM)

PIN JACL (L TYPE)
FRONT
VIDEO2

R2010
220
:CHIP

R2009
220
:CHIP

R2008
220
:CHIP

R2007
220
:CHIP

R2006
220
:CHIP

R2005
220
:CHIP

R2004
220
:CHIP

R2003
220
:CHIP

R2002
220
:CHIP

R2001
220
:CHIP

STBY 5V

IC2003
SBX1981-S1
REMOTE
SENSOR

C2068
100
25V

C2067
100
25V

C2066
100
25V

C2065
100
25V

C2064
100
25V

C2063
100
25V

C2062
100
25V

C2061
100
25V

C2060
100
25V

C2059
100
25V

C2058
100
25V

C2057
100
25V

C2056
100
25V

C2055
100
25V

C2054
100
25V

TO HS BOARD
CN2101

SIRCS JW2001
JUMPER (20MM)

STBY 5V JW2002
JUMPER (20MM)

TIMER LED JW2006
JUMPER (20MM)

ST LED JW2007
JUMPER (20MM)

POWER ON JW2004
JUMPER (20MM)

KEY JW2003
JUMPER (20MM)

E JW2008
JUMPER (20MM)

3 KEY


2 E

1 POWER ON

CN2002
:S-MICRO


TO C.T PANEL

HV [MICON-CTL]



6-5. SEMICONDUCTORS

DTC114EK
2SC1623-L5L6
2SA1330-06
2SA1162-G
2SD601A-Q




2SC3209LK




2SA1837
2SC4159-E




2SA1175-HFE
2SC2785-HFE




2SD2144S-V




IRF614




MX0841




2SK2845-LB102




2SC5148




ERC06-15S
ISSI33T-77




D1NS4
D1N20R
MTZJ-3.3
MTZJ-33A
RD10ESB2
RD39ES-B2
RD5.6ESB2
RD6.2ESB2




D2L20U
EL1Z
EZD150AV1
GP08D
MTZJ-T-77-4.3C
EGP20G




2SC4834M




EGP30D
ERD29-08J




D10SBS4F




D4SB60L
D1NL40-TA2




D10SC4M



U05G



D1NL20U



SECTION 7 EXPLODED VIEW


- Items with no part number and no description are not stocked because they are seldom required for routine service.
- The component parts of an assembly are indicated by the reference numbers in the remarks column.
- Items marked with an asterisk " * " are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.

The components identified by shading and "Δ" are critical for safety. Replace only with specified part number.

Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

7-1. CHASSIS (KV-32S40/34SL40/34SL40C/32S45/34SL45/34SL40T)

- 7-685-648-79 SCREW +BVTP 3X12
- 4-388-477-01 SCREW +BVTP 3X16




REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
1	X-4035-771-1	BEZNET ASSY (KV-32S40/34SL50C/34SL40/34SL40T)	2-4	17 *	A-1316-389-A	G BOARD, COMPLETE (KV-32S40/34SL40/32S45/34SL45)	
1	X-4035-772-1	BEZNET ASSY (KV-32S45/34SL45)	2-4	17 *	A-1316-395-A	G BOARD, COMPLETE (KV-34SL40C)	
2	4-046-160-11	EMBLEM (NO.9), SONY		17 *	A-1316-396-A	G BOARD, COMPLETE (KV-34SL40T)	
3	4-063-573-01	BUTTON, MULTI		18 Δ	1-751-059-11	CORD, POWER (W/CONNECTOR)	
4	4-063-570-01	GUIDE, LED		19 Δ	1-453-207-11	TRANSFORMER, FBT ASSY NX-2609//X4C	
5	1-504-531-11	SPEAKER (13.1X6.2CM)		20	4-064-530-01	CLIP, CHASSIS (KV-32S45/34SL45)	
6 *	A-1372-519-A	HS BOARD, COMPLETE (KV-32S45/34SL45)		21 *	A-1135-950-A	B, BOARD COMPLETE	
7 Δ	8-733-756-05	CRT 34FX2T (A80JYV52X) (KV-34SL40C)		22	1-766-374-11	PLUG, F-PIN	
7 Δ	8-733-757-05	CRT 34FX2T (A80JYV52X) (FOR N.A. AREA) (KV-32S40/32S45/34SL40/34SL45/34SL40T)		23 Δ	8-598-431-00	FSS TUNER, BTF-WA411 (EXCEPT KV-34SL40T)	
8 Δ	8-451-482-21	DY Y34FXA2-X		23 Δ	8-598-477-00	FSS TUNER, BTF-WG411 (KV-34SL40T ONLY)	
9	4-053-005-01	SPACER, DY		24 *	A-1195-138-A	P BOARD, COMPLETE (KV-32S45/34SL45)	
10 Δ	1-452-579-21	NECK ASSY		25 *	A-1298-661-A	A BOARD, COMPLETE (KV-34SL40T)	
11 *	A-1372-508-A	WB BOARD, MOUNTED		25 *	A-1298-630-A	A BOARD, COMPLETE (KV-32S40/34SL40/34SL40C)	
12 *	A-1331-837-A	C BOARD, COMPLETE		25 *	A-1298-631-A	A, BOARD COMPLETE (KV-32S45/34SL45)	
13	4-036-329-01	SPRING (B) TENSION		26	4-063-852-01	COVER, REAR (KV-32S40/34SL40/34SL40C/34SL40T)	
14	4-041-268-01	SCREW (7), TAPPING		26	4-064-760-01	COVER, REAR (KV-32S45/34SL45)	
15 Δ	1-402-952-11	COIL, DEMAGNETIC		27	1-452-885-11	MAGNET, LANDING	
16 *	4-371-629-01	STOPPER, WIRE		28	4-062-047-01	PIECE A (110), CONV. CORRECT	
				29	3-704-372-31	HOLDER, HV	

The components identified by shading and "Δ" mark are critical for safety. Replace only with specified part number.

Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

7-2. CHASSIS (KV-35S40/35S45/37SL45)

- 7-685-648-79 SCREW +BVTP 3X12
● 4-388-477-01 SCREW +BVTP 3X16




REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
1	X-4035-596-1	BEZNET ASSY (KV-35S40)	2	15 Δ	1-411-882-11	COIL, DEMAGNETIC	
1	X-4035-597-1	BEZNET ASSY (KV-35S45/37SL45)	2	16	4-052-900-02	HOLDER, DGC	
2	4-046-160-01	EMBLEM (NO.9), SONY		17	4-059-585-01	TIE, CABLE (KV-35S40/35S45/37SL45)	
3	4-058-053-11	BUTTON, MULTI		18	4-058-052-21	COVER, REAR	
4	4-058-054-01	BAR, OPTICAL		19 *	A-1316-399-A	G, BOARD, COMPLETE	
5	1-504-531-11	SPEAKER (13.1X6.2CM)		20 Δ	1-751-059-11	CORD, POWER (W/CONNECTOR)	
6 Δ	8-733-761-61	ITC 37GXT-A1	7,8	21 Δ	X-4034-797-1	TRANSFORMER, FBT ASSY NX-3005//J1C	
7 Δ	8-733-761-05	CRT 37GXT		22 *	A-1135-950-A	B, BOARD COMPLETE	
8 Δ	8-451-480-11	DY Y37GXA-X		23	1-766-374-11	PLUG, F-PIN	
9 Δ	8-453-007-11	NA324-M (KV-35S40/35S45/37SL45)		24	8-598-431-00	FSS TUNER, BTF-WA411	
10 *	A-1372-462-A	WA BOARD, MOUNTED		25 *	A-1195-138-A	P BOARD, COMPLETE (KV-35S45/37SL45)	
11	4-046-765-01	SCREW, TAPPING		26 *	A-1298-645-A	A, BOARD COMPLETE (KV-35S40)	
12 *	A-1331-843-A	C BOARD, COMPLETE		26 *	A-1298-646-A	A, BOARD COMPLETE (KV-35S45/37SL45)	
13	4-036-329-01	SPRING (B) TENSION		27 *	A-1372-523-A	HV BOARD, COMPLETE	
14 Δ	1-411-881-11	COIL, DEMAGNETIC		28 *	A-1372-507-A	HS BOARD, COMPLETE	
				29	3-704-372-31	HOLDER, HV	

The components identified by shading and "Δ" mark are critical for safety. Replace only with specified part number.

Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

7-3. CHASSIS (KV-32V40/32V65/34VL65/35VL65C/35V65/37VL65/37VL65C)

- 7-685-648-79 SCREW +BVTP 3X12
- 7-685-663-79 SCREW +BVTP 3X12
- 4-388-477-01 SCREW +BVTP 4X16




REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
1 *	A-1372-510-A	HS BOARD, COMPLETE		15 *	A-1135-948-A	B BOARD, COMPLETE (KV-32V40 ONLY)	
2 *	A-1372-505-A	HV BOARD, COMPLETE (KV-32V40 ONLY)		15 *	A-1135-949-A	B BOARD, COMPLETE (EXCEPT KV-32V40)	
2 *	A-1372-509-A	HV BOARD, COMPLETE (EXCEPT KV-32V40)		16 *	A-1380-585-A	K BOARD, MOUNTED (EXCEPT KV-32V40)	
3 *	A-1298-613-A	A BOARD, COMPLETE					
		(KV-34VL65C/32V65/34VL65)		17 *	A-1316-389-A	G BOARD, COMPLETE (KV-32V40)	
3 *	A-1298-647-A	A BOARD, COMPLETE		17 *	A-1316-390-A	G BOARD, COMPLETE (KV-34VL65C)	
		(KV-35V65/37VL65/37VL65C)		17 *	A-1316-391-A	G BOARD, COMPLETE (KV-32V65/34VL65)	
3 *	A-1298-611-A	A BOARD, COMPLETE (KV-32V40 ONLY)		17 *	A-1316-405-A	G BOARD, COMPLETE (KV-35V65/37VL65)	
				17 *	A-1316-406-A	G BOARD, COMPLETE (KV-37VL65C)	
4 Δ	8-598-431-00	TUNER, FSS BTF-WA411		18 Δ	1-751-059-11	CORD, POWER (WITH CONNECTOR)	
5 Δ	1-453-207-11	TRANSFORMER, FBT ASSY NX-2609//X4C		19	4-052-905-01	V5/6 BRACKET (KV-35V65/37VL65/37VL65C)	
		(KV-32V40/34VL65C/32V65/34VL65)		20	4-052-903-11	COVER, REAR (KV-35V65/37VL65/37VL65C)	
5 Δ	X-4034-797-1	TRANSFORMER, FBT ASSY NX-3005//J1C		20	4-053-766-21	COVER, REAR (KV-32V65/34VL65C/34VL65)	
		(KV-35V65/37VL65/37VL65C)		20	4-053-766-31	COVER, REAR (KV-32V40)	
6 *	A-1195-138-A	P BOARD, COMPLETE (EXCEPT KV-32V40)		21 *	4-052-898-41	LABEL, TERMINAL (EXCEPT KV-32V40)	
7 *	A-1298-612-A	AV BOARD, COMPLETE (EXCEPT KV-32V40)		21 *	4-052-899-31	LABEL, TERMINAL (KV-32V40 ONLY)	
				22	4-374-745-31	CUSHION (A) (KV-32V40/34VL65C/32V65/34VL65)	
8 Δ	8-598-430-00	TUNER, FSS BTF-FA401 (EXCEPT 32V40)		23	X-4035-400-1	BAFFLE ASSY (KV-32V40/34VL65C/32V65/34VL65)	
9 *	1-556-056-01	CABLE, P-P (EXCEPT KV-32V40)		24	1-503-326-21	SPEAKER (8CM) (KV-34VL65C/32V65/34VL65)	
10 *	1-557-945-21	CABLE, P-P (EXCEPT KV-32V40)		24	1-504-524-31	SPEAKER (8CM) (KV-32V40 ONLY)	
11	1-766-374-11	PLUG, F-PIN (KV-32V40 ONLY)					
12	8-598-414-00	ANTENNA SWITCH (KV-35V65/37VL65/37VL65C)		25	X-4035-401-1	COVER ASSY	
						(KV-32V40/34VL65C/32V65/34VL65)	
13 *	A-1394-905-A	UV BOARD, COMPLETE (KV-32V40 ONLY)		26	1-505-684-11	SPEAKER UNIT, BOX TYPE 2 WAY	
13 *	A-1394-906-A	UV BOARD, COMPLETE (EXCEPT KV-32V40)				(KV-35V65/37VL65/37VL65C)	
14	3-696-606-02	HINGE, VI (KV-32V40 ONLY)					

The components identified by shading and "Δ" mark are critical for safety. Replace only with specified part number.

Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

7-4. PICTURE TUBE (KV-32V40/32V65/34VL65)




REF.NO.	PART NO.	DESCRIPTION	REMARK
50	X-4035-591-1	BEZNET ASSY (KV-32V40 ONLY)	51,52
50	X-4035-592-1	BEZNET ASSY (KV-34VL65C/32V65/34VL65)	51,52
51	4-046-160-01	EMBLEM, (NO.9) SONY (KV-32V40 ONLY)	
52	4-052-906-01	DOOR, CONTROL (KV-32V40 ONLY)	
52	4-052-906-11	DOOR, CONTROL (EXCEPT KV-32V40)	
53	1-473-549-21	SWITCH, BLOCK CONTROL (KV-34VL65C/32V65/34VL65)	
54	4-052-907-11	BUTTON, MULTI (KV-32V40 ONLY)	
55 *	4-052-897-01	GUIDE, LED	
56 Δ	8-733-756-05	CRT 34FX2T A80JYV52X (KV-34VL65C)	
56 Δ	8-733-757-05	CRT34FX2T A80JYV52X (KV-32V40/32V65/34VL65)	
57	4-053-005-01	SPACER, DY	
58 Δ	8-451-482-21	DY Y34FXA2-X	
59 Δ	1-452-579-21	NECK ASSY	
60 *	A-1372-508-A	WB BOARD, MOUNTED	
61 *	A-1331-837-A	C BOARD, COMPLETE	
62	4-036-329-01	SPRING (B), TENSION	
63 Δ	1-402-952-11	COIL, DEMAGNETIC	
64	4-371-629-01	STOPPER, WIRE	
65	4-033-681-01	HOLDER, LEAD	
66	4-041-268-01	SCREW (7), TAPPING	
67	1-452-885-11	MAGNET, LANDING	
68	4-062-047-01	PIECE A (110), CORR. CONV.	

The components identified by shading and "Δ" mark are critical for safety. Replace only with specified part number.

Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

7-5. PICTURE TUBE (KV-35VL65C/35V65/37VL65/37VL65C)



REF.NO.	PART NO.	DESCRIPTION	REMARK
100	X-4035-594-1	BEZNET ASSY	101,102
101	4-046-160-01	EMBLEM, (NO. 9), SONY	
102	4-052-906-11	DOOR, CONTROL	
103	1-473-549-21	SWITCH, BLOCK CONTROL	
104	Δ8-733-761-61	ITC 37GXT-A1	105,106
105	Δ8-733-761-05	CRT 37GXT	
106	Δ8-451-480-11	DY Y37GXA-X	
107	4-046-765-01	SCREW, TAPPING	
108	Δ8-453-007-11	NA324-M	
109	* A-1372-462-A	WA BOARD, MOUNTED	
110	* A-1331-843-A	C BOARD, COMPLETE	
111	4-036-329-01	SPRING (B), TENSION	
112	Δ1-411-882-11	COIL, DEMAGNETIC	
113	Δ1-411-881-11	COIL, DEMAGNETIC	
114	* 4-052-900-02	HOLDER, DGC	
115	3-704-372-31	HOLDER, HV	
116	4-052-902-01	CRT SUPPORT (L)	
117	4-052-901-01	CRT SUPPORT (R)	

SECTION 8 ELECTRICAL PARTS LIST

PARTS LISTING TABLE OF CONTENTS

Page

A BOARD <u>COMMON</u> PARTS LIST (S SERIES): Parts common to <u>all</u> models listed in this manual.....	72
A BOARD <u>VARIANT</u> PARTS LIST (S SERIES): Parts that belong <u>only</u> to the model specified.....	80
A BOARD <u>COMMON</u> PARTS LIST (V SERIES): Parts common to <u>all</u> models listed in this manual.....	85
A BOARD <u>VARIANT</u> PARTS LIST (V SERIES): Parts that belong <u>only</u> to the model specified.....	91

Refer to the designated variant parts list when seeking a part indicated by an asterisk (*) on the A board schematic or by the word "variant" on the common parts list.

<u>Model</u>	<u>Page</u>
KV-32S40/34SL40/34SL40C	80
KV-32S45/34SL45	81
KV-35S40	82
KV-35S45/37SL45	83
KV-34SL40T	84
KV-32V40	91
KV-34VL65C/34VL65/32V65CND	92
KV-35V65CND/37VL65/37VL65C.....	93
AV BOARD <u>COMPLETE</u> PARTS LIST (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	94
B BOARD <u>COMPLETE</u> PARTS LIST (All Models).....	95
C BOARD <u>COMPLETE</u> PARTS LIST (All Models)	97
G BOARD <u>COMPLETE</u> PARTS LIST (All Models).....	98
HS BOARD <u>COMPLETE</u> PARTS LIST (KV-32V40/34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C/32S45/34SL45/35S40/35S45/37SL45 only)	101
HV BOARD <u>COMPLETE</u> PARTS LIST (KV-32V40/34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C/35S40/35S45/37SL45 only)	102
K BOARD <u>COMPLETE</u> PARTS LIST (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only).....	104
P BOARD <u>COMPLETE</u> PARTS LIST (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C/32S45/34SL45/35S45/37SL45 only)	105
UV BOARD <u>COMPLETE</u> PARTS LIST (KV-32V40/34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	107
WA BOARD <u>COMPLETE</u> PARTS LIST (KV-35S40/35S45/37SL45/35V65CND/37VL65/37VL65C only)	111
WB BOARD <u>COMPLETE</u> PARTS LIST (KV-32S40/34SL40/34SL40C/32S45/34SL45/32V40/34VL65C/32V65CND/34VL65 only)	113
ACCESSORIES AND PACKAGING (All Models)	114



S SERIES COMMON PARTS LISTING

SECTION 8

ELECTRICAL PARTS LIST (FOR S SERIES)

Note:

The components identified by shading and mark **Δ** are critical for safety. Replace only with part number specified.

Note:

Les composants identifiés par un trame et une marque **Δ** sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

The components identified by **Δ** in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

- Items marked " * " are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.

- All variable and adjustable resistors have characteristic curve B, unless otherwise noted.

RESISTORS

- All resistors are in ohms
- F : nonflammable

CAPACITORS

- MF = μ F

INDUCTORS

- UH = μ H, MMH = mH

When indicating parts by reference number, please include the board name.

REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
A				C069		VARIANT (SEE VARIANT PARTS LIST)	
				C070	1-126-967-11	ELECT 47MF 20%	50V
				C071	1-164-096-11	CERAMIC CHIP 0.01MF	50V
				C072	1-164-161-11	CERAMIC CHIP 0.0022MF	10% 50V
				C075	1-107-823-11	CERAMIC CHIP 0.47MF	10% 16V
				C353	1-163-231-11	CERAMIC CHIP 15PF	5% 50V
				C354	1-163-133-00	CERAMIC CHIP 470PF	5% 50V
				C355	1-126-959-11	ELECT 0.47MF	20% 50V
				C356	1-126-963-11	ELECT 4.7MF	20% 50V
				C357	1-126-959-11	ELECT 0.47MF	20% 50V
				C358	1-163-021-91	CERAMIC CHIP 0.01MF	10% 50V
				C359	1-126-933-11	ELECT 100MF	20% 16V
				C363	1-163-021-91	CERAMIC CHIP 0.01MF	10% 50V
				C364	1-163-021-91	CERAMIC CHIP 0.01MF	10% 50V
				C365	1-163-021-91	CERAMIC CHIP 0.01MF	10% 50V
				C366	1-130-495-00	FILM 0.1MF	5% 50V
				C367	1-130-495-00	FILM 0.1MF	5% 50V
				C368	1-130-495-00	FILM 0.1MF	5% 50V
				C369	1-163-243-11	CERAMIC CHIP 47PF	5% 50V
				C370		VARIANT (SEE VARIANT PARTS LIST)	
				C371	1-163-141-00	CERAMIC CHIP 0.001MF	5% 50V
				C372	1-126-959-11	ELECT 0.47MF	20% 50V
				C373	1-126-960-11	ELECT 1MF	20% 50V
				C375		VARIANT (SEE VARIANT PARTS LIST)	
				C376	1-126-964-11	ELECT 10MF	20% 50V
				C377	1-130-495-00	FILM 0.1MF	5% 50V
				C378	1-130-495-00	FILM 0.1MF	5% 50V
				C379	1-163-021-91	CERAMIC CHIP 0.01MF	10% 50V
				C380	1-126-935-11	ELECT 470MF	20% 16V
				C381	1-163-003-11	CERAMIC CHIP 330PF	10% 50V
				C383	1-130-495-00	FILM 0.1MF	5% 50V
				C385	1-164-182-11	CERAMIC CHIP 0.0033MF	10% 50V
				C386	1-163-021-91	CERAMIC CHIP 0.01MF	10% 50V
				C387	1-126-961-11	ELECT 2.2MF	20% 50V
				C388	1-126-959-11	ELECT 0.47MF	20% 50V
				C390	1-126-960-11	ELECT 1MF	20% 50V
				C391	1-163-017-00	CERAMIC CHIP 0.0047MF	10% 50V
				C392	1-163-251-11	CERAMIC CHIP 100PF	5% 50V
* A-1298-630-A	A BOARD, COMPLETE	(KV-32S40/34SL40/34SL40C only)					
* A-1298-631-A	A BOARD, COMPLETE	(KV-32S45/34SL45 only)					
* A-1298-645-A	A BOARD, COMPLETE	(KV-35S40 only)					
* A-1298-646-A	A BOARD, COMPLETE	(KV-35S45/37SL45 only)					
* A-1298-661-A	A BOARD, COMPLETE	(KV-34SL40T only)					
1-923-513-27	WIRE UL1007 AWG22 180MM GR						
4-382-854-11	SCREW (M3X10), P, SW (+)						
CAPACITOR							
C001	1-163-259-91	CERAMIC CHIP 220PF	5% 50V				
C003	1-104-760-11	CERAMIC CHIP 0.047MF	10% 50V				
C005	1-126-960-11	ELECT 1MF	20% 50V				
C009	1-126-967-11	ELECT 47MF	20% 50V				
C010	1-163-033-91	CERAMIC CHIP 0.022MF	50V				
C012	1-216-033-00	RES, CHIP 220	5% 1/10W				
C013	1-216-121-91	RES, CHIP 1M	5% 1/10W				
C014	1-164-161-11	CERAMIC CHIP 0.0022MF	10% 50V				
C023	1-163-259-91	CERAMIC CHIP 220PF	5% 50V				
C028	1-163-227-11	CERAMIC CHIP 10PF	0.5PF 50V				
C029	1-163-227-11	CERAMIC CHIP 10PF	0.5PF 50V				
C030	1-163-009-11	CERAMIC CHIP 0.001MF	10% 50V				
C035	1-163-237-11	CERAMIC CHIP 27PF	5% 50V				
C036	1-163-231-11	CERAMIC CHIP 15PF	5% 50V				
C037	1-163-243-11	CERAMIC CHIP 47PF	5% 50V				
C038	1-163-243-11	CERAMIC CHIP 47PF	5% 50V				
C039	1-163-243-11	CERAMIC CHIP 47PF	5% 50V				
C040	1-163-243-11	CERAMIC CHIP 47PF	5% 50V				
C051	1-164-004-11	CERAMIC CHIP 0.1MF	10% 25V				
C053	1-163-021-91	CERAMIC CHIP 0.01MF	10% 50V				
C056	1-163-243-11	CERAMIC CHIP 47PF	5% 50V				
C061	1-163-033-91	CERAMIC CHIP 0.022MF	50V				
C062	1-163-033-91	CERAMIC CHIP 0.022MF	50V				
C063	1-126-935-11	ELECT 470MF	20% 16V				
C068		VARIANT (SEE VARIANT PARTS LIST)					

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

S SERIES

COMMON PARTS LISTING



REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
C461	1-126-933-11	ELECT	100MF 20% 16V	C545	1-106-387-00	MYLAR	0.068MF 10% 200V
C462	1-126-961-11	ELECT	2.2MF 20% 50V	C546	1-106-343-00	MYLAR	0.001MF 10% 100V
C463	1-126-961-11	ELECT	2.2MF 20% 50V	C547	1-106-343-00	MYLAR	0.001MF 10% 100V
C464	1-163-017-00	CERAMIC CHIP	0.0047MF 10% 50V	C551	1-163-037-11	CERAMIC CHIP	0.022MF 10% 50V
C466	1-104-666-11	ELECT	220MF 20% 25V	C561	1-126-967-11	ELECT	47MF 20% 50V
C467	1-163-017-00	CERAMIC CHIP	0.0047MF 10% 50V	C563	1-126-934-11	ELECT	220MF 20% 10V
C468	1-104-664-11	ELECT	47MF 20% 25V	C564	1-126-960-11	ELECT	1MF 20% 50V
C470	1-126-961-11	ELECT	2.2MF 20% 50V	C565	1-126-969-11	ELECT	220MF 20% 50V
C471	1-104-666-11	ELECT	220MF 20% 25V	C566	1-126-964-11	ELECT	10MF 20% 50V
C472	1-136-173-00	FILM	0.47MF 5% 50V	C568	1-136-169-00	FILM	0.22MF 5% 50V
C473	1-136-169-00	FILM	0.22MF 5% 50V	C571	1-104-664-11	ELECT	47MF 20% 25V
C474	1-126-942-61	ELECT	1000MF 20% 25V	C1002	1-126-964-11	ELECT	10MF 20% 50V
C475	1-136-169-00	FILM	0.22MF 5% 50V	C1101	1-126-768-11	ELECT	2200MF 20% 16V
C476	1-126-942-61	ELECT	1000MF 20% 25V	C1103	1-126-965-11	ELECT	22MF 20% 50V
C477	1-126-942-61	ELECT	1000MF 20% 25V	C1104	1-104-664-11	ELECT	47MF 20% 16V
C501	1-163-259-91	CERAMIC CHIP	220PF 5% 50V	C1105	1-104-664-11	ELECT	47MF 20% 16V
C502	1-126-959-11	ELECT	0.47MF 20% 50V	C1106	1-126-964-11	ELECT	10MF 20% 50V
C503	1-163-003-11	CERAMIC CHIP	330PF 10% 50V	C1107	1-163-003-11	CERAMIC CHIP	330PF 10% 50V
C504	1-102-212-00	CERAMIC CHIP	820PF 10% 500V	C1108	1-126-960-11	ELECT	1MF 20% 50V
C505	1-102-002-00	CERAMIC CHIP	680PF 10% 500V	C1109	1-126-964-11	ELECT	10MF 20% 50V
C506	1-106-383-00	MYLAR	0.047MF 10% 200V	C1110	1-163-227-11	CERAMIC CHIP	10PF 0.5PF 50V
C507 Δ	1-162-116-00	CERAMIC CHIP	680PF 10% 2KV	C1111	1-163-227-11	CERAMIC CHIP	10PF 0.5PF 50V
C508	1-102-244-00	CERAMIC CHIP	220PF 10% 500V	C1112	1-163-227-11	CERAMIC CHIP	10PF 0.5PF 50V
C509	1-162-116-00	CERAMIC CHIP	680PF 10% 2KV	C1236	1-163-031-11	CERAMIC CHIP	0.01MF 50V
C510	1-137-150-11	MYLAR	0.01MF 10% 100V	C1237	1-136-161-00	FILM	0.047MF 5% 50V
C511 Δ	1-115-460-11	FILM	0.022MF 3% 1.2KV	C1238	1-136-161-00	FILM	0.047MF 5% 50V
C513		VARIANT (SEE VARIANT PARTS LIST)		C1239	1-126-960-11	ELECT	1MF 20% 50V
C514		VARIANT (SEE VARIANT PARTS LIST)		C1240	1-126-960-11	ELECT	1MF 20% 50V
C515	1-106-343-00	MYLAR	0.001MF 10% 100V	C1241		VARIANT (SEE VARIANT PARTS LIST)	
C516	1-115-461-11	FILM	2MF 5% 200V	C1242		VARIANT (SEE VARIANT PARTS LIST)	
C517	1-107-649-11	ELECT	2.2MF 20% 250V	C1243		VARIANT (SEE VARIANT PARTS LIST)	
C518	1-106-395-00	MYLAR	0.15MF 10% 200V	C1244	1-126-959-11	ELECT	0.47MF 20% 50V
C519	1-162-815-11	CERAMIC CHIP	47PF 5% 500V	C1245	1-126-959-11	ELECT	0.47MF 20% 50V
C520		VARIANT (SEE VARIANT PARTS LIST)		C1261	1-104-664-11	ELECT	47MF 20% 16V
C521		VARIANT (SEE VARIANT PARTS LIST)		C1262	1-104-664-11	ELECT	47MF 20% 16V
C522	1-126-960-11	ELECT	1MF 20% 50V	C1263	1-126-960-11	ELECT	1MF 20% 50V
C525	1-102-244-00	CERAMIC CHIP	220PF 10% 500V	C1264	1-126-960-11	ELECT	1MF 20% 50V
C526	1-107-662-11	ELECT	22MF 20% 250V	C1267	1-136-161-00	FILM	0.047MF 5% 50V
C527	1-162-116-00	CERAMIC CHIP	680PF 10% 2KV	C1268	1-126-960-11	ELECT	1MF 20% 50V
C528	1-164-161-11	CERAMIC CHIP	0.0022MF 10% 50V	C1269	1-126-960-11	ELECT	1MF 20% 50V
C529	1-128-551-11	ELECT	22MF 20% 25V	C1293	1-163-251-11	CERAMIC CHIP	100PF 5% 50V
C530	1-137-366-11	FILM	0.0022MF 5% 50V	C1351	1-163-251-11	CERAMIC CHIP	100PF 5% 50V
C531	1-126-965-11	ELECT	22MF 20% 50V	C1352	1-126-933-11	ELECT	100MF 20% 16V
C532	1-126-965-11	ELECT	22MF 20% 50V	C1353	1-163-037-11	CERAMIC CHIP	0.022MF 10% 50V
C537		VARIANT (SEE VARIANT PARTS LIST)		C1354	1-216-295-91	SHORT	
C539		VARIANT (SEE VARIANT PARTS LIST)		C1401	1-126-959-11	ELECT	0.47MF 20% 50V
C540	1-123-024-21	ELECT	33MF 160V	C1402	1-104-664-11	ELECT	47MF 20% 25V
C541	1-128-560-11	ELECT	22MF 20% 100V	C1403	1-126-959-11	ELECT	0.47MF 20% 50V
C542		VARIANT (SEE VARIANT PARTS LIST)		C1404	1-126-956-91	ELECT	0.1MF 20% 50V



S SERIES COMMON PARTS LISTING

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

REF.NO.	PART NO.	DESCRIPTION	REMARK
C1405	1-163-017-00	CERAMIC CHIP 0.0047MF 10% 50V	
C1406	1-126-956-91	ELECT 0.1MF 20% 50V	
C1407	1-163-017-00	CERAMIC CHIP 0.0047MF 10% 50V	
C1408	1-126-963-11	ELECT 4.7MF 20% 50V	
C1409	1-126-963-11	ELECT 4.7MF 20% 50V	
C1410	1-126-956-91	ELECT 0.1MF 20% 50V	
C1411	1-165-319-11	CERAMIC CHIP 0.1MF 50V	
C1413	1-126-963-11	ELECT 4.7MF 20% 50V	
C1415	1-126-964-11	ELECT 10MF 20% 50V	
C1416	1-126-963-11	ELECT 4.7MF 20% 50V	
C1417	1-126-767-11	ELECT 1000MF 20% 16V	
C1420	1-126-963-11	ELECT 4.7MF 20% 50V	
C1501		VARIANT (SEE VARIANT PARTS LIST)	

CONNECTOR

CN270	1-573-298-11	CONNECTOR, BOARD TO BOARD 20P	
CN351 *	1-564-509-11	PLUG, CONNECTOR 6P	
CN461 *	1-564-507-11	PLUG, CONNECTOR 4P	
CN501 *	1-580-798-11	CONNECTOR 6P	
CN503 *	1-564-508-11	PLUG, CONNECTOR 5P	

CN1001		VARIANT (SEE VARIANT PARTS LIST)	
CN1641 *	1-564-515-11	PLUG, CONNECTOR 12P	
CN1941 *	1-564-508-11	PLUG, CONNECTOR 8P	
CN3001		VARIANT (SEE VARIANT PARTS LIST)	

DIODE

D001	8-719-991-33	DIODE 1SS133T-77	
D002	8-719-109-89	DIODE RD5.6ESB2	
D003	8-719-991-33	DIODE 1SS133T-77	
D004	8-719-110-17	DIODE RD10ESB2	
D005		VARIANT (SEE VARIANT PARTS LIST)	

D006		VARIANT (SEE VARIANT PARTS LIST)	
D011	8-719-983-20	DIODE MTZJ-T-77-4.3C	
D013	8-719-991-33	DIODE 1SS133T-77	
D014	8-719-991-33	DIODE 1SS133T-77	
D015	8-719-991-33	DIODE 1SS133T-77	

D353	8-719-991-33	DIODE 1SS133T-77	
D356	8-719-991-33	DIODE 1SS133T-77	
D360	8-719-110-17	DIODE RD10ESB2	
D362	8-719-991-33	DIODE 1SS133T-77	
D368		VARIANT (SEE VARIANT PARTS LIST)	

D462	8-719-991-33	DIODE 1SS133T-77	
D501	8-719-109-89	DIODE RD5.6ESB2	
D502	8-719-945-80	DIODE ERC06-15S	
D503	8-719-945-80	DIODE ERC06-15S	
D504	8-719-900-26	DIODE ERD29-08J	

D505	8-719-908-03	DIODE GP08D	
D506	8-719-908-03	DIODE GP08D	
D507	8-719-991-33	DIODE 1SS133T-77	

REF.NO.	PART NO.	DESCRIPTION	REMARK
D515	8-719-302-43	DIODE EL1Z	
D516	8-719-991-33	DIODE 1SS133T-77	
D518	8-719-991-33	DIODE 1SS133T-77	
D519 Δ	8-719-302-43	DIODE EL1Z	
D520	8-719-991-33	DIODE 1SS133T-77	
D521	8-719-921-63	DIODE MTZJ-7.5B	
D530	8-719-979-85	DIODE EGP20G	
D531	8-719-979-85	DIODE EGP20G	
D534	8-719-302-43	DIODE EL1Z	
D561	8-719-908-03	DIODE GP08D	
D562	8-719-991-33	DIODE 1SS133T-77	
D1102	8-719-982-24	DIODE MTZJ-33A	
D1103	8-719-109-89	DIODE RD5.6ESB2	
D1247	8-719-110-17	DIODE RD10ESB2	
D1248	8-719-981-99	DIODE MTZJ-3.3	

D1261	8-719-110-17	DIODE RD10ESB2	
D1262	8-719-110-17	DIODE RD10ESB2	
D1263	8-719-110-17	DIODE RD10ESB2	
D1264	8-719-110-17	DIODE RD10ESB2	

FERRITE BEAD

FB501	1-410-396-41	FERRITE 0.45UH	
FB502	1-410-397-21	FERRITE 1.1UH	
FB503	1-410-397-21	FERRITE 1.1UH	

IC

IC001	8-752-897-18	IC CXP85840A-011S	
IC002	8-759-527-74	IC M24C02-MN6T	
IC003		VARIANT (SEE VARIANT PARTS LIST)	
IC351	8-752-082-73	IC CXA2095S	
IC461	8-759-980-43	IC TDA2009A	

IC501	8-759-700-07	IC NJM2903M	
IC561	8-759-980-58	IC TDA8172	
IC1261		VARIANT (SEE VARIANT PARTS LIST)	
IC1401	8-752-072-39	IC CXA2021S	
IC1402	8-759-100-96	IC UPC4558G2	

JACK

J1232	1-774-751-11	TERMINAL BLOCK, S	
J1233		VARIANT (SEE VARIANT PARTS LIST)	
J1234	1-774-750-11	JACK BLOCK, PIN	

CHIP CONDUCTOR

JR351		VARIANT (SEE VARIANT PARTS LIST)	
JR352		VARIANT (SEE VARIANT PARTS LIST)	
JR501	1-216-295-91	SHORT	
JR1264		VARIANT (SEE VARIANT PARTS LIST)	
JR1450	1-216-295-91	SHORT	
JR1451	1-216-295-91	SHORT	

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

S SERIES

COMMON PARTS LISTING



REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
JR1454	1-216-295-91	SHORT		Q462	8-729-216-22	TRANSISTOR 2SA1162-G	
JR1455	1-216-295-91	SHORT		Q501	8-729-140-50	TRANSISTOR 2SC3209LK	
JR1801	1-216-295-91	SHORT		Q502 Δ	8-729-035-75	TRANSISTOR 2SC5148(LBSONY)	
JR1802	1-216-295-91	SHORT		Q511 Δ	8-729-422-27	TRANSISTOR 2SD601A-Q	
JR1803	1-216-295-91	SHORT		Q512 Δ	8-729-809-29	TRANSISTOR 2SC4159-E	
JR1804	1-216-295-91	SHORT		Q551	8-729-216-22	TRANSISTOR 2SA1162-G	
JR4120	1-216-295-91	SHORT		Q552	8-729-422-27	TRANSISTOR 2SD601A-Q	
<u>COIL</u>				Q561	8-729-422-27	TRANSISTOR 2SD601A-Q	
L001	1-408-421-00	INDUCTOR 100UH		Q562	8-729-422-27	TRANSISTOR 2SD601A-Q	
L002	1-408-421-00	INDUCTOR 100UH		Q563	8-729-105-08	TRANSISTOR 2SA1330-06	
L003	1-410-470-11	INDUCTOR 10UH		Q1102	8-729-119-78	TRANSISTOR 2SC2785-HFE	
L004	1-410-470-11	INDUCTOR 10UH		Q1103	8-729-422-27	TRANSISTOR 2SD601A-QRS-TX	
L352	1-412-537-31	INDUCTOR 100UH		Q1231	8-729-422-27	TRANSISTOR 2SD601A-Q	
L461	1-408-602-31	INDUCTOR 8.2UH		Q1232	8-729-422-27	TRANSISTOR 2SD601A-Q	
L501 Δ	1-411-976-11	COIL, HORIZONTAL LINEARITY		Q1261	8-729-216-22	TRANSISTOR 2SA1162-G	
L502	1-412-552-11	INDUCTOR 2.2MMH		Q1262	8-729-216-22	TRANSISTOR 2SA1162-G	
L503	1-406-677-11	INDUCTOR		Q1263	8-729-422-27	TRANSISTOR 2SD601A-Q	
L511	1-406-607-41	INDUCTOR		<u>RESISTOR</u>			
L517	1-412-552-11	INDUCTOR 2.2MMH		R001	1-216-045-00	RES, CHIP 680 5% 1/10W	
L541		VARIANT (SEE VARIANT PARTS LIST)		R002	1-247-815-91	CARBON 220 5% 1/4W	
L1101	1-408-421-00	INDUCTOR 100UH		R003	1-216-097-91	RES, CHIP 100K 5% 1/10W	
L1102	1-410-470-11	INDUCTOR 10UH		R004	1-216-121-91	RES, CHIP 1M 5% 1/10W	
L1401	1-410-494-11	INDUCTOR 1MMH		R007	1-216-073-00	RES, CHIP 10K 5% 1/10W	
<u>IC LINK</u>				R009	1-216-073-00	RES, CHIP 10K 5% 1/10W	
PS461 Δ	1-532-984-11	LINK, IC 2A/90V		R010	1-216-037-00	RES, CHIP 330 5% 1/10W	
<u>TRANSISTOR</u>				R011	1-216-065-91	RES, CHIP 4.7K 5% 1/10W	
Q001	8-729-216-22	TRANSISTOR 2SA1162-G		R012		VARIANT (SEE VARIANT PARTS LIST)	
Q002	8-729-422-27	TRANSISTOR 2SD601A-Q		R013	1-216-065-91	RES, CHIP 4.7K 5% 1/10W	
Q003	8-729-422-27	TRANSISTOR 2SD601A-Q		R014	1-216-065-91	RES, CHIP 4.7K 5% 1/10W	
Q004	8-729-216-22	TRANSISTOR 2SA1162-G		R015	1-216-073-00	RES, CHIP 10K 5% 1/10W	
Q010	8-729-422-27	TRANSISTOR 2SD601A-Q		R016	1-216-073-00	RES, CHIP 10K 5% 1/10W	
Q011	8-729-422-27	TRANSISTOR 2SD601A-Q		R019	1-249-425-11	CARBON 4.7K 5% 1/4W	
Q012	8-729-422-27	TRANSISTOR 2SD601A-Q		R020	1-216-065-91	RES, CHIP 4.7K 5% 1/10W	
Q013	8-729-422-27	TRANSISTOR 2SD601A-Q		R022		VARIANT (SEE VARIANT PARTS LIST)	
Q014	8-729-422-27	TRANSISTOR 2SD601A-Q		R023	1-216-089-91	RES, CHIP 47K 5% 1/10W	
Q015	8-729-422-27	TRANSISTOR 2SD601A-Q		R024	1-249-381-11	CARBON 1 5% 1/4W	
Q016	8-729-422-27	TRANSISTOR 2SD601A-Q		R025	1-163-010-11	CERAMIC CHIP 0.0012MF 10% 50V	
Q017	8-729-216-22	TRANSISTOR 2SA1162-G		R026	1-163-038-91	CERAMIC CHIP 0.1MF 25V	
Q301	8-729-216-22	TRANSISTOR 2SA1162-G		R027	1-249-389-11	CARBON 4.7 5% 1/4W	
Q302	8-729-216-22	TRANSISTOR 2SA1162-G		R028	1-249-417-11	CARBON 1K 5% 1/4W	
Q303	8-729-216-22	TRANSISTOR 2SA1162-G		R029	1-216-025-91	RES, CHIP 100 5% 1/10W	
Q354	8-729-422-27	TRANSISTOR 2SD601A-Q		R030	1-249-425-11	CARBON 4.7K 5% 1/4W	
Q356	8-729-216-22	TRANSISTOR 2SA1162-G		R031		VARIANT (SEE VARIANT PARTS LIST)	
Q357	8-729-422-27	TRANSISTOR 2SD601A-Q		R032	1-247-815-91	CARBON 220 5% 1/4W	
Q358	8-729-422-27	TRANSISTOR 2SD601A-Q		R036	1-216-049-91	RES, CHIP 1K 5% 1/10W	
Q461	8-729-422-27	TRANSISTOR 2SD601A-Q		R037	1-216-049-91	RES, CHIP 1K 5% 1/10W	
				R038	1-216-049-91	RES,CHIP 1K 5% 1/10W	
				R039	1-247-807-31	CARBON 100 5% 1/4W	



S SERIES COMMON PARTS LISTING

REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
R044	1-216-033-00	RES, CHIP	220 5% 1/10W	R133	1-216-039-00	RES, CHIP	390 5% 1/10W
R046	1-247-815-91	CARBON	220 5% 1/4W	R135	1-216-073-00	RES, CHIP	10K 5% 1/10W
R047	1-249-417-11	CARBON	1K 5% 1/4W	R136	1-216-073-00	RES, CHIP	10K 5% 1/10W
R048	1-249-417-11	CARBON	1K 5% 1/4W	R137	1-216-049-91	RES, CHIP	1K 5% 1/10W
R049	1-249-417-11	CARBON	1K 5% 1/4W	R353	1-208-788-11	RES, CHIP	1.8K 0.50% 1/10W
R052	1-216-061-00	RES, CHIP	3.3K 5% 1/10W	R354	1-216-077-00	RES, CHIP	15K 5% 1/10W
R053	1-216-061-00	RES, CHIP	3.3K 5% 1/10W	R355	1-216-033-00	RES, CHIP	220 5% 1/10W
R054	1-216-061-00	RES, CHIP	3.3K 5% 1/10W	R356	1-216-033-00	RES, CHIP	220 5% 1/10W
R055	1-216-097-91	RES, CHIP	100K 5% 1/10W	R358		VARIANT (SEE VARIANT PARTS LIST)	
R056	1-216-033-00	RES, CHIP	220 5% 1/10W	R359		VARIANT (SEE VARIANT PARTS LIST)	
R057	1-249-417-11	CARBON	1K 5% 1/4W	R360		VARIANT (SEE VARIANT PARTS LIST)	
R058	1-216-033-00	RES, CHIP	220 5% 1/10W	R361	1-216-025-91	RES, CHIP	100 5% 1/10W
R059		VARIANT (SEE VARIANT PARTS LIST)		R362	1-216-025-91	RES, CHIP	100 5% 1/10W
R060		VARIANT (SEE VARIANT PARTS LIST)		R363	1-216-025-91	RES, CHIP	100 5% 1/10W
R061		VARIANT (SEE VARIANT PARTS LIST)		R364	1-216-101-00	RES, CHIP	150K 5% 1/10W
R062		VARIANT (SEE VARIANT PARTS LIST)		R365		VARIANT (SEE VARIANT PARTS LIST)	
R063		VARIANT (SEE VARIANT PARTS LIST)		R366	1-216-089-91	RES, CHIP	47K 5% 1/10W
R064	1-216-033-00	RES, CHIP	220 5% 1/10W	R367	1-216-097-91	RES, CHIP	100K 5% 1/10W
R065	1-216-033-00	RES, CHIP	220 5% 1/10W	R368	1-249-441-11	CARBON	100K 5% 1/4W
R066	1-216-033-00	RES, CHIP	220 5% 1/10W	R369	1-216-097-91	RES, CHIP	100K 5% 1/10W
R067	1-216-041-00	RES, CHIP	470 5% 1/10W	R370	1-249-417-11	CARBON	1K 5% 1/4W
R068	1-247-815-91	CARBON	220 5% 1/4W	R371	1-216-053-00	RES, CHIP	1.5K 5% 1/10W
R069		VARIANT (SEE VARIANT PARTS LIST)		R372	1-216-113-00	RES, CHIP	470K 5% 1/10W
R070	1-249-421-11	CARBON	2.2K 5% 1/4W	R373	1-216-073-00	RES, CHIP	10K 5% 1/10W
R071	1-247-815-91	CARBON	220 5% 1/4W	R374		VARIANT (SEE VARIANT PARTS LIST)	
R072	1-216-033-00	RES, CHIP	220 5% 1/10W	R375	1-216-025-91	RES, CHIP	100 5% 1/10W
R073	1-216-033-00	RES, CHIP	220 5% 1/10W	R376	1-216-073-00	RES, CHIP	10K 5% 1/10W
R074	1-216-033-00	RES, CHIP	220 5% 1/10W	R379	1-216-033-00	RES, CHIP	220 5% 1/10W
R075	1-216-033-00	RES, CHIP	220 5% 1/10W	R380	1-247-815-91	CARBON	220 5% 1/4W
R076	1-216-033-00	RES, CHIP	220 5% 1/10W	R381	1-247-815-91	CARBON	220 5% 1/4W
R077	1-216-033-00	RES, CHIP	220 5% 1/10W	R382	1-216-033-00	RES, CHIP	220 5% 1/10W
R078	1-249-417-11	CARBON	1K 5% 1/4W	R383	1-216-049-91	RES, CHIP	1K 5% 1/10W
R079	1-216-033-00	RES, CHIP	220 5% 1/10W	R384	1-216-109-00	RES, CHIP	330K 5% 1/10W
R080	1-216-065-91	RES, CHIP	4.7K 5% 1/10W	R385	1-249-422-11	CARBON	2.7K 5% 1/4W
R081	1-216-025-91	RES, CHIP	100 5% 1/10W	R386		VARIANT (SEE VARIANT PARTS LIST)	
R082	1-216-025-91	RES, CHIP	100 5% 1/10W	R387	1-216-049-91	RES, CHIP	1K 5% 1/10W
R083	1-249-429-11	CARBON	10K 5% 1/4W	R388	1-216-089-91	RES, CHIP	47K 5% 1/10W
R084	1-216-049-91	RES, CHIP	1K 5% 1/10W	R389	1-216-067-00	RES, CHIP	5.6K 5% 1/10W
R085		VARIANT (SEE VARIANT PARTS LIST)		R390	1-216-035-00	RES, CHIP	270 5% 1/10W
R087	1-247-815-91	CARBON	220 5% 1/4W	R391	1-208-810-11	RES, CHIP	15K 0.50% 1/10W
R092	1-249-429-11	CARBON	10K 5% 1/4W	R392	1-216-025-91	RES, CHIP	100 5% 1/10W
R093	1-249-387-11	CARBON	3.3 5% 1/4W	R393	1-216-043-91	RES, CHIP	560 5% 1/10W
R094	1-249-381-11	CARBON	1 5% 1/4W	R394	1-216-059-00	RES, CHIP	2.7K 5% 1/10W
R096	1-216-347-11	METAL	0.68 5% 1W	R395	1-216-061-00	RES, CHIP	3.3K 5% 1/10W
R097	1-216-065-91	RES, CHIP	4.7K 5% 1/10W	R396	1-249-417-11	CARBON	1K 5% 1/4W
R098	1-249-379-11	CARBON	0.68 5% 1/4W	R397	1-249-425-11	CARBON	4.7K 5% 1/4W
R099	1-216-065-91	RES, CHIP	4.7K 5% 1/10W	R461	1-216-065-91	RES, CHIP	4.7K 5% 1/10W
R131	1-216-035-00	RES, CHIP	270 5% 1/10W	R462	1-216-089-91	RES, CHIP	47K 5% 1/10W
R132	1-216-115-00	RES, CHIP	560K 5% 1/10W	R463	1-249-435-11	CARBON	33K 5% 1/4W

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

The components identified by Δ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

S SERIES

COMMON PARTS LISTING



REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
R464	1-216-097-91	RES, CHIP	100K 5% 1/10W	R538	1-247-887-00	CARBON 220K 5% 1/4W	
R465	1-249-413-11	CARBON	470 5% 1/4W	R541		VARIANT (SEE VARIANT PARTS LIST)	
R466	1-249-388-11	CARBON	3.9 5% 1/4W	R542		VARIANT (SEE VARIANT PARTS LIST)	
R467	1-216-069-00	RES, CHIP	6.8K 5% 1/10W	R543	1-249-377-11	CARBON 0.47 5% 1/4W	
R469		VARIANT (SEE VARIANT PARTS LIST)		R546		VARIANT (SEE VARIANT PARTS LIST)	
R470	1-216-077-00	RES, CHIP	15K 5% 1/10W	R547	1-215-457-00	METAL 33K 1% 1/4W	
R471	1-216-069-00	RES, CHIP	6.8K 5% 1/10W	R549	1-215-437-00	METAL 4.7K 1% 1/4W	
R472		VARIANT (SEE VARIANT PARTS LIST)		R550 Δ	1-249-377-11	CARBON 0.47 5% 1/4W	
R473	1-249-398-11	CARBON	27 5% 1/4W	R551 Δ	1-215-873-00	METAL 4.7K 5% 1W	
R474	1-216-077-00	RES, CHIP	15K 5% 1/10W	R552	1-216-069-00	RES, CHIP 6.8K 5% 1/10W	
R475	1-249-430-11	CARBON	12K 5% 1/4W	R553 Δ	1-249-377-11	CARBON 0.47 5% 1/4W	
R476	1-249-430-11	CARBON	12K 5% 1/4W	R554	1-216-057-00	RES, CHIP 2.2K 5% 1/10W	
R477	1-249-398-11	CARBON	27 5% 1/4W	R561	1-216-073-00	RES, CHIP 10K 5% 1/10W	
R478	1-249-418-11	CARBON	1.2K 5% 1/4W	R563 Δ	1-216-351-00	METAL 1.5 5% 1W	
R479	1-249-418-11	CARBON	1.2K 5% 1/4W	R564	1-249-393-11	CARBON 10 5% 1/4W	
R480	1-249-385-11	CARBON	2.2 5% 1/4W	R565 Δ	1-215-890-11	METAL 470 5% 2W	
R481	1-249-385-11	CARBON	2.2 5% 1/4W	R566	1-216-073-00	RES, CHIP 10K 5% 1/10W	
R482	1-249-421-11	CARBON	2.2K 5% 1/4W	R567 Δ	1-249-385-11	CARBON 2.2 5% 1/4W	
R483	1-249-421-11	CARBON	2.2K 5% 1/4W	R568	1-216-073-00	RES, CHIP 10K 5% 1/10W	
R501	1-216-037-00	RES, CHIP	330 5% 1/10W	R569	1-216-073-00	RES, CHIP 10K 5% 1/10W	
R502	1-216-061-00	RES, CHIP	3.3K 5% 1/10W	R570	1-216-097-91	RES, CHIP 100K 5% 1/10W	
R503	1-249-426-11	CARBON	5.6K 5% 1/4W	R571	1-216-081-00	RES, CHIP 22K 5% 1/10W	
R504 Δ	1-215-915-11	METAL	470 5% 3W	R572	1-216-081-00	RES, CHIP 22K 5% 1/10W	
R505	1-249-431-11	CARBON	15K 5% 1/4W	R573	1-216-097-91	RES, CHIP 100K 5% 1/10W	
R506	1-215-861-00	METAL	47 5% 1W	R574 Δ	1-216-365-00	METAL 0.47 5% 2W	
R507	1-249-401-11	CARBON	47 5% 1/4W	R575	1-216-113-00	RES, CHIP 470K 5% 1/10W	
R508	1-249-427-11	CARBON	6.8K 5% 1/4W	R576	1-216-073-00	RES, CHIP 10K 5% 1/10W	
R509	1-247-750-11	CARBON	680 5% 1/2W	R577	1-216-097-91	RES, CHIP 100K 5% 1/10W	
R510 Δ	1-215-860-11	METAL	33 5% 1W	R578	1-208-784-11	RES, CHIP 1.2K 0.50% 1/10W	
R511		VARIANT (SEE VARIANT PARTS LIST)		R579	1-208-842-11	RES, CHIP 330K 0.50% 1/10W	
R512 Δ	1-215-886-11	METAL	100 5% 2W	R580	1-249-441-11	CARBON 100K 5% 1/4W	
R515		VARIANT (SEE VARIANT PARTS LIST)		R1009		VARIANT (SEE VARIANT PARTS LIST)	
R516	1-216-057-00	RES, CHIP	2.2K 5% 1/10W	R1010		VARIANT (SEE VARIANT PARTS LIST)	
R517	1-249-415-11	CARBON	680 5% 1/4W	R1101	1-216-049-91	RES, CHIP 1K 5% 1/10W	
R518	1-216-073-00	RES, CHIP	10K 5% 1/10W	R1102	1-215-900-11	METAL 22K 5% 2W	
R519	1-249-411-11	CARBON	330 5% 1/4W	R1103	1-216-051-00	RES, CHIP 1.2K 5% 1/10W	
R521 Δ	1-215-915-11	METAL	470 5% 3W	R1104	1-216-083-00	RES, CHIP 27K 5% 1/10W	
R523		VARIANT (SEE VARIANT PARTS LIST)		R1105	1-216-689-11	RES, CHIP 39K 5% 1/10W	
R524	1-249-429-11	CARBON	10K 5% 1/4W	R1106	1-216-049-91	RES, CHIP 1K 5% 1/10W	
R525	1-216-071-00	RES, CHIP	8.2K 5% 1/10W	R1107	1-216-065-91	RES, CHIP 4.7K 5% 1/10W	
R528	1-216-081-00	RES, CHIP	22K 5% 1/10W	R1108	1-216-073-00	RES, CHIP 10K 5% 1/10W	
R529		VARIANT (SEE VARIANT PARTS LIST)		R1109	1-216-019-00	RES, CHIP 56 5% 1/10W	
Δ R530 Δ	1-208-808-11	RES, CHIP	12K 0.50% 1/10W	R1110	1-216-019-00	RES, CHIP 56 5% 1/10W	
R531		VARIANT (SEE VARIANT PARTS LIST)		R1111	1-216-019-00	RES, CHIP 56 5% 1/10W	
R532	1-208-760-11	RES, CHIP	120 0.50% 1/10W	R1115	1-216-045-00	RES, CHIP 680 5% 1/10W	
R533		VARIANT (SEE VARIANT PARTS LIST)		R1117	1-249-425-11	CARBON 4.7K 5% 1/4W	
R535		VARIANT (SEE VARIANT PARTS LIST)		R1118	1-249-425-11	CARBON 4.7K 5% 1/4W	
R536 Δ	1-249-377-11	CARBON	0.47 5% 1/4W	R1120	1-216-057-00	RES, CHIP 2.2K 5% 1/10W	
R537 Δ	1-249-377-11	CARBON	0.47 5% 1/4W	R1121	1-216-035-00	RES, CHIP 270 5% 1/10W	



S SERIES COMMON PARTS LISTING

REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
R1122	1-216-115-00	RES, CHIP	560K 5% 1/10W	R1288	1-247-807-31	CARBON	100 5% 1/4W
R1123	1-216-039-00	RES, CHIP	390 5% 1/10W	R1290	1-216-041-00	RES, CHIP	470 5% 1/10W
R1125	1-216-057-00	RES, CHIP	2.2K 5% 1/10W	R1291	1-216-045-00	RES, CHIP	680 5% 1/10W
R1126	1-216-035-00	RES, CHIP	270 5% 1/10W	R1292	1-216-065-91	RES, CHIP	4.7K 5% 1/10W
R1127	1-216-115-00	RES, CHIP	560K 5% 1/10W	R1293	1-216-065-91	RES, CHIP	4.7K 5% 1/10W
R1128	1-216-039-00	RES, CHIP	390 5% 1/10	R1294	1-216-049-91	RES, CHIP	1K 5% 1/10W
R1130	1-216-057-00	RES, CHIP	2.2K 5% 1/10W	R1295	1-216-049-91	RES, CHIP	1K 5% 1/10W
R1234	1-249-441-11	CARBON	100K 5% 1/4W	R1296		VARIANT (SEE VARIANT PARTS LIST)	
R1240	1-216-022-00	RES, CHIP	75 5% 1/10W	R1297		VARIANT (SEE VARIANT PARTS LIST)	
R1241	1-216-022-00	RES, CHIP	75 5% 1/10W	R1351	1-247-815-91	CARBON	220 5% 1/4W
R1242	1-216-065-91	RES, CHIP	4.7K 5% 1/10W	R1352	1-247-815-91	CARBON	220 5% 1/4W
R1243	1-249-441-11	CARBON	100K 5% 1/4W	R1353	1-247-815-91	CARBON	220 5% 1/4W
R1244	1-216-022-00	RES, CHIP	75 5% 1/10W	R1354	1-216-033-00	RES, CHIP	220 5% 1/10W
R1245	1-216-113-00	RES, CHIP	470K 5% 1/10W	R1355	1-216-025-91	RES, CHIP	100 5% 1/10W
R1246	1-216-065-91	RES, CHIP	4.7K 5% 1/10W	R1356	1-216-025-91	RES, CHIP	100 5% 1/10W
R1247	1-216-113-00	RES, CHIP	470K 5% 1/10W	R1357	1-216-025-91	RES, CHIP	100 5% 1/10W
R1248	1-216-065-91	RES, CHIP	4.7K 5% 1/10W	R1358	1-247-807-31	CARBON	100 5% 1/4W
R1249		VARIANT (SEE VARIANT PARTS LIST)		R1359	1-216-025-91	RES, CHIP	100 5% 1/10W
R1250		VARIANT (SEE VARIANT PARTS LIST)		R1360	1-216-069-00	RES, CHIP	6.8K 5% 1/10W
R1251		VARIANT (SEE VARIANT PARTS LIST)		R1361	1-216-065-91	RES, CHIP	4.7K 5% 1/10W
R1252		VARIANT (SEE VARIANT PARTS LIST)		R1362	1-216-295-91	SHORT	
R1253		VARIANT (SEE VARIANT PARTS LIST)		R1402	1-249-429-11	CARBON	10K 5% 1/4W
R1254	1-216-113-00	RES, CHIP	470K 5% 1/10W	R1404	1-249-429-11	CARBON	10K 5% 1/4W
R1255	1-216-049-91	RES, CHIP	1K 5% 1/10W	R1407	1-216-073-00	RES, CHIP	10K 5% 1/10W
R1256	1-216-113-00	RES, CHIP	470K 5% 1/10W	R1408	1-249-429-11	CARBON	10K 5% 1/4W
R1257	1-216-049-91	RES, CHIP	1K 5% 1/10W	R1409	1-249-429-11	CARBON	10K 5% 1/4W
R1258	1-216-061-00	RES, CHIP	3.3K 5% 1/10W	R1410	1-216-121-91	RES, CHIP	1M 5% 1/10W
R1259	1-216-097-91	RES, CHIP	100K 5% 1/10W	R1411	1-216-073-00	RES, CHIP	10K 5% 1/10W
R1260	1-216-061-00	RES, CHIP	3.3K 5% 1/10W	R1412	1-216-081-00	RES, CHIP	22K 5% 1/10W
R1261	1-216-033-00	RES, CHIP	220 5% 1/10W	R1413	1-216-089-91	RES, CHIP	47K 5% 1/10W
R1262	1-216-025-91	RES, CHIP	100 5% 1/10W	R1414	1-216-089-91	RES, CHIP	47K 5% 1/10W
R1263	1-216-033-00	RES, CHIP	220 5% 1/10W	R1415	1-216-025-91	RES, CHIP	100 5% 1/10W
R1264	1-216-025-91	RES, CHIP	100 5% 1/10W	R1418	1-216-081-00	RES, CHIP	22K 5% 1/10W
R1265	1-216-033-00	RES, CHIP	220 5% 1/10W	R1419	1-216-089-91	RES, CHIP	47K 5% 1/10W
R1266	1-216-025-91	RES, CHIP	100 5% 1/10W	R1420	1-216-089-91	RES, CHIP	47K 5% 1/10W
R1267	1-216-295-91	SHORT		R1421	1-216-025-91	RES, CHIP	100 5% 1/10W
R1268	1-216-025-91	RES, CHIP	100 5% 1/10W	R1424	1-247-815-91	CARBON	220 5% 1/4W
R1270	1-216-025-91	RES, CHIP	100 5% 1/10W	R1425	1-247-815-91	CARBON	220 5% 1/4W
R1273		VARIANT (SEE VARIANT PARTS LIST)					
R1274		VARIANT (SEE VARIANT PARTS LIST)					
R1277	1-247-815-91	CARBON	220 5% 1/4W				
R1278	1-247-815-91	CARBON	220 5% 1/4W				
R1280	1-216-025-91	RES, CHIP	100 5% 1/10W				
R1282	1-216-025-91	RES, CHIP	100 5% 1/10W				
R1283		VARIANT (SEE VARIANT PARTS LIST)					
R1284	1-247-807-31	CARBON	100 5% 1/4W				
R1286	1-216-049-91	RES, CHIP	1K 5% 1/10W				
R1287	1-216-049-91	RES, CHIP	1K 5% 1/10W				

SWITCH

S001		VARIANT (SEE VARIANT PARTS LIST)
S002		VARIANT (SEE VARIANT PARTS LIST)
S003		VARIANT (SEE VARIANT PARTS LIST)
S004		VARIANT (SEE VARIANT PARTS LIST)
S005		VARIANT (SEE VARIANT PARTS LIST)
S006		VARIANT (SEE VARIANT PARTS LIST)
S007		VARIANT (SEE VARIANT PARTS LIST)
S501	1-572-707-11	SWITCH, LEVER



<u>REF.NO.</u>	<u>PART NO.</u>	<u>DESCRIPTION</u>	<u>REMARK</u>	<u>REF.NO.</u>	<u>PART NO.</u>	<u>DESCRIPTION</u>	<u>REMARK</u>
<u>TRANSFORMER</u>							
T501	1-437-210-11	TRANSFORMER, HORIZONTAL DRIVE					
T502		VARIANT (SEE VARIANT PARTS LIST)					
T503		VARIANT (SEE VARIANT PARTS LIST)					
T504		VARIANT (SEE VARIANT PARTS LIST)					
<u>TUNER</u>							
TU102		VARIANT (SEE VARIANT PARTS LIST)					
<u>CRYSTAL</u>							
X001	1-578-774-11	VIBRATOR, CRYSTAL					
X353	1-567-505-11	OSCILLATOR, CRYSTAL					
X354	1-577-611-11	OSCILLATOR, CERAMIC					

ELECTRICAL PARTS LIST (FOR V SERIES)

Note:

The components identified by shading and mark **Δ** are critical for safety. Replace only with part number specified.

Note:

Les composants identifiés par un trame et une marque **Δ** sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

The components identified by **Δ** in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

- Items marked " * " are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.

- All variable and adjustable resistors have characteristic curve B, unless otherwise noted.

RESISTORS

- All resistors are in ohms
- F : nonflammable

CAPACITORS

- MF = μ F

INDUCTORS

- UH = μ H, MMH = mH

When indicating parts by reference number, please include the board name.

REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
<div style="border: 1px solid black; padding: 5px; display: inline-block; font-size: 2em; font-weight: bold; margin-bottom: 10px;">A</div> <p>* A-1298-611-A A BOARD, COMPLETE (KV-32V40 only)</p> <p>* A-1298-613-A A BOARD, COMPLETE (KV-34VL65C/34VL65/32V65CND only)</p> <p>* A-1298-647-A A BOARD, COMPLETE (KV-35V65CND/37VL65/37VL65C only)</p>				C070	1-126-967-11	ELECT	47MF 20% 50V
				C071	1-164-096-11	CERAMIC CHIP	0.01MF 50V
				C072	1-164-161-11	CERAMIC CHIP	0.0022MF 10% 50V
				C075	1-107-823-11	CERAMIC CHIP	0.47MF 10% 16V
				C353	1-163-231-11	CERAMIC CHIP	15PF 5% 50V
4-382-854-11	SCREW (M3X10), P, SW (+)			C354	1-163-133-00	CERAMIC CHIP	470PF 5% 50V
CAPACITOR				C355	1-126-959-11	ELECT	0.47MF 20% 50V
C001	1-163-259-91	CERAMIC CHIP	220PF 5% 50V	C356	1-126-963-11	ELECT	4.7MF 20% 50V
C003	1-104-760-11	CERAMIC CHIP	0.047MF 10% 50V	C357	1-126-959-11	ELECT	0.47MF 20% 50V
C005	1-126-960-11	ELECT	1MF 20% 50V	C358	1-163-021-91	CERAMIC CHIP	0.01MF 10% 50V
C009	1-126-967-11	ELECT	47MF 20% 50V	C359	1-126-933-11	ELECT	100MF 20% 16V
C010	1-163-033-91	CERAMIC CHIP	0.022MF 50V	C363	1-163-021-91	CERAMIC CHIP	0.01MF 10% 50V
C012	1-216-033-00	RES, CHIP	220 5% 1/10W	C364	1-163-021-91	CERAMIC CHIP	0.01MF 10% 50V
C013	1-216-121-91	RES, CHIP	1M 5% 1/10W	C365	1-163-021-91	CERAMIC CHIP	0.01MF 10% 50V
C014	1-164-161-11	CERAMIC CHIP	0.0022MF 10% 50V	C366	1-130-495-00	FILM	0.1MF 5% 50V
C023	1-163-259-91	CERAMIC CHIP	220PF 5% 50V	C367	1-130-495-00	FILM	0.1MF 5% 50V
C028	1-163-227-11	CERAMIC CHIP	10PF 0.5PF 50V	C368	1-130-495-00	FILM	0.1MF 5% 50V
C029	1-163-227-11	CERAMIC CHIP	10PF 0.5PF 50V	C369	1-163-243-11	CERAMIC CHIP	47PF 5% 50V
C030	1-163-009-11	CERAMIC CHIP	0.001MF 10% 50V	C370	1-163-037-11	CERAMIC CHIP	0.022MF 10% 50V
C035	1-163-237-11	CERAMIC CHIP	27PF 5% 50V	C371	1-163-141-00	CERAMIC CHIP	0.001MF 5% 50V
C036	1-163-231-11	CERAMIC CHIP	15PF 5% 50V	C372	1-126-959-11	ELECT	0.47MF 20% 50V
C037	1-163-243-11	CERAMIC CHIP	47PF 5% 50V	C373	1-126-960-11	ELECT	1MF 20% 50V
C038	1-163-243-11	CERAMIC CHIP	47PF 5% 50V	C376	1-126-964-11	ELECT	10MF 20% 50V
C039	1-163-243-11	CERAMIC CHIP	47PF 5% 50V	C377	1-130-495-00	FILM	0.1MF 5% 50V
C040	1-163-243-11	CERAMIC CHIP	47PF 5% 50V	C378	1-130-495-00	FILM	0.1MF 5% 50V
C051	1-164-004-11	CERAMIC CHIP	0.1MF 10% 25V	C379	1-163-021-91	CERAMIC CHIP	0.01MF 10% 50V
C053	1-163-021-91	CERAMIC CHIP	0.01MF 10% 50V	C380	1-126-935-11	ELECT	470MF 20% 16V
C056	1-163-243-11	CERAMIC CHIP	47PF 5% 50V	C381	1-163-003-11	CERAMIC CHIP	330PF 10% 50V
C061	1-163-033-91	CERAMIC CHIP	0.022MF 50V	C383	1-130-495-00	FILM	0.1MF 5% 50V
C062	1-163-033-91	CERAMIC CHIP	0.022MF 50V	C385	1-164-182-11	CERAMIC CHIP	0.0033MF 10% 50V
C063	1-126-935-11	ELECT	470MF 20% 16V	C386	1-163-021-91	CERAMIC CHIP	0.01MF 10% 50V
C069		VARIANT(SEE VARIANT PARTS LIST)		C387	1-126-961-11	ELECT	2.2MF 20% 50V
				C388	1-126-959-11	ELECT	0.47MF 20% 50V
				C390	1-126-960-11	ELECT	1MF 20% 50V
				C391	1-163-017-00	CERAMIC CHIP	0.0047MF 10% 50V
				C392	1-163-251-11	CERAMIC CHIP	100PF 5% 50V
				C461		VARIANT(SEE VARIANT PARTS LIST)	
				C462		VARIANT(SEE VARIANT PARTS LIST)	



V SERIES COMMON PARTS LISTING

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

Les composants identifiés par un triangle et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
C463		VARIANT(SEE VARIANT PARTS LIST)		C542		VARIANT(SEE VARIANT PARTS LIST)	
C464		VARIANT(SEE VARIANT PARTS LIST)		C545	1-106-387-00	MYLAR 0.068MF 10%	200V
C466		VARIANT(SEE VARIANT PARTS LIST)		C546	1-106-343-00	MYLAR 0.001MF 10%	100V
C467		VARIANT(SEE VARIANT PARTS LIST)		C547	1-106-343-00	MYLAR 0.001MF 10%	100V
C468		VARIANT(SEE VARIANT PARTS LIST)		C551	1-163-037-11	CERAMIC CHIP 0.022MF 10%	50V
C470		VARIANT(SEE VARIANT PARTS LIST)		C561	1-126-967-11	ELECT 47MF 20%	50V
C471		VARIANT(SEE VARIANT PARTS LIST)		C563	1-126-934-11	ELECT 220MF 20%	10V
C472		VARIANT(SEE VARIANT PARTS LIST)		C564	1-126-960-11	ELECT 1MF 20%	50V
C473		VARIANT(SEE VARIANT PARTS LIST)		C565	1-126-969-11	ELECT 220MF 20%	50V
C474		VARIANT(SEE VARIANT PARTS LIST)		C566	1-126-964-11	ELECT 10MF 20%	50V
C475		VARIANT(SEE VARIANT PARTS LIST)		C568	1-136-169-00	FILM 0.22MF 5%	50V
C476		VARIANT(SEE VARIANT PARTS LIST)		C571	1-104-664-11	ELECT 47MF 20%	25V
C477		VARIANT(SEE VARIANT PARTS LIST)		C1002	1-126-964-11	ELECT 10MF 20%	50V
C478		VARIANT(SEE VARIANT PARTS LIST)		C1101	1-126-768-11	ELECT 2200MF 20%	16V
C479		VARIANT(SEE VARIANT PARTS LIST)		C1103	1-126-965-11	ELECT 22MF 20%	50V
C501	1-163-259-91	CERAMIC CHIP 220PF 5%	50V	C1104	1-104-664-11	ELECT 47MF 20%	16V
C502	1-126-959-11	ELECT 0.47MF 20%	50V	C1105	1-104-664-11	ELECT 47MF 20%	16V
C503	1-163-003-11	CERAMIC CHIP 330PF 10%	50V	C1106	1-126-964-11	ELECT 10MF 20%	50V
C504	1-102-212-00	CERAMIC CHIP 820PF 10%	500V	C1107	1-163-003-11	CERAMIC CHIP 330PF 10%	50V
C505	1-102-002-00	CERAMIC CHIP 680PF 10%	500V	C1108	1-126-960-11	ELECT 1MF 20%	50V
C506	1-106-383-00	MYLAR 0.047MF 10%	200V	C1109	1-126-964-11	ELECT 10MF 20%	50V
C507 Δ	1-162-116-00	CERAMIC CHIP2 680PF 10%	2KV	C1110	1-163-227-11	CERAMIC CHIP 10PF 0.5PF	50V
C508	1-102-244-00	CERAMIC CHIP 220PF 10%	500V	C1111	1-163-227-11	CERAMIC CHIP 10PF 0.5PF	50V
C509	1-162-116-00	CERAMIC CHIP 680PF 10%	2KV	C1112	1-163-227-11	CERAMIC CHIP 10PF 0.5PF	50V
C510	1-137-150-11	MYLAR 0.01MF 10%	100V	C1351	1-163-251-11	CERAMIC CHIP 100PF 5%	50V
C511 Δ	1-115-460-11	FILM 0.022MF 3%	1.2KV	C1352	1-126-933-11	ELECT 100MF 20%	16V
C513		VARIANT(SEE VARIANT PARTS LIST)		C1353	1-163-037-11	CERAMIC CHIP 0.022MF 10%	50V
C514		VARIANT(SEE VARIANT PARTS LIST)		C1354	1-216-295-91	SHORT	
C515	1-106-343-00	MYLAR 0.001MF 10%	100V	C1501		VARIANT(SEE VARIANT PARTS LIST)	
C516	1-115-461-11	FILM 2MF 5%	200V				
C517	1-107-649-11	ELECT 2.2MF 20%	250V				
C518	1-106-395-00	MYLAR 0.15MF 10%	200V				
C519	1-162-815-11	CERAMIC CHIP 47PF 5%	500V				
C520		VARIANT(SEE VARIANT PARTS LIST)					
C521		VARIANT(SEE VARIANT PARTS LIST)					
C522	1-126-960-11	ELECT 1MF 20%	50V				
C525	1-102-244-00	CERAMIC CHIP 220PF 10%	500V				
C526	1-107-662-11	ELECT 22MF 20%	250V				
C527	1-162-116-00	CERAMIC CHIP 680PF 10%	2KV				
C528	1-164-161-11	CERAMIC CHIP 0.0022MF 10%	50V				
C529	1-128-551-11	ELECT 22MF 20%	25V				
C530	1-137-366-11	FILM 0.0022MF 5%	50V				
C531	1-126-965-11	ELECT 22MF 20%	50V				
C532	1-126-965-11	ELECT 22MF 20%	50V				
C537		VARIANT(SEE VARIANT PARTS LIST)					
C539		VARIANT(SEE VARIANT PARTS LIST)					
C540	1-123-024-21	ELECT 33MF	160V				
C541	1-128-560-11	ELECT 22MF 20%	100V				

CONNECTOR

CN270	1-573-298-11	CONNECTOR, BOARD TO BOARD 20P
CN271	1-573-978-21	CONNECTOR, BOARD TO BOARD 11P
CN351 *	1-564-509-11	PLUG, CONNECTOR 6P
CN461 *		VARIANT(SEE VARIANT PARTS LIST)
CN501 *	1-580-798-11	CONNECTOR PIN (DY) 6P
CN503 *	1-564-508-11	PLUG, CONNECTOR 5P
CN1001*	1-564-512-11	PLUG, CONNECTOR 9P
CN1101		VARIANT(SEE VARIANT PARTS LIST)
CN1231	1-564-511-11	PLUG, CONNECTOR 8P
CN1641*	1-564-515-11	PLUG, CONNECTOR 12P
CN1941*	1-564-508-11	PLUG, CONNECTOR 5P
CN3001		VARIANT(SEE VARIANT PARTS LIST)

DIODE

D001	8-719-991-33	DIODE 1SS133T-77
D002	8-719-109-89	DIODE RD5.6ESB2
D003	8-719-991-33	DIODE 1SS133T-77

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

V SERIES

COMMON PARTS LISTING



REF.NO.	PART NO.	DESCRIPTION	REMARK
D004	8-719-110-17	DIODE RD10ESB2	
D011	8-719-983-20	DIODE MTZJ-T-77-4.3C	
D013	8-719-991-33	DIODE 1SS133T-77	
D014	8-719-991-33	DIODE 1SS133T-77	
D015	8-719-991-33	DIODE 1SS133T-77	
D353	8-719-991-33	DIODE 1SS133T-77	
D356	8-719-991-33	DIODE 1SS133T-77	
D360	8-719-110-17	DIODE RD10ESB2	
D362	8-719-991-33	DIODE 1SS133T-77	
D368		VARIANT(SEE VARIANT PARTS LIST)	
D462	8-719-991-33	DIODE 1SS133T-77	
D501	8-719-109-89	DIODE RD5.6ESB2	
D502	8-719-945-80	DIODE ERC06-15S	
D503	8-719-945-80	DIODE ERC06-15S	
D504	8-719-900-26	DIODE ERD29-08J	
D505	8-719-908-03	DIODE GP08D	
D506	8-719-908-03	DIODE GP08D	
D507	8-719-991-33	DIODE 1SS133T-77	
D515	8-719-302-43	DIODE EL1Z	
D516	8-719-991-33	DIODE 1SS133T-77	
D518	8-719-991-33	DIODE 1SS133T-77	
D519 Δ	8-719-302-43	DIODE EL1Z	
D520	8-719-991-33	DIODE 1SS133T-77	
D521	8-719-921-63	DIODE MTZJ-7.5B	
D530	8-719-979-85	DIODE EGP20G	
D531	8-719-979-85	DIODE EGP20G	
D534	8-719-302-43	DIODE EL1Z	
D561	8-719-908-03	DIODE GP08D	
D562	8-719-991-33	DIODE 1SS133T-77	
D1102	8-719-982-24	DIODE MTZJ-33A	
D1103	8-719-109-89	DIODE RD5.6ESB2	
D1263	8-719-110-17	DIODE RD10ESB2	
D1264	8-719-110-17	DIODE RD10ESB2	
FERRITE BEAD			
FB501	1-410-396-41	FERRITE 0.45UH	
FB502	1-410-397-21	FERRITE 1.1UH	
FB503	1-410-397-21	FERRITE 1.1UH	
IC			
IC001	8-752-897-18	IC CXP85840A-011S	
IC002	8-759-527-74	IC M24C02-MN6T	
IC351	8-752-082-73	IC CXA2095S	
IC461		VARIANT(SEE VARIANT PARTS LIST)	
IC501	8-759-700-07	IC NJM2903M	
IC561	8-759-980-58	IC TDA8172	

REF.NO.	PART NO.	DESCRIPTION	REMARK
CHIP CONDUCTOR			
JR001		VARIANT(SEE VARIANT PARTS LIST)	
JR200	1-216-295-91	SHORT	
JR201		VARIANT(SEE VARIANT PARTS LIST)	
JR202		VARIANT(SEE VARIANT PARTS LIST)	
JR351		VARIANT(SEE VARIANT PARTS LIST)	
JR352		VARIANT(SEE VARIANT PARTS LIST)	
JR463		VARIANT(SEE VARIANT PARTS LIST)	
JR501	1-216-295-91	SHORT	
JR1417		VARIANT(SEE VARIANT PARTS LIST)	
JR1454	1-216-295-91	SHORT	
JR1455	1-216-295-91	SHORT	
JR1801	1-216-295-91	SHORT	
JR1802	1-216-295-91	SHORT	
JR1803	1-216-295-91	SHORT	
JR1804	1-216-295-91	SHORT	
JR4120	1-216-295-91	SHORT	
COIL			
L001	1-408-421-00	INDUCTOR 100UH	
L002	1-408-421-00	INDUCTOR 100UH	
L003	1-410-470-11	INDUCTOR 10UH	
L004	1-410-470-11	INDUCTOR 10UH	
L352	1-412-537-31	INDUCTOR 100UH	
L461		VARIANT(SEE VARIANT PARTS LIST)	
L501 Δ	1-411-976-11	COIL, HORIZONTAL LINEARITY	
L502	1-412-552-11	INDUCTOR 2.2MMH	
L503	1-406-677-11	INDUCTOR	
L511	1-406-607-41	INDUCTOR	
L517	1-412-552-11	INDUCTOR 2.2MMH	
L541		VARIANT(SEE VARIANT PARTS LIST)	
L1101	1-408-421-00	INDUCTOR 100UH	
L1102	1-410-470-11	INDUCTOR 10UH	
IC LINK			
PS461		VARIANT(SEE VARIANT PARTS LIST)	
TRANSISTOR			
Q001	8-729-216-22	TRANSISTOR 2SA1162-G	
Q002	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q003	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q004	8-729-216-22	TRANSISTOR 2SA1162-G	
Q010	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q011	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q012	8-729-422-27	TRANSISTOR 2SD601A-Q	
Q013	8-729-422-27	TRANSISTOR 2SD601A-Q	



V SERIES COMMON PARTS LISTING

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
Q014	8-729-422-27	TRANSISTOR 2SD601A-Q		R027	1-249-389-11	CARBON 4.7 5%	1/4W
Q015	8-729-422-27	TRANSISTOR 2SD601A-Q		R028	1-249-417-11	CARBON 1K 5%	1/4W
Q016	8-729-422-27	TRANSISTOR 2SD601A-Q		R029	1-216-025-91	RES, CHIP 100 5%	1/10W
Q017	8-729-216-22	TRANSISTOR 2SA1162-G		R030	1-249-425-11	CARBON 4.7K 5%	1/4W
Q301	8-729-216-22	TRANSISTOR 2SA1162-G		R031		VARIANT(SEE VARIANT PARTS LIST)	
Q302	8-729-216-22	TRANSISTOR 2SA1162-G		R032	1-247-815-91	CARBON 220 5%	1/4W
Q303	8-729-216-22	TRANSISTOR 2SA1162-G		R036	1-216-049-91	RES, CHIP 1K 5%	1/10W
Q354	8-729-422-27	TRANSISTOR 2SD601A-Q		R037	1-216-049-91	RES, CHIP 1K 5%	1/10W
Q356	8-729-216-22	TRANSISTOR 2SA1162-G		R038	1-216-049-91	RES, CHIP 1K 5%	1/10W
Q357	8-729-422-27	TRANSISTOR 2SD601A-Q		R039	1-247-807-31	CARBON 100 5%	1/4W
Q358	8-729-422-27	TRANSISTOR 2SD601A-Q		R040		VARIANT(SEE VARIANT PARTS LIST)	
Q461		VARIANT(SEE VARIANT PARTS LIST)		R041		VARIANT(SEE VARIANT PARTS LIST)	
Q462		VARIANT(SEE VARIANT PARTS LIST)		R042		VARIANT(SEE VARIANT PARTS LIST)	
Q501	8-729-140-50	TRANSISTOR 2SC3209LK		R044	1-216-033-00	RES, CHIP 220 5%	1/10W
Q502 Δ	8-729-035-75	TRANSISTOR 2SC5148(LBSONY)		R045		VARIANT(SEE VARIANT PARTS LIST)	
Q511 Δ	8-729-422-27	TRANSISTOR 2SD601A-Q		R046	1-247-815-91	CARBON 220 5%	1/4W
Q512 Δ	8-729-809-29	TRANSISTOR 2SC4159-E		R047	1-249-417-11	CARBON 1K 5%	1/4W
Q551	8-729-216-22	TRANSISTOR 2SA1162-G		R048	1-249-417-11	CARBON 1K 5%	1/4W
Q552	8-729-422-27	TRANSISTOR 2SD601A-Q		R049	1-249-417-11	CARBON 1K 5%	1/4W
Q561	8-729-422-27	TRANSISTOR 2SD601A-Q		R052	1-216-061-00	RES, CHIP 3.3K 5%	1/10W
Q562	8-729-422-27	TRANSISTOR 2SD601A-Q		R053	1-216-061-00	RES, CHIP 3.3K 5%	1/10W
Q563	8-729-105-08	TRANSISTOR 2SA1330-06		R054	1-216-061-00	RES, CHIP 3.3K 5%	1/10W
Q1102	8-729-119-78	TRANSISTOR 2SC2785-HFE		R055	1-216-097-91	RES, CHIP 100K 5%	1/10W
Q1103	8-729-422-27	TRANSISTOR 2SD601A-QRS-TX		R056	1-216-033-00	RES, CHIP 220 5%	1/10W
RESISTOR				R057	1-249-417-11	CARBON 1K 5%	1/4W
R001	1-216-045-00	RES, CHIP 680 5%	1/10W	R058	1-216-033-00	RES, CHIP 220 5%	1/10W
R002	1-247-815-91	CARBON 220 5%	1/4W	R064	1-216-033-00	RES, CHIP 220 5%	1/10W
R003	1-216-097-91	RES, CHIP 100K 5%	1/10W	R065	1-216-033-00	RES, CHIP 220 5%	1/10W
R004	1-216-121-91	RES, CHIP 1M 5%	1/10W	R066	1-216-033-00	RES, CHIP 220 5%	1/10W
R006		VARIANT(SEE VARIANT PARTS LIST)		R067	1-216-041-00	RES, CHIP 470 5%	1/10W
R007	1-216-073-00	RES, CHIP 10K 5%	1/10W	R068	1-247-815-91	CARBON 220 5%	1/4W
R008		VARIANT(SEE VARIANT PARTS LIST)		R069		VARIANT(SEE VARIANT PARTS LIST)	
R009	1-216-073-00	RES, CHIP 10K 5%	1/10W	R070	1-249-421-11	CARBON 2.2K 5%	1/4W
R010	1-216-037-00	RES, CHIP 330 5%	1/10W	R071	1-247-815-91	CARBON 220 5%	1/4W
R011	1-216-065-91	RES, CHIP 4.7K 5%	1/10W	R072	1-216-033-00	RES, CHIP 220 5%	1/10W
R012		VARIANT(SEE VARIANT PARTS LIST)		R073	1-216-033-00	RES, CHIP 220 5%	1/10W
R013	1-216-065-91	RES, CHIP 4.7K 5%	1/10W	R074	1-216-033-00	RES, CHIP 220 5%	1/10W
R014	1-216-065-91	RES, CHIP 4.7K 5%	1/10W	R075	1-216-033-00	RES, CHIP 220 5%	1/10W
R015	1-216-073-00	RES, CHIP 10K 5%	1/10W	R076	1-216-033-00	RES, CHIP 220 5%	1/10W
R016	1-216-073-00	RES, CHIP 10K 5%	1/10W	R077	1-216-033-00	RES, CHIP 220 5%	1/10W
R019	1-249-425-11	CARBON 4.7K 5%	1/4W	R078	1-249-417-11	CARBON 1K 5%	1/4W
R020	1-216-065-91	RES, CHIP 4.7K 5%	1/10W	R079	1-216-033-00	RES, CHIP 220 5%	1/10W
R021	1-216-033-00	RES, CHIP 220 5%	1/10W	R080	1-216-065-91	RES, CHIP 4.7K 5%	1/10W
R022	1-249-429-11	CARBON 10K 5%	1/4W	R081	1-216-025-91	RES, CHIP 100 5%	1/10W
R023	1-216-089-91	RES, CHIP 47K 5%	1/10W	R082	1-216-025-91	RES, CHIP 100 5%	1/10W
R024	1-249-381-11	CARBON 1 5%	1/4W	R083	1-249-429-11	CARBON 10K 5%	1/4W
R025	1-163-010-11	CERAMIC CHIP 0.0012MF 10% 50V		R084	1-216-049-91	RES, CHIP 1K 5%	1/10W
R026	1-163-038-91	CERAMIC CHIP 0.1MF 25V		R085		VARIANT(SEE VARIANT PARTS LIST)	
				R087	1-247-815-91	CARBON 220 5%	1/4W

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

V SERIES

COMMON PARTS LISTING



REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
R088		VARIANT(SEE VARIANT PARTS LIST)		R389	1-216-067-00	RES, CHIP 5.6K 5%	1/10W
R089	1-216-033-00	RES, CHIP 220 5%	1/10W	R390	1-216-035-00	RES, CHIP 270 5%	1/10W
R090		VARIANT(SEE VARIANT PARTS LIST)		R391	1-208-810-11	RES, CHIP 15K 0.50%	1/10W
R092	1-249-429-11	CARBON 10K 5%	1/4W	R392	1-216-025-91	RES, CHIP 100 5%	1/10W
R093	1-249-387-11	CARBON 3.3 5%	1/4W				
R094	1-249-381-11	CARBON 1 5%	1/4W	R393	1-216-043-91	RES, CHIP 560 5%	1/10W
R096	1-216-347-11	METAL OXIDE 0.68 5%	1W	R394	1-216-059-00	RES, CHIP 2.7K 5%	1/10W
R097	1-216-065-91	RES, CHIP 4.7K 5%	1/10W	R395	1-216-061-00	RES, CHIP 3.3K 5%	1/10W
R099	1-216-065-91	RES, CHIP 4.7K 5%	1/10W	R396	1-249-417-11	CARBON 1K 5%	1/4W
R101	1-249-381-11	CARBON 1 5%	1/4W	R397	1-249-425-11	CARBON 4.7K 5%	1/4W
				R461		VARIANT(SEE VARIANT PARTS LIST)	
R131	1-216-035-00	RES, CHIP 270 5%	1/10W	R462		VARIANT(SEE VARIANT PARTS LIST)	
R132	1-216-115-00	RES, CHIP 560K 5%	1/10W	R463		VARIANT(SEE VARIANT PARTS LIST)	
R133	1-216-039-00	RES, CHIP 390 5%	1/10W	R464		VARIANT(SEE VARIANT PARTS LIST)	
R135	1-216-073-00	RES, CHIP 10K 5%	1/10W	R465		VARIANT(SEE VARIANT PARTS LIST)	
R136	1-216-073-00	RES, CHIP 10K 5%	1/10W				
R137	1-216-049-91	RES, CHIP 1K 5%	1/10W	R466		VARIANT(SEE VARIANT PARTS LIST)	
R353	1-208-788-11	RES, CHIP 1.8K 0.50%	1/10W	R467		VARIANT(SEE VARIANT PARTS LIST)	
R354	1-216-077-00	RES, CHIP 15K 5%	1/10W	R469		VARIANT(SEE VARIANT PARTS LIST)	
R355	1-216-033-00	RES, CHIP 220 5%	1/10W	R470		VARIANT(SEE VARIANT PARTS LIST)	
R356	1-216-033-00	RES, CHIP 220 5%	1/10W	R471		VARIANT(SEE VARIANT PARTS LIST)	
R358		VARIANT(SEE VARIANT PARTS LIST)		R472		VARIANT(SEE VARIANT PARTS LIST)	
R359		VARIANT(SEE VARIANT PARTS LIST)		R473		VARIANT(SEE VARIANT PARTS LIST)	
R360		VARIANT(SEE VARIANT PARTS LIST)		R474		VARIANT(SEE VARIANT PARTS LIST)	
R361	1-216-025-91	RES, CHIP 100 5%	1/10W	R475		VARIANT(SEE VARIANT PARTS LIST)	
R362	1-216-025-91	RES, CHIP 100 5%	1/10W	R476		VARIANT(SEE VARIANT PARTS LIST)	
R363	1-216-025-91	RES, CHIP 100 5%	1/10W	R477		VARIANT(SEE VARIANT PARTS LIST)	
R364	1-216-101-00	RES, CHIP 150K 5%	1/10W	R478		VARIANT(SEE VARIANT PARTS LIST)	
R365	1-216-101-00	RES, CHIP 150K 5%	1/10W	R479		VARIANT(SEE VARIANT PARTS LIST)	
R366	1-216-089-91	RES, CHIP 47K 5%	1/10W	R480		VARIANT(SEE VARIANT PARTS LIST)	
R367	1-216-097-91	RES, CHIP 100K 5%	1/10W	R481		VARIANT(SEE VARIANT PARTS LIST)	
R368	1-249-441-11	CARBON 100K 5%	1/4W	R482		VARIANT(SEE VARIANT PARTS LIST)	
R369	1-216-097-91	RES, CHIP 100K 5%	1/10W	R483		VARIANT(SEE VARIANT PARTS LIST)	
R370	1-249-417-11	CARBON 1K 5%	1/4W	R501	1-216-037-00	RES, CHIP 330 5%	1/10W
R371	1-216-053-00	RES, CHIP 1.5K 5%	1/10W	R502	1-216-061-00	RES, CHIP 3.3K 5%	1/10W
R372	1-216-113-00	RES, CHIP 470K 5%	1/10W	R503	1-249-426-11	CARBON 5.6K 5%	1/4W
R373	1-216-073-00	RES, CHIP 10K 5%	1/10W	R504 Δ	1-215-915-11	METAL OXIDE 470 5%	3W
R374	1-216-125-00	RES, CHIP 1.5M 5%	1/10W	R505	1-249-431-11	CARBON 15K 5%	1/4W
R375	1-216-025-91	RES, CHIP 100 5%	1/10W	R506	1-215-861-00	METAL OXIDE 47 5%	1W
R376	1-216-073-00	RES, CHIP 10K 5%	1/10W	R507	1-249-401-11	CARBON 47 5%	1/4W
R379	1-216-033-00	RES, CHIP 220 5%	1/10W	R508	1-249-427-11	CARBON 6.8K 5%	1/4W
R380	1-247-815-91	CARBON 220 5%	1/4W	R509	1-247-750-11	CARBON 680 5%	1/2W
R381	1-247-815-91	CARBON 220 5%	1/4W	R510 Δ	1-215-860-11	METAL OXIDE 33 5%	1W
R382	1-216-033-00	RES, CHIP 220 5%	1/10W	R511		VARIANT(SEE VARIANT PARTS LIST)	
R383	1-216-049-91	RES, CHIP 1K 5%	1/10W	R512 Δ	1-215-886-11	METAL OXIDE 100 5%	2W
R384	1-216-109-00	RES, CHIP 330K 5%	1/10W	R515		VARIANT(SEE VARIANT PARTS LIST)	
R385	1-249-422-11	CARBON 2.7K 5%	1/4W	R516	1-216-057-00	RES, CHIP 2.2K 5%	1/10W
R386		VARIANT(SEE VARIANT PARTS LIST)		R517	1-249-415-11	CARBON 680 5%	1/4W
R387	1-216-049-91	RES, CHIP 1K 5%	1/10W	R518	1-216-073-00	RES, CHIP 10K 5%	1/10W
R388	1-216-089-91	RES, CHIP 47K 5%	1/10W	R519	1-249-411-11	CARBON 330 5%	1/4W
				R521	1-215-915-11	METAL OXIDE 470 5%	3W



V SERIES COMMON PARTS LISTING

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

The components identified by Δ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

REF.NO.	PART NO.	DESCRIPTION	REMARK			
R523		VARIANT(SEE VARIANT PARTS LIST)				
R524	1-249-429-11	CARBON	10K	5%	1/4W	
R525	1-216-071-00	RES, CHIP	8.2K	5%	1/10W	
R528	1-216-081-00	RES, CHIP	22K	5%	1/10W	
R529		VARIANT(SEE VARIANT PARTS LIST)				
Δ R530 Δ	1-208-808-11	RES, CHIP	12K	0.50%	1/10W	
R531		VARIANT(SEE VARIANT PARTS LIST)				
R532	1-208-760-11	RES, CHIP	120	0.50%	1/10W	
R533		VARIANT(SEE VARIANT PARTS LIST)				
R535	1-216-101-00	RES, CHIP	150K	5%	1/10W	
R536 Δ	1-249-377-11	CARBON	0.47	5%	1/4W	
R537 Δ	1-249-377-11	CARBON	0.47	5%	1/4W	
R538	1-247-887-00	CARBON	220K	5%	1/4W	
R541		VARIANT(SEE VARIANT PARTS LIST)				
R542		VARIANT(SEE VARIANT PARTS LIST)				
R543	1-249-377-11	CARBON	0.47	5%	1/4W	
R546		VARIANT(SEE VARIANT PARTS LIST)				
R547	1-215-457-00	METAL OXIDE	33K	1%	1/4W	
R549	1-215-437-00	METAL OXIDE	4.7K	1%	1/4W	
R550 Δ	1-249-377-11	CARBON	0.47	5%	1/4W	
R551 Δ	1-215-873-00	METAL OXIDE	4.7K	5%	1W	
R552	1-216-069-00	RES, CHIP	6.8K	5%	1/10W	
R553 Δ	1-249-377-11	CARBON	0.47	5%	1/4W	
R554	1-216-057-00	RES, CHIP	2.2K	5%	1/10W	
R561	1-216-073-00	RES, CHIP	10K	5%	1/10W	
R563 Δ	1-216-351-00	METAL OXIDE	1.5	5%	1W	
R564	1-249-393-11	CARBON	10	5%	1/4W	
R565 Δ	1-215-890-11	METAL OXIDE	470	5%	2W	
R566	1-216-073-00	RES, CHIP	10K	5%	1/10W	
R567 Δ	1-249-385-11	CARBON	2.2	5%	1/4W	
R568	1-216-073-00	RES, CHIP	10K	5%	1/10W	
R569	1-216-073-00	RES, CHIP	10K	5%	1/10W	
R570	1-216-097-91	RES, CHIP	100K	5%	1/10W	
R571	1-216-081-00	RES, CHIP	22K	5%	1/10W	
R572	1-216-081-00	RES, CHIP	22K	5%	1/10W	
R573	1-216-097-91	RES, CHIP	100K	5%	1/10W	
R574 Δ	1-216-365-00	METAL OXIDE	0.47	5%	2W	
R575	1-216-113-00	RES, CHIP	470K	5%	1/10W	
R576	1-216-073-00	RES, CHIP	10K	5%	1/10W	
R577	1-216-097-91	RES, CHIP	100K	5%	1/10W	
R578	1-208-784-11	RES, CHIP	1.2K	0.50%	1/10W	
R579	1-208-842-11	RES, CHIP	330K	0.50%	1/10W	
R580	1-249-441-11	CARBON	100K	5%	1/4W	
R1101	1-216-049-91	RES, CHIP	1K	5%	1/10W	
R1102	1-215-900-11	METAL OXIDE	22K	5%	2W	
R1103	1-216-051-00	RES, CHIP	1.2K	5%	1/10W	
R1104	1-216-083-00	RES, CHIP	27K	5%	1/10W	
R1105	1-216-689-11	RES, CHIP	39K	5%	1/10W	
R1106	1-216-049-91	RES, CHIP	1K	5%	1/10W	

REF.NO.	PART NO.	DESCRIPTION	REMARK			
R1107	1-216-065-91	RES, CHIP	4.7K	5%	1/10W	
R1108	1-216-073-00	RES, CHIP	10K	5%	1/10W	
R1109	1-216-019-00	RES, CHIP	56	5%	1/10W	
R1110	1-216-019-00	RES, CHIP	56	5%	1/10W	
R1111	1-216-019-00	RES, CHIP	56	5%	1/10W	
R1115	1-216-045-00	RES, CHIP	680	5%	1/10W	
R1117	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1118	1-249-425-11	CARBON	4.7K	5%	1/4W	
R1120	1-216-057-00	RES, CHIP	2.2K	5%	1/10W	
R1121	1-216-035-00	RES, CHIP	270	5%	1/10W	
R1122	1-216-115-00	RES, CHIP	560K	5%	1/10W	
R1123	1-216-039-00	RES, CHIP	390	5%	1/10W	
R1125	1-216-057-00	RES, CHIP	2.2K	5%	1/10W	
R1126	1-216-035-00	RES, CHIP	270	5%	1/10W	
R1127	1-216-115-00	RES, CHIP	560K	5%	1/10W	
R1128	1-216-039-00	RES, CHIP	390	5%	1/10W	
R1130	1-216-057-00	RES, CHIP	2.2K	5%	1/10W	
R1351	1-247-815-91	CARBON	220	5%	1/4W	
R1352	1-247-815-91	CARBON	220	5%	1/4W	
R1353	1-247-815-91	CARBON	220	5%	1/4W	
R1354	1-216-033-00	RES, CHIP	220	5%	1/10W	
R1355	1-216-025-91	RES, CHIP	100	5%	1/10W	
R1356	1-216-025-91	RES, CHIP	100	5%	1/10W	
R1357	1-216-025-91	RES, CHIP	100	5%	1/10W	
R1358	1-247-807-31	CARBON	100	5%	1/4W	
R1359	1-216-025-91	RES, CHIP	100	5%	1/10W	
R1360	1-216-069-00	RES, CHIP	6.8K	5%	1/10W	
R1361	1-216-065-91	RES, CHIP	4.7K	5%	1/10W	
R1362	1-216-295-91	SHORT				

SWITCH

S501 1-572-707-11 SWITCH, LEVER

TRANSFORMER

T501 1-437-210-11 TRANSFORMER, HORIZONTAL DRIVE
T502 VARIANT(SEE VARIANT PARTS LIST)
T503 VARIANT(SEE VARIANT PARTS LIST)
T504 VARIANT(SEE VARIANT PARTS LIST)

TUNER

TU102 Δ 8-598-431-00 TUNER, FSS BTF-WA411

CRYSTAL

X001 1-578-774-11 VIBRATOR, CRYSTAL
X353 1-567-505-11 OSCILLATOR, CRYSTAL
X354 1-577-611-11 OSCILLATOR, CERAMIC CHIP



S SERIES BOARD VARIANT PARTS LIST

The parts on this page belong to the following model(s) only:

KV-32S40/34SL40/34SL40C

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

The components identified by Δ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

REF.NO.	PART NO.	DESCRIPTION	REMARK
---------	----------	-------------	--------

A BOARD VARIANT LIST: KV-32S40/34SL40/34SL40C

* A-1298-630-A A BOARD, COMPLETE

CAPACITOR

C068	1-164-096-11	CERAMIC CHIP	0.01MF		50V
C370	1-163-037-11	CERAMIC CHIP	0.022MF	10%	50V
C375	1-165-319-11	CERAMIC CHIP	0.1MF		50V
C513 Δ	1-130-895-00	FILM	0.056MF	5%	400V
C514 Δ	1-104-844-11	FILM	0.62MF	5%	200V
C520	1-164-645-11	CERAMIC CHIP	1000PF	10%	500V
C521	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V
C537	1-126-941-11	ELECT	470MF	20%	25V
C539 Δ	1-126-935-11	ELECT	470MF	20%	16V
C1501	1-115-462-11	FILM	0.12MF	5%	200V

DIODE

D005	8-719-991-33	DIODE 1SS133T-77
D006	1-810-039-31	LED UNIT

IC

IC003	8-742-014-11	HYB IC SBX1981-51
IC1261	8-759-366-77	IC MM1311AD

CHIP CONDUCTOR

JR351	1-216-295-91	SHORT
JR352	1-216-295-91	SHORT
JR1264	1-216-295-91	SHORT

RESISTOR

R059	1-216-047-91	RES, CHIP	820	5%	1/10W
R060	1-216-049-91	RES, CHIP	1K	5%	1/10W
R061	1-216-055-00	RES, CHIP	1.8K	5%	1/10W
R062	1-216-065-91	RES, CHIP	4.7K	5%	1/10W
R063	1-216-073-00	RES, CHIP	10K	5%	1/10W
R365	1-216-101-00	RES, CHIP	150K	5%	1/10W
R374	1-216-125-00	RES, CHIP	1.5M	5%	1/10W
R469	1-216-069-00	RES, CHIP	6.8K	5%	1/10W
R472	1-216-069-00	RES, CHIP	6.8K	5%	1/10W
R511 Δ	1-215-885-00	METAL	68	5%	2W
R515	1-216-083-00	RES, CHIP	27K	5%	1/10W
R523	1-216-073-00	RES, CHIP	10K	5%	1/10W
R529	1-208-814-11	RES, CHIP	22K	0.50%	1/10W
Δ R531 Δ	1-208-826-11	RES, CHIP	68K	0.50%	1/10W
R533 Δ	1-215-902-11	METAL	47K	5%	1W

REF.NO.	PART NO.	DESCRIPTION	REMARK
---------	----------	-------------	--------

R535	1-216-101-00	RES, CHIP	150K	5%	1/10W
R546	1-215-453-00	METAL	22K	1%	1/4W
R1009	1-216-033-00	RES, CHIP	220	5%	1/10W
R1010	1-216-033-00	RES, CHIP	220	5%	1/10W

SWITCH

S001	1-692-431-21	SWITCH, TACTILE
S002	1-692-431-21	SWITCH, TACTILE
S003	1-692-431-21	SWITCH, TACTILE
S004	1-692-431-21	SWITCH, TACTILE
S005	1-692-431-21	SWITCH, TACTILE
S006	1-692-431-21	SWITCH, TACTILE
S007	1-692-431-21	SWITCH, TACTILE

TRANSFORMER

T502 Δ	1-424-545-11	TRANSFORMER FERRITE (PMT)
T503 Δ	1-453-207-11	FLYBACK TRANSFORMER ASSY, NX-2609//X4C

TUNER

TU102 Δ	8-598-431-00	TUNER, FSS BTF-WA411
----------------	--------------	----------------------

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

The components identified by \boxtimes in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.



**S SERIES
BOARD VARIANT PARTS LIST**

The parts on this page belong to the following model(s) only:

KV-32S45/34SL45

REF.NO. PART NO. DESCRIPTION REMARK

A BOARD VARIANT LIST: KV-32S45/34SL45

* A-1298-631-A A BOARD, COMPLETE

CAPACITOR

C370	1-163-037-11	CERAMIC CHIP	0.022MF	10%	50V
C513 Δ	1-130-895-00	FILM	0.056MF	5%	400V
C514 Δ	1-104-844-11	FILM	0.62MF	5%	200V
C520	1-164-645-11	CERAMIC CHIP	1000PF	10%	500V
C521	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V
C537	1-126-941-11	ELECT	470MF	20%	25V
C539 Δ	1-126-935-11	ELECT	470MF	20%	16V
C1241	1-136-161-00	FILM	0.047MF	5%	50V
C1242	1-126-960-11	ELECT	1MF	20%	50V
C1243	1-126-960-11	ELECT	1MF	20%	50V
C1501	1-115-462-11	FILM	0.12MF	5%	200V

CONNECTOR

CN1001*	1-564-512-11	PLUG, CONNECTOR	9P		
CN3001	1-573-298-11	CONNECTOR, BOARD TO BOARD			

DIODE

D368	8-719-991-33	DIODE	1SS133T-77		
------	--------------	-------	------------	--	--

IC

IC1261	8-759-534-81	IC	MM1313AD		
--------	--------------	----	----------	--	--

JACK

J1233	1-774-749-11	JACK BLOCK, PIN			
-------	--------------	-----------------	--	--	--

RESISTOR

R012	1-216-033-00	RES, CHIP	220	5%	1/10W
R022	1-249-429-11	CARBON	10K	5%	1/4W
R031	1-247-815-91	CARBON	220	5%	1/4W
R358	1-247-815-91	CARBON	220	5%	1/4W
R359	1-247-815-91	CARBON	220	5%	1/4W
R360	1-247-815-91	CARBON	220	5%	1/4W
R365	1-216-101-00	RES, CHIP	150K	5%	1/10W
R374	1-216-125-00	RES, CHIP	1.5M	5%	1/10W
R386	1-216-049-91	RES, CHIP	1K	5%	1/10W
R469	1-216-069-00	RES, CHIP	6.8K	5%	1/10W
R472	1-216-069-00	RES, CHIP	6.8K	5%	1/10W
R511 Δ	1-215-885-00	METAL	68	5%	2W
R515	1-216-083-00	RES, CHIP	27K	5%	1/10W

REF.NO. PART NO. DESCRIPTION REMARK

R523	1-216-073-00	RES, CHIP	10K	5%	1/10W
R529	1-208-814-11	RES, CHIP	22K	0.50%	1/10W
\boxtimes R531 Δ	1-208-826-11	RES, CHIP	68K	0.50%	1/10W
R533 Δ	1-215-902-11	METAL	47K	5%	1W
R535	1-216-101-00	RES, CHIP	150K	5%	1/10W
R546	1-215-453-00	METAL	22K	1%	1/4W
R1249	1-216-022-00	RES, CHIP	75	5%	1/10W
R1250	1-216-113-00	RES, CHIP	470K	5%	1/10W
R1251	1-216-065-91	RES, CHIP	4.7K	5%	1/10W
R1252	1-216-113-00	RES, CHIP	470K	5%	1/10W
R1253	1-216-065-91	RES, CHIP	4.7K	5%	1/10W
R1273	1-216-033-00	RES, CHIP	220	5%	1/10W
R1274	1-216-025-91	RES, CHIP	100	5%	1/10W
R1283	1-247-791-91	CARBON	22	5%	1/4W
R1297	1-216-025-91	RES, CHIP	100	5%	1/10W

TRANSFORMER

T502 Δ	1-424-545-11	TRANSFORMER FERRITE (PMT)			
T503 Δ	1-453-207-11	FLYBACK TRANSFORMER ASSY, NX-2609//X4C			

TUNER

TU102 Δ	8-598-431-00	TUNER, FSS BTF-WA411			
----------------	--------------	----------------------	--	--	--



S SERIES BOARD VARIANT PARTS LIST

The parts on this page belong to the following model(s) only:

KV-35S40

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

The components identified by Δ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

REF.NO.	PART NO.	DESCRIPTION	REMARK
A BOARD VARIANT LIST: KV-35S40			

* A-1298-645-A A BOARD COMPLETE

CAPACITOR

C069	1-126-964-11	ELECT	10MF	20%	50V
C370	1-163-035-00	CERAMIC CHIP	0.047MF		50V
C375	1-165-319-11	CERAMIC CHIP	0.1MF		50V
C513 Δ	1-129-720-00	FILM	0.033MF	5%	630V
C514 Δ	1-136-540-11	FILM	0.82MF	5%	200V
C520	1-101-821-00	CERAMIC CHIP	0.0022MF		500V
C521	1-164-182-11	CERAMIC CHIP	0.0033MF	10%	50V
C537	1-126-942-61	ELECT	1000MF	20%	25V
C539 Δ	1-126-942-61	ELECT	1000MF	20%	25V
C542	1-106-383-00	MYLAR	0.047MF	10%	200V
C1241	1-136-161-00	FILM	0.047MF	5%	50V
C1242	1-126-960-11	ELECT	1MF	20%	50V
C1243	1-126-960-11	ELECT	1MF	20%	50V

CONNECTOR

CN1001* 1-564-512-11 PLUG, CONNECTOR 9P

IC

IC1261 8-759-366-77 IC MM1311AD

JACK

J1233 1-774-749-11 JACK BLOCK, PIN

CHIP CONDUCTOR

JR351 1-216-295-91 SHORT
JR352 1-216-295-91 SHORT
JR1264 1-216-295-91 SHORT

COIL

L541 1-406-677-11 INDUCTOR

RESISTOR

R022 1-249-429-11 CARBON 10K 5% 1/4W
R069 1-216-073-00 RES, CHIP 10K 5% 1/10W
R085 1-216-073-00 RES, CHIP 10K 5% 1/10W
R365 1-216-097-91 RES, CHIP 100K 5% 1/10W
R374 1-216-121-91 RES, CHIP 1M 5% 1/10W

REF.NO.	PART NO.	DESCRIPTION	REMARK
R469	1-216-065-91	RES, CHIP	4.7K 5% 1/10W
R472	1-216-065-91	RES, CHIP	4.7K 5% 1/10W
R511 Δ	1-215-886-11	METAL	100 5% 2W
R515	1-216-077-00	RES, CHIP	15K 5% 1/10W
R523	1-216-071-00	RES, CHIP	8.2K 5% 1/10W
R529	1-208-812-11	RES, CHIP	18K 0.50% 1/10W
Δ R531 Δ	1-208-838-11	RES, CHIP	220K 0.50% 1/10W
R533 Δ	1-215-878-00	METAL	33K 5% 1W
R535	1-216-103-00	RES, CHIP	180K 5% 1/10W
R541	1-249-377-11	CARBON	0.47 5% 1/4W
R542	1-249-397-11	CARBON	22 5% 1/4W
R546	1-215-451-00	METAL	18K 1% 1/4W
R1249	1-216-022-00	RES, CHIP	75 5% 1/10W
R1250	1-216-113-00	RES, CHIP	470K 5% 1/10W
R1251	1-216-065-91	RES, CHIP	4.7K 5% 1/10W
R1252	1-216-113-00	RES, CHIP	470K 5% 1/10W
R1253	1-216-065-91	RES, CHIP	4.7K 5% 1/10W
R1273	1-216-033-00	RES, CHIP	220 5% 1/10W
R1274	1-216-025-91	RES, CHIP	100 5% 1/10W
R1283	1-247-791-91	CARBON	22 5% 1/4W
R1296	1-216-025-91	RES, CHIP	100 5% 1/10W

TRANSFORMER

T502 Δ 1-429-408-11 TRANSFORMER FERRITE (PMT)
T503 Δ X-4034-797-1 FLYBACK TRANSFORMER ASSY, NX-3005/J1C
T504 1-413-059-00 TRANSFORMER FERRITE (DFT)

TUNER

TU102 Δ 8-598-431-00 TUNER, FSS BTF-WA411

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

The components identified by ✕ in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.



S SERIES BOARD VARIANT PARTS LIST

The parts on this page belong to the following model(s) only:

KV-35S45/37SL45

REF.NO.	PART NO.	DESCRIPTION	REMARK
---------	----------	-------------	--------

A BOARD VARIANT LIST: KV-35S45/37SL45

* A-1298-646-A A BOARD, COMPLETE

CAPACITOR

C069	1-126-964-11	ELECT	10MF	20%	50V
C370	1-163-035-00	CERAMIC CHIP	0.047MF		50V
C513 Δ	1-129-720-00	FILM	0.033MF	5%	630V
C514 Δ	1-136-540-11	FILM	0.82MF	5%	200V
C520	1-101-821-00	CERAMIC CHIP	0.0022MF		500V

C521	1-164-182-11	CERAMIC CHIP	0.0033MF	10%	50V
C537	1-126-942-61	ELECT	1000MF	20%	25V
C539 Δ	1-126-942-61	ELECT	1000MF	20%	25V
C542	1-106-383-00	MYLAR	0.047MF	10%	200V
C1241	1-136-161-00	FILM	0.047MF	5%	50V

C1242	1-126-960-11	ELECT	1MF	20%	50V
C1243	1-126-960-11	ELECT	1MF	20%	50V

CONNECTOR

CN1001*	1-564-512-11	PLUG, CONNECTOR 9P
CN3001	1-573-298-11	CONNECTOR, BOARD TO BOARD

DIODE

D368	8-719-991-33	DIODE 1SS133T-77
------	--------------	------------------

IC

IC1261	8-759-534-81	IC MM1313AD
--------	--------------	-------------

JACK

J1233	1-774-749-11	JACK BLOCK, PIN
-------	--------------	-----------------

COIL

L541	1-406-677-11	INDUCTOR
------	--------------	----------

RESISTOR

R012	1-216-033-00	RES, CHIP	220	5%	1/10W
R022	1-249-429-11	CARBON	10K	5%	1/4W
R031	1-247-815-91	CARBON	220	5%	1/4W
R069	1-216-073-00	RES, CHIP	10K	5%	1/10W
R085	1-216-073-00	RES, CHIP	10K	5%	1/10W

R358	1-247-815-91	CARBON	220	5%	1/4W
R359	1-247-815-91	CARBON	220	5%	1/4W
R360	1-247-815-91	CARBON	220	5%	1/4W
R365	1-216-097-91	RES, CHIP	100K	5%	1/10W
R374	1-216-121-91	RES, CHIP	1M	5%	1/10W

REF.NO.	PART NO.	DESCRIPTION	REMARK
---------	----------	-------------	--------

R386	1-216-049-91	RES, CHIP	1K 5% 1/10W
R469	1-216-065-91	RES, CHIP	4.7K 5% 1/10W
R472	1-216-065-91	RES, CHIP	4.7K 5% 1/10W
R511 Δ	1-215-886-11	METAL	100 5% 2W
R515	1-216-077-00	RES, CHIP	15K 5% 1/10W

R523	1-216-071-00	RES, CHIP	8.2K 5% 1/10W
R529	1-208-812-11	RES, CHIP	18K 0.50% 1/10W
✕ R531 Δ	1-208-838-11	RES, CHIP	220K 0.50% 1/10W
R533 Δ	1-215-878-00	METAL	33K 5% 1W
R535	1-216-103-00	RES, CHIP	180K 5% 1/10W

R541	1-249-377-11	CARBON	0.47 5% 1/4W
R542	1-249-397-11	CARBON	22 5% 1/4W
R546	1-215-451-00	METAL	18K 1% 1/4W
R1249	1-216-022-00	RES, CHIP	75 5% 1/10W
R1250	1-216-113-00	RES, CHIP	470K 5% 1/10W

R1251	1-216-065-91	RES, CHIP	4.7K 5% 1/10W
R1252	1-216-113-00	RES, CHIP	470K 5% 1/10W
R1253	1-216-065-91	RES, CHIP	4.7K 5% 1/10W
R1273	1-216-033-00	RES, CHIP	220 5% 1/10W
R1274	1-216-025-91	RES, CHIP	100 5% 1/10W

R1283	1-247-791-91	CARBON	22 5% 1/4W
R1297	1-216-025-91	RES, CHIP	100 5% 1/10W

TRANSFORMER

T502 Δ	1-429-408-11	TRANSFORMER FERRITE (PMT)
T503 Δ	X-4034-797-1	FLYBACK TRANSFORMER ASSY, NX-3005//J1C
T504	1-413-059-00	TRANSFORMER FERRITE (DFT)

TUNER

TU102 Δ	8-598-431-00	TUNER, FSS 2BTF-WA411
---------	--------------	-----------------------

A

S SERIES BOARD VARIANT PARTS LIST

The parts on this page belong to the following model(s) only:

KV-34SL40T

Note:

The components identified with shading and a critical symbol (**△**) are critical for safety. Replace only with part number specified.

Note:

The components identified by **⊠** in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

REF.NO.	PART NO.	DESCRIPTION	REMARK		
A BOARD VARIANT LIST: KV-34SL40T					
* A-1298-661-A A BOARD, COMPLETE					
CAPACITOR					
C068	1-164-096-11	CERAMIC CHIP	0.01MF		50V
C370	1-163-037-11	CERAMIC CHIP	0.022MF	10%	50V
C375	1-165-319-11	CERAMIC CHIP	0.1MF		50V
C513	1-130-895-00	FILM	0.056MF	5%	400V
C514	1-104-844-11	FILM	0.62MF	5%	200V
C520	1-164-645-11	CERAMIC CHIP	1000PF	10%	500V
C521	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V
C537	1-126-941-11	ELECT	470MF	20%	25V
C539	1-126-935-11	ELECT	470MF	20%	16V
C1501	1-115-462-11	FILM	0.12MF	5%	200V
DIODE					
D005	8-719-991-33	DIODE 1SS133T-77			
D006	1-810-039-31	LED UNIT			
IC					
IC003	8-742-014-11	HYB IC SBX1981-51			
IC1261	8-759-366-77	IC MM1311AD			
CHIP CONDUCTOR					
JR351	1-216-295-91	SHORT			
JR352	1-216-295-91	SHORT			
JR1264	1-216-295-91	SHORT			
RESISTOR					
R059	1-216-047-91	RES, CHIP	820	5%	1/10W
R060	1-216-049-91	RES, CHIP	1K	5%	1/10W
R061	1-216-055-00	RES, CHIP	1.8K	5%	1/10W
R062	1-216-065-91	RES, CHIP	4.7K	5%	1/10W
R063	1-216-073-00	RES, CHIP	10K	5%	1/10W
R365	1-216-101-00	RES, CHIP	150K	5%	1/10W
R374	1-216-125-00	RES, CHIP	1.5M	5%	1/10W
R469	1-216-069-00	RES, CHIP	6.8K	5%	1/10W
R472	1-216-069-00	RES, CHIP	6.8K	5%	1/10W
R511	1-215-885-00	METAL	68	5%	2W
R515	1-216-083-00	RES, CHIP	27K	5%	1/10W
R523	1-216-073-00	RES, CHIP	10K	5%	1/10W
R529	1-208-814-11	RES, CHIP	22K	0.50%	1/10W
R531	1-208-826-11	RES, CHIP	68K	0.50%	1/10W
R533	1-215-902-11	METAL	47K	5%	1W

REF.NO.	PART NO.	DESCRIPTION	REMARK		
R535	1-216-101-00	RES, CHIP	150K	5%	1/10W
R546	1-215-453-00	METAL	22K	1%	1/4W
R1009	1-216-033-00	RES, CHIP	220	5%	1/10W
R1010	1-216-033-00	RES, CHIP	220	5%	1/10W
<u>SWITCH</u>					
S001	1-692-431-21	SWITCH, TACTILE			
S002	1-692-431-21	SWITCH, TACTILE			
S003	1-692-431-21	SWITCH, TACTILE			
S004	1-692-431-21	SWITCH, TACTILE			
S005	1-692-431-21	SWITCH, TACTILE			
S006	1-692-431-21	SWITCH, TACTILE			
S007	1-692-431-21	SWITCH, TACTILE			
<u>TRANSFORMER</u>					
T502 △	1-424-545-11	TRANSFORMER, FERRITE (PMT)			
T503 △	1-453-207-11	FLYBACK TRANSFORMER ASSY, NX-2609//X4C			
<u>TUNER</u>					
TU102 △	8-598-477-00	FSS TUNER BTF-WG411			



V SERIES BOARD VARIANT PARTS LIST

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

The components identified by \boxtimes in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

The parts on this page belong to the following model(s) only:

KV-32V40

REF.NO.	PART NO.	DESCRIPTION	REMARK
---------	----------	-------------	--------

A BOARD VARIANT LIST: KV-32V40

* A-1298-611-A A BOARD, COMPLETE

CAPACITOR

C461	1-126-964-11	ELECT	10MF	20%	50V
C462	1-126-961-11	ELECT	2.2MF	20%	50V
C463	1-126-961-11	ELECT	2.2MF	20%	50V
C464	1-163-017-00	CERAMIC	0.0047MF	10%	50V
C466	1-104-666-11	ELECT	220MF	20%	25V
C467	1-163-017-00	CERAMIC	0.0047MF	10%	50V
C468	1-104-664-11	ELECT	47MF	20%	25V
C470	1-126-961-11	ELECT	2.2MF	20%	50V
C471	1-104-666-11	ELECT	220MF	20%	25V
C472	1-136-173-00	FILM	0.47MF	5%	50V
C473	1-136-169-00	FILM	0.22MF	5%	50V
C474	1-126-942-61	ELECT	1000MF	20%	25V
C475	1-136-169-00	FILM	0.22MF	5%	50V
C476	1-126-942-61	ELECT	1000MF	20%	25V
C477	1-126-942-61	ELECT	1000MF	20%	25V
C513 Δ	1-130-895-00	FILM	0.056MF	5%	400V
C514 Δ	1-104-844-11	FILM	0.62MF	5%	200V
C520	1-164-645-11	CERAMIC CHIP	1000PF	10%	500V
C521	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V
C537	1-126-941-11	ELECT	470MF	20%	25V
C539 Δ	1-126-935-11	ELECT	470MF	20%	16V
C1501	1-115-462-11	FILM	0.12MF	5%	200V

CONNECTOR

CN461 1-564-507-11 PLUG, CONNECTOR 4P

IC

IC461 8-759-980-43 IC TDA2009A

CHIP CONDUCTOR

JR351 1-216-295-91 SHORT
JR352 1-216-295-91 SHORT
JR1417 1-216-295-91 SHORT

COIL

L461 1-410-472-41 INDUCTOR 15UH

REF.NO.	PART NO.	DESCRIPTION	REMARK
---------	----------	-------------	--------

IC LINK

PS461 Δ 1-532-984-11 LINK, IC 2A/90V

TRANSISTOR

Q461 8-729-422-27 TRANSISTOR 2SD601A-Q
Q462 8-729-216-22 TRANSISTOR 2SA1162-G
Q1103 8-729-422-27 TRANSISTOR 2SD601A-Q

RESISTOR

R461	1-216-065-91	RES, CHIP	4.7K	5%	1/10W
R462	1-216-089-91	RES, CHIP	47K	5%	1/10W
R463	1-249-435-11	CARBON	33K	5%	1/4W
R464	1-216-097-91	RES, CHIP	100K	5%	1/10W
R465	1-249-413-11	CARBON	470	5%	1/4W
R466	1-249-385-11	CARBON	2.2	5%	1/4W
R467	1-216-069-00	RES, CHIP	6.8K	5%	1/10W
R469	1-216-055-00	RES, CHIP	1.8K	5%	1/10W
R470	1-216-077-00	RES, CHIP	15K	5%	1/10W
R471	1-216-069-00	RES, CHIP	6.8K	5%	1/10W
R472	1-216-055-00	RES, CHIP	1.8K	5%	1/10W
R473	1-249-398-11	CARBON	27	5%	1/4W
R474	1-216-077-00	RES, CHIP	15K	5%	1/10W
R475	1-249-430-11	CARBON	12K	5%	1/4W
R476	1-249-430-11	CARBON	12K	5%	1/4W
R477	1-249-398-11	CARBON	27	5%	1/4W
R478	1-249-418-11	CARBON	1.2K	5%	1/4W
R479	1-249-418-11	CARBON	1.2K	5%	1/4W
R480	1-249-385-11	CARBON	2.2	5%	1/4W
R481	1-249-385-11	CARBON	2.2	5%	1/4W
R482	1-249-421-11	CARBON	2.2K	5%	1/4W
R483	1-249-421-11	CARBON	2.2K	5%	1/4W
R511 Δ	1-215-885-00	METAL	68	5%	2W
R515	1-216-083-00	RES, CHIP	27K	5%	1/10W
R523	1-216-073-00	RES, CHIP	10K	5%	1/10W
R529	1-208-814-11	RES, CHIP	22K	0.50%	1/10W
\boxtimes R531 Δ	1-208-826-11	RES, CHIP	68K	0.50%	1/10W
R533 Δ	1-215-902-11	METAL	47K	5%	1W
R546	1-215-453-00	METAL	22K	1%	1/4W

TRANSFORMER

T502 Δ 1-424-545-11 TRANSFORMER FERRITE (PMT)
T503 Δ 1-453-207-11 FLYBACK TRANSFORMER ASSY, NX-2609//X4C



V SERIES BOARD VARIANT PARTS LIST

The parts on this page belong to the following model(s) only:

KV-34VL65C/34VL65/32V65CND

Note:

The components identified with shading and a critical symbol (**Δ**) are critical for safety. Replace only with part number specified.

Note:

The components identified by **✖** in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

REF.NO.	PART NO.	DESCRIPTION	REMARK		
A BOARD VARIANT LIST: KV-34VL65C/34VL65/32V65CND					
* A-1298-613-A A BOARD COMPLETE					
CAPACITOR					
C461	1-126-966-11	ELECT	33MF	20%	16V
C478	1-126-934-11	ELECT	220MF	20%	16V
C513	1-130-895-00	FILM	0.056MF	5%	400V
C514	1-104-844-11	FILM	0.62MF	5%	200V
C520	1-164-645-11	CERAMIC CHIP	1000PF	10%	500V
C521	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V
C537	1-126-941-11	ELECT	470MF	20%	25V
C539	1-126-935-11	ELECT	470MF	20%	16V
C1501	1-115-462-11	FILM	0.12MF	5%	200V
CONNECTOR					
CN461	1-564-508-11	PLUG, CONNECTOR 5P			
CN1101	1-573-298-11	CONNECTOR, BOARD TO BOARD			
CN3001	1-573-298-11	CONNECTOR, BOARD TO BOARD			
DIODE					
D368	8-719-991-33	DIODE 1SS133T-77			
CHIP CONDUCTOR					
JR001	1-216-295-91	SHORT			
JR201	1-216-295-91	SHORT			
JR202	1-216-295-91	SHORT			
JR463	1-216-295-91	SHORT			
COIL					
L461	1-408-612-31	INDUCTOR 56UH			
TRANSISTOR					
Q1103	8-729-422-27	TRANSISTOR 2SD601A-Q			
RESISTOR					
R006	1-247-815-91	CARBON	220	5%	1/4W
R008	1-247-815-91	CARBON	220	5%	1/4W
R012	1-216-033-00	RES,CHIP	220	5%	1/10W
R031	1-247-815-91	CARBON	220	5%	1/4W
R040	1-247-815-91	CARBON	220	5%	1/4W
R041	1-216-065-91	RES,CHIP	4.7K	5%	1/10W
R042	1-216-065-91	RES,CHIP	4.7K	5%	1/10W
R045	1-247-815-91	CARBON	220	5%	1/4W

REF.NO.	PART NO.	DESCRIPTION	REMARK		
R088	1-216-033-00	RES,CHIP	220	5%	1/10W
R090	1-216-033-00	RES,CHIP	220	5%	1/10W
R358	1-247-815-91	CARBON	220	5%	1/4W
R359	1-247-815-91	CARBON	220	5%	1/4W
R360	1-247-815-91	CARBON	220	5%	1/4W
R386	1-216-049-91	RES,CHIP	1K	5%	1/10W
R466	1-249-382-11	CARBON	1.2	5%	1/4W
R511 Δ	1-215-885-00	METAL	68	5%	2W
R515	1-216-083-00	RES, CHIP	27K	5%	1/10W
R523	1-216-073-00	RES,CHIP	10K	5%	1/10W
R529	1-208-814-11	RES,CHIP	22K	0.50%	1/10W
✖ R531 Δ	1-208-826-11	RES,CHIP	68K	0.50%	1/10W
R533 Δ	1-215-902-11	METAL	47K	5%	1W
R546	1-215-453-00	METAL	22K	1%	1/4W

TRANSFORMER

T502 Δ	1-424-545-11	TRANSFORMER FERRITE (PMT)
T503 Δ	1-453-207-11	FLYBACK TRANSFORMER ASSY, NX-2609//X4C

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

The components identified by \boxtimes in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.



V SERIES BOARD VARIANT PARTS LIST

The parts on this page belong to the following model(s) only:

KV-35V65CND/37VL65/37VL65C

REF.NO.	PART NO.	DESCRIPTION	REMARK
---------	----------	-------------	--------

A BOARD VARIANT LIST: KV-35V65CND/37VL65/37VL65C

* A-1298-647-A A BOARD, COMPLETE

CAPACITOR

C069	1-126-964-11	ELECT	10MF	20%	50V
C461	1-126-964-11	ELECT	10MF	20%	50V
C478	1-126-934-11	ELECT	220MF	20%	16V
C479	1-126-964-11	ELECT	10MF	20%	50V
C513 Δ	1-129-720-00	FILM	0.033MF	5%	630V
C514 Δ	1-136-540-11	FILM	0.82MF	5%	200V
C520	1-101-821-00	CERAMIC CHIP	0.0022MF		500V
C521	1-164-182-11	CERAMIC CHIP	0.0033MF	10%	50V
C537	1-126-942-61	ELECT	1000MF	20%	25V
C539 Δ	1-126-942-61	ELECT	1000MF	20%	25V
C542	1-106-383-00	MYLAR	0.047MF	10%	200V

CONNECTOR

CN461	1-564-508-11	PLUG, CONNECTOR 5P
CN1101	1-573-298-11	CONNECTOR, BOARD TO BOARD
CN3001	1-573-298-11	CONNECTOR, BOARD TO BOARD

DIODE

D368	8-719-991-33	DIODE 1SS133T-77
------	--------------	------------------

CHIP CONDUCTOR

JR001	1-216-295-91	SHORT
JR201	1-216-295-91	SHORT
JR202	1-216-295-91	SHORT
JR463	1-216-295-91	SHORT

COIL

L461	1-408-617-31	INDUCTOR 180UH
L541	1-406-677-11	INDUCTOR

TRANSISTOR

Q1103	8-729-120-28	TRANSISTOR 2SC1623-L5L6
-------	--------------	-------------------------

RESISTOR

R006	1-247-815-91	CARBON	220	5%	1/4W
R008	1-247-815-91	CARBON	220	5%	1/4W
R012	1-216-033-00	RES,CHIP	220	5%	1/10W
R031	1-247-815-91	CARBON	220	5%	1/4W
R040	1-247-815-91	CARBON	220	5%	1/4W

REF.NO.	PART NO.	DESCRIPTION	REMARK
---------	----------	-------------	--------

R041	1-216-065-91	"RES,CHIP"	4.7K	5%	1/10W
R042	1-216-065-91	"RES,CHIP"	4.7K	5%	1/10W
R045	1-247-815-91	CARBON	220	5%	1/4W
R069	1-216-073-00	RES,CHIP	10K	5%	1/10W
R085	1-216-073-00	RES,CHIP	10K	5%	1/10W
R088	1-216-033-00	RES,CHIP	220	5%	1/10W
R090	1-216-033-00	RES,CHIP	220	5%	1/10W
R358	1-247-815-91	CARBON	220	5%	1/4W
R359	1-247-815-91	CARBON	220	5%	1/4W
R360	1-247-815-91	CARBON	220	5%	1/4W
R386	1-216-049-91	RES,CHIP	1K	5%	1/10W
R511 Δ	1-215-886-11	METAL	100	5%	2W
R515	1-216-077-00	RES,CHIP	15K	5%	1/10W
R523	1-216-071-00	RES,CHIP	8.2K	5%	1/10W
R529	1-208-812-11	RES,CHIP	18K	0.50%	1/10W
\boxtimes R531 Δ	1-208-838-11	RES,CHIP	220K	0.50%	1/10W
R533 Δ	1-215-878-00	METAL	33K	5%	1W
R541	1-249-377-11	CARBON	0.47	5%	1/4W
R542	1-249-397-11	CARBON	22	5%	1/4W
R546	1-215-451-00	METAL	18K	1%	1/4W

TRANSFORMER

T502 Δ	1-429-408-11	TRANSFORMER FERRITE (PMT)
T503 Δ	X-4034-797-1	FLYBACK TRANSFORMER ASSY, NX-3005//J1C
T504	1-413-059-00	TRANSFORMER FERRITE (DFT)



COMPLETE PARTS LISTING

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

REF.NO.	PART NO.	DESCRIPTION	REMARK
<div><div>AV</div><div><div>* A-1298-612-A AV BOARD, COMPLETE</div><div>(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)</div></div></div>			
<u>CAPACITOR</u>			
C101	1-126-960-11	ELECT	1MF 20% 50V
C102	1-164-161-11	CERAMIC CHIP	0.0022MF 10% 50V
C104	1-126-964-11	ELECT	10MF 20% 50V
C106	1-104-664-11	ELECT	47MF 20% 25V
C108	1-126-933-11	ELECT	100MF 20% 16V
C109	1-163-259-91	CERAMIC CHIP	220PF 5% 50V
C110	1-104-760-11	CERAMIC CHIP	0.047MF 10% 50V
C111	1-126-960-11	ELECT	1MF 20% 50V
C113	1-126-934-11	ELECT	220MF 20% 16V
C1904	1-102-129-00	CERAMIC	0.01MF 10% 50V
C1905	1-126-964-11	ELECT	10MF 20% 50V
C1906	1-102-129-00	CERAMIC	0.01MF 10% 50V
C1907	1-126-964-11	ELECT	10MF 20% 50V
C1908	1-163-009-11	CERAMIC CHIP	0.001MF 10% 50V
C1909	1-163-009-11	CERAMIC CHIP	0.001MF 10% 50V
<u>CONNECTOR</u>			
CN101	1-573-301-21	CONNECTOR, BOARD TO BOARD	20P
CN102	1-573-979-21	CONNECTOR, BOARD TO BOARD	11P
CN103 *	1-564-507-11	PLUG, CONNECTOR	4P
CN106 *	1-564-506-11	PLUG, CONNECTOR	3P
<u>DIODE</u>			
D101	8-719-109-89	DIODE RD5.6ESB2	
D103	8-719-991-33	DIODE 1SS133T-77	
D104	8-719-991-33	DIODE 1SS133T-77	
D105	8-719-991-33	DIODE 1SS133T-77	
D106	8-719-991-33	DIODE 1SS133T-77	
<u>IC</u>			
IC1901	8-752-058-68	IC CXA1315M	
IC1902	8-759-470-63	IC NJM2145M-TE2	
<u>CHIP CONDUCTOR</u>			
JR101	1-216-295-91	SHORT	
JR102	1-216-295-91	SHORT	
JR103	1-216-295-91	SHORT	
JR105	1-216-295-91	SHORT	

REF.NO.	PART NO.	DESCRIPTION	REMARK
<u>COIL</u>			
L102	1-410-470-11	INDUCTOR	10UH
L105	1-408-421-00	INDUCTOR	100UH
<u>TRANSISTOR</u>			
Q101	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q103	8-729-216-22	TRANSISTOR 2SA1162-G	
Q104	8-729-216-22	TRANSISTOR 2SA1162-G	
Q105	8-729-216-22	TRANSISTOR 2SA1162-G	
Q1901	8-729-216-22	TRANSISTOR 2SA1162-G	
Q1902	8-729-216-22	TRANSISTOR 2SA1162-G	
<u>RESISTOR</u>			
R101	1-216-065-91	RES, CHIP	4.7K 5% 1/10W
R102	1-216-083-00	RES, CHIP	27K 5% 1/10W
R103	1-216-689-11	RES, CHIP	39K 5% 1/10W
R104	1-216-045-00	RES, CHIP	680 5% 1/10W
R106	1-216-081-00	RES, CHIP	22K 5% 1/10W
R107	1-216-081-00	RES, CHIP	22K 5% 1/10W
R108	1-216-081-00	RES, CHIP	22K 5% 1/10W
R109	1-216-081-00	RES, CHIP	22K 5% 1/10W
R112	1-216-057-00	RES, CHIP	2.2K 5% 1/10W
R113	1-216-097-91	RES, CHIP	100K 5% 1/10W
R114	1-216-121-91	RES, CHIP	1M 5% 1/10W
R115	1-216-073-00	RES, CHIP	10K 5% 1/10W
R116	1-216-073-00	RES, CHIP	10K 5% 1/10W
R117	1-216-065-91	RES, CHIP	4.7K 5% 1/10W
R118	1-216-295-91	SHORT	
R121	1-216-049-91	RES, CHIP	1K 5% 1/10W
R1904	1-216-073-00	RES, CHIP	10K 5% 1/10W
R1905	1-216-073-00	RES, CHIP	10K 5% 1/10W
R2904	1-216-033-00	RES, CHIP	220 5% 1/10W
R2905	1-216-033-00	RES, CHIP	220 5% 1/10W
R2909	1-216-073-00	RES, CHIP	10K 5% 1/10W
R2910	1-216-073-00	RES, CHIP	10K 5% 1/10W
R2912	1-216-073-00	RES, CHIP	10K 5% 1/10W
R2913	1-216-073-00	RES, CHIP	10K 5% 1/10W
R2914	1-216-073-00	RES, CHIP	10K 5% 1/10W
<u>TUNER</u>			
TU101 Δ	8-598-430-00	TUNER, FSS	BTF-FA401

REF.NO.	PART NO.	DESCRIPTION	REMARK
B			
* A-1135-948-A B BOARD, COMPLETE (KV-32V40 only)			
* A-1135-949-A B BOARD, COMPLETE (KV-34VL65C/32V65CND/34VL65/35V65CND/ 37VL65/37VL65C only)			
* A-1135-950-A B BOARD, COMPLETE (KV-32S40/34SL40/34SL40C/32S45/34SL45/35S40/35S45/ 37SL45/34SL40T only)			
<u>CAPACITOR</u>			
C3501	1-104-664-11	ELECT	47MF 20% 25V
C3502	1-163-231-11	CERAMIC CHIP	15PF 5% 50V
C3503	1-163-021-91	CERAMIC	0.01MF 10% 50V
C3504	1-126-964-11	ELECT	10MF 20% 50V
C3505	1-163-131-00	CERAMIC	390PF 5% 50V
C3506	1-163-021-91	CERAMIC CHIP	0.01MF 10% 50V
C3507	1-126-963-11	ELECT	4.7MF 20% 50V
C3508	1-163-021-91	CERAMIC CHIP	0.01MF 10% 50V
C3509	1-126-961-11	ELECT	2.2MF 20% 50V
C3510	1-163-229-11	CERAMIC CHIP	12PF 5% 50V
C3511	1-126-964-11	ELECT	10MF 20% 50V
C3512	1-163-133-00	CERAMIC CHIP	470PF 5% 50V
C3513	1-163-131-00	CERAMIC CHIP	390PF 5% 50V
C3514	1-163-009-11	CERAMIC CHIP	0.001MF 10% 50V
C3515	1-126-963-11	ELECT	4.7MF 20% 50V
C3516	1-163-089-00	CERAMIC CHIP	6PF 0.5PF 50V
C3517	1-163-021-91	CERAMIC CHIP	0.01MF 10% 50V
C3518	1-126-941-11	ELECT	470MF 20% 25V
C3519	1-163-021-91	CERAMIC CHIP	0.01MF 10% 50V
C3520	1-163-133-00	CERAMIC CHIP	470PF 5% 50V
C3521	1-104-664-11	ELECT	47MF 20% 25V
C3522	1-126-964-11	ELECT	10MF 20% 50V
C3523	1-163-021-91	CERAMIC CHIP	0.01MF 10% 50V
C3524	1-104-664-11	ELECT	47MF 20% 25V
C3525	1-163-021-91	CERAMIC CHIP	0.01MF 10% 50V
C3526	1-163-038-91	CERAMIC CHIP	0.1MF 25V
C3527	1-163-038-91	CERAMIC CHIP	0.1MF 25V
C3528	1-164-222-11	CERAMIC CHIP	0.22MF 25V
C3529	1-163-038-91	CERAMIC CHIP	0.1MF 25V
C3530	1-163-037-11	CERAMIC CHIP	0.022MF 10% 50V
C3532	1-164-004-11	CERAMIC CHIP	0.1MF 10% 25V
C3533	1-163-021-91	CERAMIC CHIP	0.01MF 10% 50V
C3534	1-163-021-91	CERAMIC CHIP	0.01MF 10% 50V
C3535	1-104-664-11	ELECT	47MF 20% 25V
C3536	1-126-964-11	ELECT	10MF 20% 50V

REF.NO.	PART NO.	DESCRIPTION	REMARK
C3537	1-163-231-11	CERAMIC CHIP	15PF 5% 50V
C3538	1-163-021-91	CERAMIC CHIP	0.01MF 10% 50V
C3539	1-163-021-91	CERAMIC CHIP	0.01MF 10% 50V
C3540	1-163-231-11	CERAMIC CHIP	15PF 5% 50V
C3541	1-104-664-11	ELECT	47MF 20% 25V
C3542	1-163-021-91	CERAMIC CHIP	0.01MF 10% 50V
C3543	1-104-664-11	ELECT	47MF 20% 25V
C3544	1-104-664-11	ELECT	47MF 20% 25V
C3545	1-164-004-11	CERAMIC CHIP	0.1MF 10% 25V
C3548	1-164-004-11	CERAMIC CHIP	0.1MF 10% 25V
C3549	1-126-964-11	ELECT	10MF 20% 50V
C3550	1-104-664-11	ELECT	47MF 20% 25V
C3551	1-163-021-91	CERAMIC CHIP	0.01MF 10% 50V
C3553	1-126-941-11	ELECT	470MF 20% 25V
C3556	1-128-551-11	ELECT	22MF 20% 25V
C3557	1-163-235-11	CERAMIC CHIP	22PF 5% 50V
<u>CONNECTOR</u>			
CN3502 * 1-573-978-21 CONNECTOR, BOARD TO BOARD 11P (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)			
CN3561 * 1-691-616-21 CONNECTOR, BOARD TO BOARD 15P (KV-32V40/34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)			
CN3570 * 1-764-816-11 CONNECTOR, BOARD TO BOARD 20P (KV-32S40/34SL40/34SL40C/32S45/34SL45/35S40/35S45/37SL45/34SL40T only)			
<u>FILTER</u>			
FL3501	1-239-847-11	FILTER, LOW PASS	
FL3502	1-239-847-11	FILTER, LOW PASS	
FL3503	1-239-847-11	FILTER, LOW PASS	
<u>IC</u>			
IC3501	8-759-065-82	IC MM1093ND	
IC3502	8-752-385-80	IC CXD2073S	
IC3503	8-759-231-53	IC TA7805S	
<u>COIL</u>			
L3501	1-410-470-11	INDUCTOR 10UH	
L3502	1-410-466-41	INDUCTOR 4.7UH	
L3503	1-410-470-11	INDUCTOR 10UH	
L3504	1-410-470-11	INDUCTOR 10UH	
L3505	1-410-470-11	INDUCTOR 10UH	



COMPLETE PARTS LISTING

REF.NO.	PART NO.	DESCRIPTION	REMARK			REF.NO.	PART NO.	DESCRIPTION	REMARK		
<u>TRANSISTOR</u>						R3537	1-216-043-91	RES, CHIP	560	5%	1/10W
						R3538	1-216-071-00	RES, CHIP	8.2K	5%	1/10W
Q3501	8-729-422-27	TRANSISTOR 2SD601A-Q				R3539	1-216-089-91	RES, CHIP	47K	5%	1/10W
Q3502	8-729-216-22	TRANSISTOR 2SA1162-G				R3540	1-216-049-91	RES, CHIP	1K	5%	1/10W
Q3503	8-729-422-27	TRANSISTOR 2SD601A-Q				R3541	1-216-081-00	RES, CHIP	22K	5%	1/10W
Q3504	8-729-216-22	TRANSISTOR 2SA1162-G									
Q3505	8-729-422-27	TRANSISTOR 2SD601A-Q				R3542	1-216-041-00	RES, CHIP	470	5%	1/10W
						R3543	1-216-035-00	RES, CHIP	270	5%	1/10W
Q3506	8-729-216-22	TRANSISTOR 2SA1162-G				R3544	1-216-057-00	RES, CHIP	2.2K	5%	1/10W
Q3507	8-729-216-22	TRANSISTOR 2SA1162-G				R3545	1-216-043-91	RES, CHIP	560	5%	1/10W
Q3509	8-729-216-22	TRANSISTOR 2SA1162-G				R3546	1-216-071-00	RES, CHIP	8.2K	5%	1/10W
Q3510	8-729-422-27	TRANSISTOR 2SD601A-Q									
Q3516	8-729-216-22	TRANSISTOR 2SA1162-G				R3547	1-216-089-91	RES, CHIP	47K	5%	1/10W
						R3548	1-216-081-00	RES, CHIP	22K	5%	1/10W
Q3555	8-729-216-22	TRANSISTOR 2SA1162-G				R3549	1-216-049-91	RES, CHIP	1K	5%	1/10W
						R3550	1-208-774-11	RES, CHIP	470	0.50%	1/10W
<u>RESISTOR</u>						R3551	1-208-764-11	RES, CHIP	180	0.50%	1/10W
R3501	1-216-091-00	RES, CHIP	56K	5%	1/10W	R3565	1-216-295-91	SHORT			
R3502	1-216-081-00	RES, CHIP	22K	5%	1/10W	R3566	1-216-025-91	RES, CHIP	100	5%	1/10W
R3503	1-216-009-00	RES, CHIP	22	5%	1/10W	R3568	1-216-025-91	RES, CHIP	100	5%	1/10W
R3504	1-216-029-00	RES, CHIP	150	5%	1/10W	R3569	1-216-041-00	RES, CHIP	470	5%	1/10W
R3505	1-216-037-00	RES, CHIP	330	5%	1/10W	R3578	1-216-081-00	RES, CHIP	22K	5%	1/10W
R3506	1-216-035-00	RES, CHIP	270	5%	1/10W	R3579	1-216-081-00	RES, CHIP	22K	5%	1/10W
R3507	1-216-057-00	RES, CHIP	2.2K	5%	1/10W	R3580	1-216-295-91	SHORT			
R3508	1-216-043-91	RES, CHIP	560	5%	1/10W	R3596	1-216-057-00	RES, CHIP	2.2K	5%	1/10W
R3509	1-216-075-00	RES, CHIP	12K	5%	1/10W	R3597	1-216-057-00	RES, CHIP	2.2K	5%	1/10W
R3510	1-216-049-91	RES, CHIP	1K	5%	1/10W	R3599	1-208-774-11	RES, CHIP	470	0.50%	1/10W
R3511	1-216-065-91	RES, CHIP	4.7K	5%	1/10W	<u>CRYSTAL</u>					
R3512	1-216-065-91	RES, CHIP	4.7K	5%	1/10W						
R3513	1-216-041-00	RES, CHIP	470	5%	1/10W	X3501	1-567-505-11	OSCILLATOR, CRYSTAL			
R3514	1-216-121-91	RES, CHIP	1M	5%	1/10W						
R3515	1-216-077-00	RES, CHIP	15K	5%	1/10W						
R3516	1-216-037-00	RES, CHIP	330	5%	1/10W						
R3517	1-216-077-00	RES, CHIP	15K	5%	1/10W						
R3518	1-216-067-00	RES, CHIP	5.6K	5%	1/10W						
R3520	1-208-766-11	RES, CHIP	220	0.50%	1/10W						
R3521	1-208-766-11	RES, CHIP	220	0.50%	1/10W						
R3522	1-208-774-11	RES, CHIP	470	0.50%	1/10W						
R3523	1-208-778-11	RES, CHIP	680	0.50%	1/10W						
R3524	1-208-794-11	RES, CHIP	3.3K	0.50%	1/10W						
R3526	1-208-776-11	RES, CHIP	560	0.50%	1/10W						
R3527	1-208-824-11	RES, CHIP	56K	0.50%	1/10W						
R3529	1-216-295-91	SHORT									
R3531	1-216-295-91	SHORT									
R3534	1-216-295-91	SHORT									
R3535	1-216-295-91	SHORT									
R3536	1-216-057-00	RES, CHIP	2.2K	5%	1/10W						

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

COMPLETE PARTS LISTING

REF.NO.	PART NO.	DESCRIPTION	REMARK
C			
* A-1331-837-A C BOARD, COMPLETE (KV-32V40/34VL65C/32V65CND/34VL65/32S40/34SL40/34SL40C/32S45/34SL45/34SL40T only)			
* A-1331-843-A C BOARD, COMPLETE (KV-35V65CND/37VL65/37VL65C/35S40/35S45/37SL45 only)			
4-382-854-11	SCREW (M3X10), P, SW (+)		
CAPACITOR			
C1750	1-137-528-11	FILM 0.1MF 10% 250V	
C1751	1-107-652-11	ELECT 10MF 20% 250V	
C1790	1-102-129-00	CERAMIC CHIP 0.01MF 10% 50V	
C1791	1-126-968-11	ELECT 100MF 20% 50V	
C1792	1-102-108-00	CERAMIC CHIP 150PF 10% 50V	
C1794	1-107-651-11	ELECT 4.7MF 20% 250V (KV-35V65CND/37VL65/37VL65C/35S40/35S45/37SL45 only)	
C1795	1-102-074-00	CERAMIC CHIP 0.001MF 10% 50V	
C1799	1-162-114-00	CERAMIC CHIP 0.0047MF 2KV	
CONNECTOR			
CN1761*	1-564-509-11	PLUG, CONNECTOR 6P	
CN1764*	1-564-508-11	PLUG, CONNECTOR 5P	
CN1765	1-695-915-11	TAB (CONTACT)	
DIODE			
D1790	8-719-991-33	DIODE 1SS133T-77	
D1791	8-719-908-03	DIODE GP08D	
D1792	8-719-908-03	DIODE GP08D (KV-35V65CND/37VL65/37VL65C/35S40/35S45/37SL45 only)	
D1793	8-719-908-03	DIODE GP08D	
D1794	8-719-908-03	DIODE GP08D	
D1795	8-719-908-03	DIODE GP08D	
IC			
IC1701	8-759-535-08	IC TDA6108Q	
JACK			
J1761 Δ	1-251-388-11	SOCKET, CRT	
COIL			
L1790	1-410-671-31	INDUCTOR 47UH	

REF.NO.	PART NO.	DESCRIPTION	REMARK
TRANSISTOR			
Q1790	8-729-119-76	TRANSISTOR 2SA1175-HFE	
RESISTOR			
R1750	1-247-870-11	CARBON 43K 5% 1/4W	
R1763	1-260-099-11	CARBON 1K 5% 1/2W	
R1764	1-247-807-31	CARBON 100 5% 1/4W	
R1773	1-260-099-11	CARBON 1K 5% 1/2W	
R1774	1-247-807-31	CARBON 100 5% 1/4W	
R1783	1-260-099-11	CARBON 1K 5% 1/2W	
R1784	1-247-807-31	CARBON 100 5% 1/4W	
R1788	1-216-349-00	METAL OXIDE 1 5% 1W F	
R1789	1-249-437-11	CARBON 47K 5% 1/4W	
R1790	1-216-378-11	METAL OXIDE 5.6 5% 2W F (KV-32V40/34VL65C/32V65CND/34VL65/32S40/34SL40/34SL40C/32S45/34SL45/34SL40T only)	
R1790	1-216-369-00	METAL OXIDE 1 5% 2W F (KV-35V65CND/37VL65/37VL65C/35S40/35S45/37SL45 only)	
R1792	1-247-815-91	CARBON 220 5% 1/4W	
R1793	1-247-866-11	CARBON 30K 5% 1/4W	
R1794	1-260-132-11	CARBON 560K 5% 1/2W (KV-35V65CND/37VL65/37VL65C/35S40/35S45/37SL45 only)	
R1795	1-260-087-11	CARBON 100 5% 1/2W	
R1796	1-216-378-11	METAL OXIDE 5.6 5% 2W F (KV-32V40/34VL65C/32V65CND/34VL65/32S40/34SL40/34SL40C/32S45/34SL45/34SL40T only)	
R1796	1-216-369-00	METAL OXIDE 1 5% 2W F (KV-35V65CND/37VL65/37VL65C/35S40/35S45/37SL45 only)	
R1797	1-260-123-11	CARBON 100K 5% 1/2W	



COMPLETE PARTS LISTING

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

REF.NO.	PART NO.	DESCRIPTION	REMARK
G			
	<ul style="list-style-type: none"> * A-1316-389-A G BOARD, COMPLETE (KV-32V40/32S40/34SL40/32S45/34SL45 only) * A-1316-390-A G BOARD, COMPLETE (KV-34VL65C only) * A-1316-391-A G BOARD, COMPLETE (KV-32V65CND/34VL65 only) * A-1316-395-A G BOARD, COMPLETE (KV-34SL40C only) * A-1316-396-A G BOARD, COMPLETE KV-34SL40T only) * A-1316-399-A G BOARD, COMPLETE (KV-35S40/35S45/37SL45 only) * A-1316-405-A G BOARD, COMPLETE (KV-35V65CND/37VL65 only) * A-1316-406-A G BOARD, COMPLETE (KV-37VL65C only) 		
	1-533-223-11	HOLDER, FUSE	
	4-382-854-11	SCREW(M3X10), P, SW (+)	
CAPACITOR			
C601	1-136-346-21	FILM 0.22MF 20% 125V (KV-35S40/35S45/37SL45/35V65CND/37VL65/37VL65C only)	
C602	1-126-964-11	ELECT 10MF 20% 50V	
C603 Δ	1-113-907-51	CERAMIC CHIP 0.0022MF 20% 250V (KV-34VL65C/34SL40C/37VL65C only)	
C603 Δ	1-113-903-11	CERAMIC 0.001MF 20% 250V (KV-32V40/32S40/34SL40/32S45/34SL45/32V65CND/34VL65/35V65CND/37VL65/34SL40T/35S40/35S45/37SL45 only)	
C604 Δ	1-136-346-21	FILM 0.22MF 20% 300V (KV-34SL40T only)	
C605 Δ	1-136-311-11	FILM 0.47MF 20% 300V (KV-34VL65C/37VL65C/34SL40C only)	
C605 Δ	1-136-346-21	FILM 0.22MF 20% 125V (KV-32V40/32S40/34SL40/32S45/34SL45/32V65CND/34VL65/35V65CND/37VL65/34SL40T/35S40/35S45/37SL45 only)	
C606 Δ	1-117-894-11	ELECT 560MF 20% 250V	
C607 Δ	1-117-894-11	ELECT 560MF 20% 250V	
C608	1-165-127-11	CERAMIC CHIP 470PF 10% 500V	
C609	1-136-175-00	FILM 0.68MF 5% 50V	
C610	1-136-175-00	FILM 0.68MF 5% 50V	
C611	1-136-169-00	FILM 0.22MF 5% 50V (KV-32V40/32S40/34SL40/32S45/34SL45/34SL40C/34SL40T/35S40/35S45/37VL65 only)	
C611	1-136-171-00	FILM 0.33MF 5% 50V (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	

REF.NO.	PART NO.	DESCRIPTION	REMARK
C612	1-136-169-00	FILM 0.22MF 5% 50V (KV-32V40/32S40/34SL40/32S45/34SL45/34SL40C/34SL40T/35S40/35S45/37VL65 only)	
C612	1-136-171-00	FILM 0.33MF 5% 50V KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
C613	1-164-646-11	CERAMIC CHIP 2200PF 10% 500V	
C615	1-129-722-00	FILM 0.047MF 5% 630V	
C616 Δ	1-117-699-11	CERAMIC CHIP 0.001MF 20% 250V (KV-32V40/32S40/34SL40/32S45/34SL45/32V65CND/34VL65/34SL40T/35S40/35S45/37SL45/35V65CND/37VL65 only)	
C624	1-126-961-11	ELECT 2.2MF 20% 50V	
C628 Δ	1-113-924-11	CERAMIC CHIP 0.0047MF 20% 250V	
C629 Δ	1-107-679-91	ELECT 10MF 20% 450V (KV-34VL65C/34SL40C/37VL65C only)	
C629 Δ	1-107-680-91	ELECT 22MF 20% 450V (KV-32V40/32S40/34SL40/32S45/34SL45/32V65CND/34VL65/34SL40T/35S40/35S45/37SL45/35V65CND/37VL65 only)	
C630	1-130-471-00	MYLAR 0.001MF 5% 50V	
C631	1-137-605-11	FILM 0.01MF 10% 250V	
C633	1-130-471-00	MYLAR 0.001MF 5% 50V	
C634	1-130-467-00	MYLAR 470PF 5% 50V	
C635	1-130-471-00	MYLAR 0.001MF 5% 50V	
C636	1-126-965-11	ELECT 22MF 20% 50V	
C637	1-126-940-11	ELECT 330MF 20% 25V	
C640 Δ	1-113-924-11	CERAMIC CHIP 0.0047MF 20% 250V	
C641	1-128-550-11	ELECT 2200MF 20% 50V	
C643	1-107-641-11	ELECT 220MF 20% 160V	
C647	1-104-665-11	ELECT 100MF 20% 25V	
C648	1-126-965-11	ELECT 22MF 20% 50V (KV-37VL65C/34SL40C/34VL65C only)	
C650	1-104-664-11	ELECT 47MF 20% 25V	
C651	1-137-366-11	FILM 0.0022MF 5% 50V	
C652	1-106-351-00	MYLAR 0.0022MF 20% 200V	
C653	1-107-636-11	ELECT 10MF 20% 160V	
C654	1-164-625-11	CERAMIC CHIP 680PF 10% 500V	
C655	1-164-625-11	CERAMIC CHIP 680PF 10% 500V	
C656	1-164-625-11	CERAMIC CHIP 680PF 10% 500V	
C657	1-164-625-11	CERAMIC CHIP 680PF 10% 500V	
C660	1-126-767-11	ELECT 1000MF 20% 16V	
C690	1-164-645-11	CERAMIC CHIP 1000PF 10% 500V	
C691	1-164-645-11	CERAMIC CHIP 1000PF 10% 500V	

Note:

The components identified with shading and a critical symbol (▲) are critical for safety. Replace only with part number specified.

Note:

Les composants identifiés par un trame et une marque ▲ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

COMPLETE PARTS LISTING

REF.NO.	PART NO.	DESCRIPTION	REMARK
CONNECTOR			
CN601	1-573-963-11	PIN, CONNECTOR (PC BOARD) 3P (KV-35S40/35S45/37SL45/35V65CND/37VL65/37VL65C only)	
CN602	1-580-844-11	PIN, CONNECTOR (POWER) 2P	
CN603	1-573-963-11	PIN, CONNECTOR (PC BOARD) 3P KV-35S40/35S45/37SL45/35V65CND/37VL65 only)	
CN604	1-573-963-11	PIN, CONNECTOR (PC BOARD) 3P (KV-32V40/32S40/34SL40/32S45/34SL45/34VL65C/32VCND/34VL65/ 34SL40C/34SL40T/35S40/35S45/37SL45 only)	
CN641	1-564-515-11	PLUG, CONNECTOR 12P	
CN643	1-508-784-00	PIN, CONNECTOR (5MM PITCH) 1P (KV-32V40/32S40/34SL40/32S45/34SL45/34VL65C/32VCND/34VL65/ 34SL40C/35S40/35S45/37SL45/35V65CND/35VL65/37VL65C only)	
DIODE			
D600 ▲	8-719-991-33	DIODE 1SS133T-77	
D601	8-719-991-33	DIODE 1SS133T-77	
D602 ▲	8-719-510-53	DIODE D4SB60L	
D603	8-719-052-90	DIODE D1NL40-TA2 (KV-32V40/32S40/34SL40/32S45/34SL45/32V65CND/34VL65/ 34SL40T/35S40/35S45/37SL45/35V65CND/37VL65 only)	
D604	8-719-052-90	DIODE D1NL40-TA2 (KV-32V40/32S40/34SL40/32S45/34SL45/32V65CND/34VL65/ 34SL40T/35S40/35S45/37SL45/35V65CND/37VL65 only)	
D612	8-719-991-33	DIODE 1SS133T-77	
D613	8-719-991-33	DIODE 1SS133T-77	
D614	8-719-991-33	DIODE 1SS133T-77	
D621 ▲	8-719-911-55	DIODE U05G	
D622 ▲	8-719-911-55	DIODE U05G	
D623	8-719-055-18	DIODE ERA22-08TP3	
D624	8-719-991-33	DIODE 1SS133T-77	
D625	8-719-991-33	DIODE 1SS133T-77 (KV-32V40/32S40/34SL40/32S45/34SL45/34VL65C/32V65CND/ 34VL65/34SL40C/34SL40T/35S40/35S45/37SL45/37VL65C only)	
D626	8-719-109-93	DIODE RD6.2ESB2	
D627	8-719-510-48	DIODE D1N20R	
D628	8-719-063-70	DIODE D1NL20U	
D631	8-719-109-69	DIODE RD3.6ES-B2 (KV-37VL65C/34SL40C/34VL65C only)	
D632	8-719-063-70	DIODE D1NL20U-TA2 (KV-37VL65C/34SL40C/34VL65C only)	
D641	8-719-052-92	DIODE D10SBS4F	
D642 ▲	8-719-510-12	DIODE D10SC4M	
D643	8-719-028-45	DIODE D2L20U	
D644	8-719-028-45	DIODE D2L20U	
D645	8-719-028-45	DIODE D2L20U	
D646	8-719-028-45	DIODE D2L20U	
D647	8-719-063-70	DIODE D1NL20U	

REF.NO.	PART NO.	DESCRIPTION	REMARK
D648	8-719-057-52	DIODE EZ0150AV1	
D649	8-719-510-02	DIODE D1NS4	
D650	8-719-510-02	DIODE D1NS4	
FUSE			
F601 ▲	1-576-193-11	FUSE 6.3A/125V (KV-32V40/32S40/34SL40/32S45/34SL45/32V65CND/34VL65/ 34SL40T/35S40/35S45/37SL45/35V65CND/37VL65 only)	
F601 ▲	1-532-506-51	FUSE 6.3A/250V (KV-37VL65C/34SL40C/34VL65C only)	
FERRITE BEAD			
FB601	1-410-396-41	FERRITE	0.45UH
FB602	1-410-396-41	FERRITE	0.45UH
FB603	1-410-396-41	FERRITE	0.45UH
FB604	1-410-396-41	FERRITE	0.45UH
FB641	1-410-397-21	FERRITE	1.1UH
FB642	1-410-397-21	FERRITE	1.1UH
FB645	1-410-397-21	FERRITE	1.1UH
FB647	1-410-397-21	FERRITE	1.1UH
IC			
IC601 ▲	8-729-041-12	TRANSISTOR	MX0841AB-F
IC622	8-759-450-47	IC	BA05T
IC641	8-759-198-03	IC	PQ09RF21
IC643	8-749-012-13	IC	DM-58
COIL			
L642	1-412-529-11	INDUCTOR	22UH
TRANSISTOR			
Q621 ▲	8-729-044-30	TRANSISTOR	2SK2845-LB102
Q622	8-729-119-78	TRANSISTOR	2SC2785-HFE
Q644	8-729-119-78	TRANSISTOR	2SC2785-HFE
Q645	8-729-119-76	TRANSISTOR	2SA1175-HFE
Q646	8-729-119-76	TRANSISTOR	2SA1175-HFE
Q647	8-729-119-78	TRANSISTOR	2SC2785-HFE
Q648	8-729-922-39	TRANSISTOR	2SD2144S-V
RESISTOR			
R603 ▲	1-219-776-11	CARBON	2.2M 10% 1/2W (KV-32V40/32S40/34SL40/32S45/34SL45/32V65CND/ 34VL65/34SL40T/35S40/35S45/37SL45/35V65CND/37VL65 only)
R603 ▲	1-247-289-00	CARBON	8.2M 5% 1W (KV-34VL65C/34SL40C/37VL65C only)
R607 ▲	1-202-933-61	FUSIBLE	0.1 10% 1/2W F
R608 ▲	1-216-373-11	METAL	2.2 5% 2W F



COMPLETE PARTS LISTING

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

REF.NO.	PART NO.	DESCRIPTION	REMARK
R611 Δ	1-216-373-11	METAL 2.2 5% 2W F	
R612	1-215-903-11	METAL 68K 5% 2W F	
R613	1-215-903-11	METAL 68K 5% 2W F	
R614	1-215-903-11	METAL 68K 5% 2W F	
R615	1-215-903-11	METAL 68K 5% 2W F	
R618	1-249-425-11	CARBON 4.7K 5% 1/4W	
R619	1-249-425-11	CARBON 4.7K 5% 1/4W	
R620	1-249-425-11	CARBON 4.7K 5% 1/4W	
R621	1-249-429-11	CARBON 10K 5% 1/4W	
R622	1-247-863-91	CARBON 22K 5% 1/4W	
R623 Δ	1-205-943-11	CEMENTED 1 5% 20W	
		(KV-32V40/32S40/34SL40/32S45/34SL45/32V65CND/34VL65/34SL40T/35S40/35S45/37SL45/35V65CND/37VL65 only)	
R623 Δ	1-243-032-11	CEMENTED 3.9 5% 20W	
		(KV-34VL65C/34SL40C/37VL65C only)	
R624	1-260-131-11	CARBON 470K 5% 1/2W	
R625	1-260-131-11	CARBON 470K 5% 1/2W	
R626	1-249-425-11	CARBON 4.7K 5% 1/4W	
R627 Δ	1-220-797-11	CEMENTED 0.47 5% 10W	
		(KV-32V40/32S40/34SL40/32S45/34SL45/32V65CND/34VL65/34SL40T/35S40/35S45/37SL45/35V65CND/37VL65 only)	
R628	1-240-205-91	CARBON 22M 5% 1/2W	
R629 Δ	1-220-797-11	CEMENTED 0.47 5% 10W	
		(KV-32V40/32S40/34SL40/32S45/34SL45/32V65CND/34VL65/34SL40T/35S40/35S45/37SL45/35V65CND/37VL65 only)	
R630	1-215-421-00	METAL 1K 1% 1/4W	
		(KV-34VL65C/37VL65C/34SL40C only)	
R631	1-215-445-00	METAL 10K 1% 1/4W	
		(KV-34VL65C/37VL65C/34SL40C only)	
R632	1-249-421-11	CARBON 2.2K 5% 1/4W	
R633	1-249-429-11	CARBON 10K 5% 1/4W	
R634	1-249-437-11	CARBON 47K 5% 1/4W	
R635	1-247-791-91	CARBON 22 5% 1/4W	
R636	1-249-415-11	CARBON 680 5% 1/4W	
R637	1-260-302-51	CARBON 6.8 5% 1/2W	
R638	1-249-413-11	CARBON 470 5% 1/4W	
R639 Δ	1-249-389-11	CARBON 4.7 5% 1/4W F	
R640	1-215-485-00	METAL 470K 1% 1/4W	
R640	1-247-895-91	CARBON 470K 5% 1/4W	
R641	1-247-843-11	CARBON 3.3K 5% 1/4W	
R642	1-247-843-11	CARBON 3.3K 5% 1/4W	
R643	1-249-387-11	CARBON 3.3 5% 1/4W F	
R648	1-247-887-00	CARBON 220K 5% 1/4W	
R649	1-249-425-11	CARBON 4.7K 5% 1/4W F	
R659	1-249-429-11	CARBON 10K 5% 1/4W	
R660 Δ	1-249-393-11	CARBON 10 5% 1/4W F	
R661	1-249-419-11	CARBON 1.5K 5% 1/4W F	
R666 Δ	1-249-377-11	CARBON 0.47 5% 1/4W F	

REF.NO.	PART NO.	DESCRIPTION	REMARK
R667 Δ	1-249-377-11	CARBON 0.47 5% 1/4W F	
R668 Δ	1-249-377-11	CARBON 0.47 5% 1/4W F	
R670 Δ	1-249-377-11	CARBON 0.47 5% 1/4W F	
R671 Δ	1-249-377-11	CARBON 0.47 5% 1/4W F	
R672 Δ	1-249-377-11	CARBON 0.47 5% 1/4W F	

RELAY

RY600 Δ	1-755-266-11	RELAY, AC POWER
RY601 Δ	1-755-146-11	RELAY, AC POWER

TRANSFORMER

T601 Δ	1-426-717-11	TRANSFORMER, LINE FILTER (LFT)
		(KV-32V40/32S40/34SL40/32S45/34SL45/32V65CND/34VL65/34SL40T/35S40/35S45/37SL45/35V65CND/37VL65 only)
T602 Δ	1-426-717-11	TRANSFORMER, LINE FILTER (LFT)
T603 Δ	1-429-992-21	TRANSFORMER, CONVERTER (PRT)
T605 Δ	1-429-415-11	TRANSFORMER, CONVERTER (PIT)
		(KV-32V40/32S40/34SL40/32S45/34SL45/34SL40C/34SL40T/35S40/35S45/37SL45 only)
T605 Δ	1-431-467-11	TRANSFORMER, CONVERTER (PIT)
		(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)
T621 Δ	1-431-852-11	TRANSFORMER, CONVEYBER (SRT)

THERMISTOR

THP601 Δ	1-809-539-11	THERMISTOR, POSITIVE
		(KV-32V40/32S40/34SL40/32S45/34SL45/32V65CND/34VL65/35S40/35S45/37SL45/35V65CND/37VL65 only)
THP601 Δ	1-809-827-11	THERMISTOR, POSITIVE
		(KV-34VL65C/34SL40C/34SL40T/37VL65C only)

VARISTOR

VDR602	1-801-074-41	VARISTOR ERZV10D271
		(KV-32V40/32S40/34SL40/32S45/34SL45/32V65CND/34VL65/34SL40T/35S40/35S45/37SL45/35V65CND/37VL65 only)
VDR602	1-809-267-41	VARISTOR ERZV10D471
		(KV-34VL65C/34SL40C/37VL65C only)

HS

REF.NO.	PART NO.	DESCRIPTION	REMARK		
<div><div>*</div><div>A-1372-507-A HS BOARD, COMPLETE (KV-35S40/35S45/37SL45 only)</div></div> <div><div>*</div><div>A-1372-510-A HS BOARD, COMPLETE (KV-32V40/34VL65C/32V65CND/34VL65/35V65CND/ 37VL65/37VL65C only)</div></div> <div><div>*</div><div>A-1372-519-A HS BOARD, COMPLETE (KV-32S45/34SL45 only)</div></div>					
<div>CAPACITOR</div>					
C2168	1-104-665-11	ELECT	100MF	20%	25V
	(KV-32S45/34SL45 only)				
C2169	1-126-959-11	ELECT	0.47MF	20%	50V
	(KV-32S45/34SL45 only)				
<div>CONNECTOR</div>					
CN2101	1-564-524-11	PLUG, CONNECTOR 9P			
CN2102	1-564-523-11	PLUG, CONNECTOR 8P			
	(KV-32V40/34VL65C/32V65CND/34VL65/35V65CND/ 37VL65/37VL65C/32S45/34SL45 only)				
<div>DIODE</div>					
D2106	1-810-039-11	LED UNIT			
	(KV-32S45/34SL45 only)				
<div>IC</div>					
IC2103	8-742-014-11	HYB IC SBX1981-51			
	(KV-32S45/34SL45 only)				
<div>RESISTOR</div>					
R2109	1-216-033-00	RES, CHIP	220	5%	1/10W
	(KV-32S45/34SL45 only)				
R2110	1-216-033-00	RES, CHIP	220	5%	1/10W
	(KV-32S45/34SL45 only)				
R2159	1-216-047-91	RES, CHIP	820	5%	1/10W
	(KV-32S45/34SL45 only)				
R2160	1-216-049-91	RES, CHIP	1K	5%	1/10W
	(KV-32S45/34SL45 only)				
R2161	1-216-055-00	RES, CHIP	1.8K	5%	1/10W
	(KV-32S45/34SL45 only)				
R2162	1-216-065-91	RES, CHIP	4.7K	5%	1/10W
	(KV-32S45/34SL45 only)				
R2163	1-216-073-00	RES, CHIP	10K	5%	1/10W
	(KV-32S45/34SL45 only)				

REF.NO.	PART NO.	DESCRIPTION	REMARK
<u>SWITCH</u>			
S2101	1-692-431-21	SWITCH, TACTILE	
		(KV-32S45/34SL45 only)	
S2102	1-692-431-21	SWITCH, TACTILE	
		(KV-32S45/34SL45 only)	
S2103	1-692-431-21	SWITCH, TACTILE	
		(KV-32S45/34SL45 only)	
S2104	1-692-431-21	SWITCH, TACTILE	
		(KV-32S45/34SL45 only)	
S2105	1-692-431-21	SWITCH, TACTILE	
		(KV-32S45/34SL45 only)	
S2106	1-692-431-21	SWITCH, TACTILE	
		(KV-32S45/34SL45 only)	
S2107	1-692-431-21	SWITCH, TACTILE	
		(KV-32S45/34SL45 only)	



COMPLETE PARTS LISTING

REF.NO.	PART NO.	DESCRIPTION	REMARK
<div>HV</div>			
* A-1372-505-A HV BOARD, COMPLETE (KV-32V40 only)			
* A-1372-509-A HV BOARD, COMPLETE (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)			
* A-1372-523-A HV BOARD, COMPLETE (KV-35S40/35S45/37SL45 only)			
CAPACITOR			
C2068	1-104-665-11	ELECT	100MF 20% 25V
C2070	1-165-319-11	CERAMIC CHIP	0.1MF 50V
C2231	1-163-031-11	CERAMIC CHIP	0.01MF 50V (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)
C2232	1-136-161-00	FILM	0.047MF 5% 50V (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)
C2233	1-136-161-00	FILM	0.047MF 5% 50V (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only) (KV-32V40 only)
C2234	1-126-960-11	ELECT	1MF 20% 50V (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only) (KV-32V40 only)
C2235	1-126-960-11	ELECT	1MF 20% 50V (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only) (KV-32V40 only)
CONNECTOR			
CN2002*	1-564-518-11	PLUG, CONNECTOR 3P	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)
DIODE			
D2006	1-810-039-11	LED UNIT	
D2231	8-719-110-17	DIODE RD10ESB2	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)
D2232	8-719-110-17	DIODE RD10ESB2	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)
D2233	8-719-110-17	DIODE RD10ESB2	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)
D2236	8-719-110-17	DIODE RD10ESB2	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only) (KV-32V40 only)
IC			
IC2003	8-742-014-11	HYB IC SBX1981-51	

REF.NO.	PART NO.	DESCRIPTION	REMARK		
<u>JACK</u>					
J2231	1-691-110-11	JACK, PIN 3P			
	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)				
	(KV-32V40 only)				
J2232	1-694-063-11	TERMINAL, S			
	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)				
<u>RESISTOR</u>					
R2009	1-216-033-00	RES, CHIP	220	5%	1/10W
R2010	1-216-033-00	RES, CHIP	220	5%	1/10W
R2059	1-216-047-91	RES, CHIP	820	5%	1/10W
	(KV-35S40/35S45/37SL45 only)				
R2060	1-216-049-91	RES, CHIP	1K	5%	1/10W
	(KV-32V40 only)				
	(KV-35S40/35S45/37SL45 only)				
R2061	1-216-055-00	RES, CHIP	1.8K	5%	1/10W
	(KV-32V40 only)				
	(KV-35S40/35S45/37SL45 only)				
R2062	1-216-065-91	RES, CHIP	4.7K	5%	1/10W
	(KV-32V40 only)				
	(KV-35S40/35S45/37SL45 only)				
R2063	1-216-073-00	RES, CHIP	10K	5%	1/10W
	(KV-32V40 only)				
	(KV-35S40/35S45/37SL45 only)				
R2231	1-216-022-00	RES, CHIP	75	5%	1/10W
	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)				
R2232	1-216-022-00	RES, CHIP	75	5%	1/10W
	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)				
R2233	1-216-065-91	RES, CHIP	4.7K	5%	1/10W
	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)				
R2235	1-216-022-00	RES, CHIP	75	5%	1/10W
	(KV-32V40 only)				
	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)				
R2236	1-216-113-00	RES, CHIP	470K	5%	1/10W
	(KV-32V40 only)				
	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)				
R2237	1-216-065-91	RES, CHIP	4.7K	5%	1/10W
	(KV-32V40 only)				
	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)				
R2238	1-216-113-00	RES, CHIP	470K	5%	1/10W
	(KV-32V40 only)				
	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)				
R2239	1-216-065-91	RES,CHIP	4.7K	5%	1/10W
	(KV-32V40 only)				
	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)				
<u>SWITCH</u>					

<u>REF.NO.</u>	<u>PART NO.</u>	<u>DESCRIPTION</u>	<u>REMARK</u>	<u>REF.NO.</u>	<u>PART NO.</u>	<u>DESCRIPTION</u>	<u>REMARK</u>
S2001	1-692-431-21	SWITCH, TACTILE (KV-32V40 only) (KV-35S40/35S45/37SL45 only)					
S2002	1-692-431-21	SWITCH, TACTILE (KV-32V40 only) (KV-35S40/35S45/37SL45 only)					
S2003	1-692-431-21	SWITCH, TACTILE (KV-32V40 only) (KV-35S40/35S45/37SL45 only)					
S2004	1-692-431-21	SWITCH, TACTILE (KV-32V40 only) (KV-35S40/35S45/37SL45 only)					
S2005	1-692-431-21	SWITCH, TACTILE (KV-32V40 only) (KV-35S40/35S45/37SL45 only)					
S2006	1-692-431-21	SWITCH, TACTILE (KV-32V40 only) (KV-35S40/35S45/37SL45 only)					
S2007	1-692-431-21	SWITCH, TACTILE (KV-32V40 only) (KV-35S40/35S45/37SL45 only)					



COMPLETE PARTS LISTING

REF.NO.	PART NO.	DESCRIPTION	REMARK
---------	----------	-------------	--------

*** A-1380-585-A K BOARD, COMPLETE**

(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)

- * 1-556-945-21 CABLE, P-P
- * 1-557-056-31 CABLE, P-P
- * 4-052-905-01 V5/6 BRACKET
- 8-598-414-00 ANTENNA SWITCH AS-2F

CAPACITOR

C1461	1-126-960-11	ELECT	1MF	20%	50V
C1462	1-126-960-11	ELECT	1MF	20%	50V
C1463	1-126-961-11	ELECT	2.2MF	20%	50V
C1464	1-104-666-11	ELECT	220MF	20%	25V
C1465	1-126-960-11	ELECT	1MF	20%	50V

C1467	1-104-664-11	ELECT	47MF	20%	25V
C1468	1-126-960-11	ELECT	1MF	20%	50V
C1470	1-104-666-11	ELECT	220MF	20%	25V
C1471	1-136-169-00	FILM	0.22MF	5%	50V
C1472	1-136-173-00	FILM	0.47MF	5%	50V

C1473	1-128-550-11	ELECT	2200MF	20%	50V
C1474	1-136-169-00	FILM	0.22MF	5%	50V
C1475	1-128-550-11	ELECT	2200MF	20%	50V
C1476	1-128-550-11	ELECT	2200MF	20%	50V
C1477	1-104-665-11	ELECT	100MF	20%	25V

C1478	1-126-969-11	ELECT	220MF	20%	50V
-------	--------------	-------	-------	-----	-----

CONNECTOR

CN1461	* 1-564-508-11	PLUG, CONNECTOR 5P
CN1462	* 1-564-507-11	PLUG, CONNECTOR 4P
CN1463	* 1-564-508-11	PLUG, CONNECTOR 5P

DIODE

D1461	8-719-991-33	DIODE 1SS133T-77
D1462	8-719-979-50	DIODE EGP30D
D1463	8-719-991-33	DIODE 1SS133T-77
D1464	8-719-991-33	DIODE 1SS133T-77
D1465	8-719-991-33	DIODE 1SS133T-77

D1466	8-719-979-50	DIODE EGP30D
D1467	8-719-979-50	DIODE EGP30D

REF.NO.	PART NO.	DESCRIPTION	REMARK
---------	----------	-------------	--------

IC

IC1461	8-759-089-13	IC TDA7262
--------	--------------	------------

IC LINK

PS1461	1-532-984-11	LINK, IC 2A/90V
--------	--------------	-----------------

TRANSISTOR

Q1461	8-729-422-27	TRANSISTOR 2SD601A-Q
Q1462	8-729-216-22	TRANSISTOR 2SA1162-G
Q1463	8-729-900-53	TRANSISTOR DTC114EK
Q1464	8-729-900-53	TRANSISTOR DTC114EK
Q1465	8-729-216-22	TRANSISTOR 2SA1162-G

RESISTOR

R1461	1-216-061-00	RES, CHIP	3.3K	5%	1/10W
R1462	1-216-073-00	RES, CHIP	10K	5%	1/10W
R1464	1-216-061-00	RES, CHIP	3.3K	5%	1/10W
R1465	1-216-065-91	RES, CHIP	4.7K	5%	1/10W
R1466	1-216-089-91	RES, CHIP	47K	5%	1/10W
R1467	1-216-073-00	RES, CHIP	10K	5%	1/10W
R1469	1-249-385-11	CARBON	2.2	5%	1/4W F
R1470	1-249-385-11	CARBON	2.2	5%	1/4W F
R1471	1-216-089-91	RES, CHIP	47K	5%	1/10W
R1472	1-216-041-00	RES, CHIP	470	5%	1/10W
R1473	1-216-113-00	RES, CHIP	470K	5%	1/10W
R1474	1-216-077-00	RES, CHIP	15K	5%	1/10W
R1475	1-216-077-00	RES, CHIP	15K	5%	1/10W
R1476	1-247-791-91	CARBON	22	5%	1/4W
R1477	1-249-417-11	CARBON	1K	5%	1/4W F

R1478	1-247-791-91	CARBON	22	5%	1/4W
R1479	1-249-417-11	CARBON	1K	5%	1/4W F
R1480	1-249-421-11	CARBON	2.2K	5%	1/4W
R1481	1-249-421-11	CARBON	2.2K	5%	1/4W
R1482	1-216-073-00	RES, CHIP	10K	5%	1/10W

R1483	1-216-073-00	RES, CHIP	10K	5%	1/10W
R1487	1-216-025-91	RES, CHIP	100	5%	1/10W
R1488	1-216-073-00	RES, CHIP	10K	5%	1/10W



REF.NO.	PART NO.	DESCRIPTION	REMARK
---------	----------	-------------	--------

P

*** A-1195-138-A P BOARD, COMPLETE**

(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)

(KV-32S45/34SL45/35S45/37SL45 only)

CAPACITOR

C3319	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C3320	1-126-960-11	ELECT	1MF	20%	50V
C3321	1-163-231-11	CERAMIC CHIP	15PF	5%	50V
C3322	1-163-231-11	CERAMIC CHIP	15PF	5%	50V
C3323	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C3324	1-104-664-11	ELECT	47MF	20%	16V
C3328	1-104-664-11	ELECT	47MF	20%	16V
C3329	1-104-664-11	ELECT	47MF	20%	16V
C3330	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C3331	1-104-664-11	ELECT	47MF	20%	16V
C3332	1-104-664-11	ELECT	47MF	20%	25V
C3334	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C3335	1-163-038-91	CERAMIC CHIP	0.1MF		25V
C3336	1-163-038-91	CERAMIC CHIP	0.1MF		25V
C3337	1-164-005-11	CERAMIC CHIP	0.47MF		25V
C3340	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C3346	1-163-251-11	CERAMIC CHIP	100PF	5%	50V
C3347	1-126-960-11	ELECT	1MF	20%	50V
C3348	1-104-664-11	ELECT	47MF	20%	16V
C3349	1-163-121-00	CERAMIC CHIP	150PF	5%	50V
C3350	1-164-004-11	CERAMIC CHIP	0.1MF	10%	25V
C3352	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C3353	1-164-346-11	CERAMIC CHIP	1MF		16V
C3354	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C3355	1-126-925-11	ELECT	470MF	20%	10V
C3356	1-163-038-91	CERAMIC CHIP	0.1MF		25V
C3357	1-163-038-91	CERAMIC CHIP	0.1MF		25V
C3358	1-163-038-91	CERAMIC CHIP	0.1MF		25V
C3359	1-163-038-91	CERAMIC CHIP	0.1MF		25V
C3360	1-163-038-91	CERAMIC CHIP	0.1MF		25V
C3361	1-163-038-91	CERAMIC CHIP	0.1MF		25V
C3362	1-126-925-11	ELECT	470MF	20%	10V
C3363	1-163-031-11	CERAMIC CHIP	0.01MF		50V
C3364	1-163-231-11	CERAMIC CHIP	15PF	5%	50V
C3365	1-163-133-00	CERAMIC CHIP	470PF	5%	50V
C3366	1-164-005-11	CERAMIC CHIP	0.47MF		25V
C3367	1-126-963-11	ELECT	4.7MF	20%	50V
C3368	1-164-005-11	CERAMIC CHIP	0.47MF		25V

REF.NO.	PART NO.	DESCRIPTION	REMARK
---------	----------	-------------	--------

C3369	1-163-251-11	CERAMIC CHIP	100PF 5% 50V
C3370	1-164-346-11	CERAMIC CHIP	1MF 16V
C3371	1-163-017-00	CERAMIC CHIP	0.0047MF 10% 50V
C3372	1-164-005-11	CERAMIC CHIP	0.47MF 25V

CONNECTOR

CN3301* 1-764-816-11 CONNECTOR, BOARD TO BOARD 20P

IC

IC3302	8-759-231-53	IC TA7805S
IC3303	8-759-533-89	IC SDA9288XE-GEG-B121
IC3304	8-752-086-80	IC CXA2019AQ-T4

COIL

L3301	1-408-607-31	INDUCTOR 22UH
L3302	1-410-473-11	INDUCTOR 18UH
L3303	1-408-612-31	INDUCTOR 56UH

TRANSISTOR

Q3301	8-729-422-27	TRANSISTOR 2SD601A-Q
Q3302	8-729-216-22	TRANSISTOR 2SA1162-G
Q3306	8-729-216-22	TRANSISTOR 2SA1162-G
Q3310	8-729-422-27	TRANSISTOR 2SD601A-Q
Q3312	8-729-216-22	TRANSISTOR 2SA1162-G
Q3314	8-729-216-22	TRANSISTOR 2SA1162-G

RESISTOR

R3301	1-216-295-91	SHORT			
R3302	1-216-295-91	SHORT			
R3305	1-216-057-00	RES, CHIP	2.2K	5%	1/10W
R3312	1-216-037-00	RES, CHIP	330	5%	1/10W
R3313	1-216-295-91	SHORT			
R3314	1-216-049-91	RES, CHIP	1K	5%	1/10W
R3323	1-216-065-91	RES, CHIP	4.7K	5%	1/10W
R3329	1-216-069-00	RES, CHIP	6.8K	5%	1/10W
R3330	1-216-295-91	SHORT			
R3337	1-216-033-00	RES, CHIP	220	5%	1/10W
R3338	1-216-033-00	RES, CHIP	220	5%	1/10W
R3339	1-216-049-91	RES, CHIP	1K	5%	1/10W
R3340	1-216-041-00	RES, CHIP	470	5%	1/10W
R3341	1-216-057-00	RES, CHIP	2.2K	5%	1/10W
R3342	1-216-057-00	RES, CHIP	2.2K	5%	1/10W
R3343	1-216-049-91	RES, CHIP	1K	5%	1/10W
R3346	1-216-049-91	RES, CHIP	1K	5%	1/10W
R3351	1-216-295-91	SHORT			
R3352	1-216-049-91	RES, CHIP	1K	5%	1/10W



COMPLETE PARTS LISTING

<u>REF.NO.</u>	<u>PART NO.</u>	<u>DESCRIPTION</u>		<u>REMARK</u>		<u>REF.NO.</u>	<u>PART NO.</u>	<u>DESCRIPTION</u>	<u>REMARK</u>
R3358	1-216-047-91	RES, CHIP	820	5%	1/10W				
R3359	1-216-047-91	RES, CHIP	820	5%	1/10W				
R3360	1-216-053-00	RES, CHIP	1.5K	5%	1/10W				
R3361	1-216-053-00	RES, CHIP	1.5K	5%	1/10W				
R3362	1-216-041-00	RES, CHIP	470	5%	1/10W				
R3363	1-216-041-00	RES, CHIP	470	5%	1/10W				
R3364	1-216-041-00	RES, CHIP	470	5%	1/10W				
R3375	1-216-041-00	RES, CHIP	470	5%	1/10W				
R3376	1-216-071-00	RES, CHIP	8.2K	5%	1/10W				
R3377	1-216-073-00	RES, CHIP	10K	5%	1/10W				
R3378	1-208-786-11	RES, CHIP	1.5K	0.50%	1/10W				
R3379	1-216-077-00	RES, CHIP	15K	5%	1/10W				
R3380	1-216-025-91	RES, CHIP	100	5%	1/10W				
R3381	1-216-025-91	RES, CHIP	100	5%	1/10W				
R3382	1-216-057-00	RES, CHIP	2.2K	5%	1/10W				
R3383	1-216-025-91	RES, CHIP	100	5%	1/10W				
R3384	1-216-033-00	RES, CHIP	220	5%	1/10W				
R3385	1-216-109-00	RES, CHIP	330K	5%	1/10W				
R3386	1-216-295-91	SHORT							
R3387	1-216-295-91	SHORT							
R3388	1-216-295-91	SHORT							
R3393	1-216-025-91	RES, CHIP	100	5%	1/10W				
R3394	1-216-025-91	RES, CHIP	100	5%	1/10W				
R3395	1-216-061-00	RES, CHIP	3.3K	5%	1/10W				
<u>CRYSTAL</u>									
X3302	1-760-095-21	VIBRATOR, CRYSTAL							
X3303	1-577-611-11	OSCILLATOR, CERAMIC							
X3304	1-567-505-11	OSCILLATOR, CRYSTAL							

REF.NO.	PART NO.	DESCRIPTION	REMARK			
<div>UV</div> <div>* A-1394-905-A UV BOARD, COMPLETE (KV-32V40 only)</div> <div>* A-1394-906-A UV BOARD, COMPLETE (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)</div> <div>CAPACITOR</div>						
C100	1-164-346-11	CERAMIC CHIP	1MF		16V	
C101	1-165-319-11	CERAMIC CHIP	0.1MF		50V	
C102	1-164-346-11	CERAMIC CHIP	1MF		16V	
C103	1-163-017-00	CERAMIC CHIP	0.0047MF	10%	50V	
C104	1-164-005-11	CERAMIC CHIP	0.47MF		25V	
C105	1-164-005-11	CERAMIC CHIP	0.47MF		25V	
C150	1-126-956-91	ELECT	0.1MF	20%	50V	
C153	1-163-017-00	CERAMIC CHIP	0.0047MF	10%	50V	
C154	1-126-963-11	ELECT	4.7MF	20%	50V	
C155	1-126-963-11	ELECT	4.7MF	20%	50V	
C156	1-126-963-11	ELECT	4.7MF	20%	50V	
C158	1-126-963-11	ELECT	4.7MF	20%	50V	
C160	1-126-964-11	ELECT	10MF	20%	50V	
C161	1-126-956-91	ELECT	0.1MF	20%	50V	
C162	1-163-017-00	CERAMIC CHIP	0.0047MF	10%	50V	
C163	1-104-664-11	ELECT	47MF	20%	25V	
C164	1-165-319-11	CERAMIC CHIP	0.1MF		50V	
C165	1-126-964-11	ELECT	10MF	20%	50V	
C168	1-126-963-11	ELECT	4.7MF	20%	50V	
C171	1-126-941-11	ELECT	470MF	20%	25V	
C172	1-126-959-11	ELECT	0.47MF	20%	50V	
C173	1-126-959-11	ELECT	0.47MF	20%	50V	
C174	1-126-964-11	ELECT	10MF	20%	50V	
C176	1-126-964-11	ELECT	10MF	20%	50V	
C177	1-126-964-11	ELECT	10MF	20%	50V	
C178	1-126-964-11	ELECT	10MF	20%	50V	
C179	1-164-182-11	CERAMIC CHIP	0.0033MF	10%	50V	
C180	1-164-182-11	CERAMIC CHIP	0.0033MF	10%	50V	
C181	1-163-989-11	CERAMIC CHIP	0.033MF	10%	25V	
C182	1-163-989-11	CERAMIC CHIP	0.033MF	10%	25V	
C183	1-163-227-11	CERAMIC CHIP	10PF	0.5PF	50V	
C184	1-163-227-11	CERAMIC CHIP	10PF	0.5PF	50V	
C185	1-163-227-11	CERAMIC CHIP	10PF	0.5PF	50V	
C187	1-126-964-11	ELECT	10MF	20%	50V	
C188	1-126-956-91	ELECT	0.1MF	20%	50V	
C189	1-126-956-91	ELECT	0.1MF	20%	50V	
C190	1-163-986-00	CERAMIC CHIP	0.027MF	10%	25V	
C191	1-163-017-00	CERAMIC CHIP	0.0047MF	10%	50V	
C192	1-163-005-11	CERAMIC CHIP	470PF	10%	50V	
C193	1-165-319-11	CERAMIC CHIP	0.1MF		50V	
C194	1-163-023-00	CERAMIC CHIP	0.015MF	10%	50V	
C195	1-164-161-11	CERAMIC CHIP	0.0022MF	10%	50V	
C196	1-126-965-11	ELECT	22MF	20%	50V	
C197	1-165-319-11	CERAMIC CHIP	0.1MF		50V	
C198	1-126-960-11	ELECT	1MF	20%	50V	
C199	1-165-319-11	CERAMIC CHIP	0.1MF		50V	
C231	1-163-031-11	CERAMIC CHIP	0.01MF		50V	
C232	1-136-161-00	FILM	0.047MF	5%	50V	
C233	1-136-161-00	FILM	0.047MF	5%	50V	
C234	1-126-960-11	ELECT	1MF	20%	50V	
C235	1-126-960-11	ELECT	1MF	20%	50V	
C236	1-136-161-00	FILM	0.047MF	5%	50V	
C237	1-126-960-11	ELECT	1MF	20%	50V	
C238	1-126-960-11	ELECT	1MF	20%	50V	
C241	1-126-941-11	ELECT	470MF	20%	25V	
C242	1-126-959-11	ELECT	0.47MF	20%	50V	
C244	1-126-959-11	ELECT	0.47MF	20%	50V	
C245	1-126-941-11	ELECT	470MF	20%	25V	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)
C246	1-126-959-11	ELECT	0.47MF	20%	50V	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)
C247	1-126-959-11	ELECT	0.47MF	20%	50V	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)
C261	1-136-161-00	FILM	0.047MF	5%	50V	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)
C262	1-104-664-11	ELECT	47MF	20%	25V	
C263	1-136-161-00	FILM	0.047MF	5%	50V	
C264	1-126-941-11	ELECT	470MF	20%	25V	
C266	1-126-960-11	ELECT	1MF	20%	50V	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)
C267	1-126-960-11	ELECT	1MF	20%	50V	(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)
C270	1-126-960-11	ELECT	1MF	20%	50V	
C271	1-126-960-11	ELECT	1MF	20%	50V	
C275	1-104-664-11	ELECT	47MF	20%	25V	
C276	1-163-251-11	CERAMIC CHIP	100PF	5%	50V	
CONNECTOR						
CN261	1-691-632-21	CONNECTOR, BOARD TO BOARD	15P			
CN262	1-573-301-21	CONNECTOR, BOARD TO BOARD	20P			
CN263 *	1-564-506-11	PLUG, CONNECTOR	3P			
CN264	1-573-979-21	CONNECTOR, BOARD TO BOARD	11P			
CN265	1-564-508-11	PLUG, CONNECTOR	5P			(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)



COMPLETE PARTS LISTING

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
DIODE							
D100	8-719-981-99	DIODE MTZJ-3.3		J902	1-764-143-11	JACK 3P (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
D231	8-719-110-17	DIODE RD10ESB2		J903	1-764-143-11	JACK 3P (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
D232	8-719-110-17	DIODE RD10ESB2		J904	1-764-143-11	JACK 3P (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
D233	8-719-110-17	DIODE RD10ESB2		CHIP CONDUCTOR			
D234	8-719-110-17	DIODE RD10ESB2		JR101	1-216-295-91	SHORT (KV-32V40 only)	
D235	8-719-110-17	DIODE RD10ESB2		JR106	1-216-295-91	SHORT	
D236	8-719-110-17	DIODE RD10ESB2		JR107	1-216-295-91	SHORT	
D237	8-719-981-99	DIODE MTZJ-3.3		JR109	1-216-295-91	SHORT (KV-32V40 only)	
D238	8-719-981-99	DIODE MTZJ-3.3		JR201	1-216-295-91	SHORT	
D239	8-719-981-99	DIODE MTZJ-3.3 (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)		JR204	1-216-295-91	SHORT	
D240	8-719-110-17	DIODE RD10ESB2		JR205	1-216-295-91	SHORT	
D241	8-719-110-17	DIODE RD10ESB2		JR269	1-216-295-91	SHORT	
D242	8-719-110-17	DIODE RD10ESB2		JR270	1-216-295-91	SHORT	
D243	8-719-110-17	DIODE RD10ESB2		JR272	1-216-295-91	SHORT	
D244	8-719-110-17	DIODE RD10ESB2		JR273	1-216-295-91	SHORT	
D245	8-719-981-99	DIODE MTZJ-3.3 (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)		JR274	1-216-295-91	SHORT	
D246	8-719-981-99	DIODE MTZJ-3.3		JR276	1-216-295-91	SHORT	
D264	8-719-110-17	DIODE RD10ESB2		JR901	1-216-295-91	SHORT (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
D265	8-719-110-17	DIODE RD10ESB2		TRANSISTOR			
D902	8-719-110-17	DIODE RD10ESB2 (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)		Q100	8-729-422-27	TRANSISTOR 2SD601A-Q	
IC				Q101	8-729-422-27	TRANSISTOR 2SD601A-Q	
IC100	8-752-072-39	IC CXA2021S		Q231	8-729-422-27	TRANSISTOR 2SD601A-Q	
IC101	8-759-100-96	IC UPC4558G2		Q232	8-729-422-27	TRANSISTOR 2SD601A-Q (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
IC102	8-759-537-25	IC NJM2150M		Q233	8-729-422-27	TRANSISTOR 2SD601A-Q	
IC103	8-759-537-26	IC TDA7467D		Q234	8-729-422-27	TRANSISTOR 2SD601A-Q	
IC261	8-759-366-77	IC MM1311AD (KV-32V40 only)		Q235	8-729-422-27	TRANSISTOR 2SD601A-Q (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
IC261	8-759-534-81	IC MM1313AD (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)		Q236	8-729-422-27	TRANSISTOR 2SD601A-Q (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
JACK				Q237	8-729-216-22	TRANSISTOR 2SA1162-G	
J231	1-750-515-11	TERMINAL BLOCK, S 3P		Q238	8-729-216-22	TRANSISTOR 2SA1162-G	
J232	1-750-517-11	JACK BLOCK, PIN 3P		Q239	8-729-216-22	TRANSISTOR 2SA1162-G	
J233	1-750-516-11	JACK BLOCK, PIN 2P		Q240	8-729-216-22	TRANSISTOR 2SA1162-G (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
J234	1-750-517-11	JACK BLOCK, PIN 3P		Q241	8-729-216-22	TRANSISTOR 2SA1162-G (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
J235	1-750-517-11	JACK BLOCK, PIN 3P (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)		Q242	8-729-216-22	TRANSISTOR 2SA1162-G (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
				Q243	8-729-216-22	TRANSISTOR 2SA1162-G	

Note:

The components identified with shading and a critical symbol (Δ) are critical for safety. Replace only with part number specified.

Note:

Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

COMPLETE PARTS LISTING

REF.NO.	PART NO.	DESCRIPTION	REMARK			
Q261	8-729-422-27	TRANSISTOR 2SD601A-Q (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)				
Q262	8-729-422-27	TRANSISTOR 2SD601A-Q				
Q263	8-729-216-22	TRANSISTOR 2SA1162-G				
Q265	8-729-216-22	TRANSISTOR 2SA1162-G				
RESISTOR						
R100	1-216-033-00	RES, CHIP	220	5%	1/10W	
R101	1-216-033-00	RES, CHIP	220	5%	1/10W	
R102	1-216-073-00	RES, CHIP	10K	5%	1/10W	
R103	1-216-093-00	RES, CHIP	68K	5%	1/10W	
R104	1-216-089-91	RES, CHIP	47K	5%	1/10W	
R105	1-216-089-91	RES, CHIP	47K	5%	1/10W	
R106	1-216-049-91	RES, CHIP	1K	5%	1/10W	
R107	1-216-049-91	RES, CHIP	1K	5%	1/10W	
R108	1-216-073-00	RES, CHIP	10K	5%	1/10W	
R109	1-216-089-91	RES, CHIP	47K	5%	1/10W	
R110	1-216-089-91	RES, CHIP	47K	5%	1/10W	
R111	1-216-025-91	RES, CHIP	100	5%	1/10W	
R112	1-216-121-91	RES, CHIP	1M	5%	1/10W	
R113	1-216-081-00	RES, CHIP	22K	5%	1/10W	
R114	1-216-081-00	RES, CHIP	22K	5%	1/10W	
R115	1-216-081-00	RES, CHIP	22K	5%	1/10W	
R116	1-216-081-00	RES, CHIP	22K	5%	1/10W	
R117	1-216-073-00	RES, CHIP	10K	5%	1/10W	
R118	1-216-073-00	RES, CHIP	10K	5%	1/10W	
R119	1-216-073-00	RES, CHIP	10K	5%	1/10W	
R124	1-216-033-00	RES, CHIP	220	5%	1/10W	
R125	1-216-033-00	RES, CHIP	220	5%	1/10W	
R126	1-216-063-91	RES, CHIP	3.9K	5%	1/10W	
R127	1-216-089-91	RES, CHIP	47K	5%	1/10W	
R128	1-216-085-00	RES, CHIP	33K	5%	1/10W	
R129	1-216-053-00	RES, CHIP	1.5K	5%	1/10W	
R130	1-216-100-00	RES, CHIP	130K	5%	1/10W	
R131	1-216-049-91	RES, CHIP	1K	5%	1/10W	
R132	1-216-088-00	RES, CHIP	43K	5%	1/10W	
R133	1-216-061-00	RES, CHIP	3.3K	5%	1/10W	
R134	1-216-061-00	RES, CHIP	3.3K	5%	1/10W	
R135	1-216-097-91	RES, CHIP	100K	5%	1/10W	
R136	1-216-093-00	RES, CHIP	68K	5%	1/10W	
R137	1-216-025-91	RES, CHIP	100	5%	1/10W	
R141	1-216-295-91	SHORT				
(KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)						

REF.NO.	PART NO.	DESCRIPTION	REMARK			
R142	1-216-295-91	SHORT (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)				
R201	1-216-065-91	RES, CHIP	4.7K	5%	1/10W	
R202	1-216-049-91	RES, CHIP	1K	5%	1/10W	
R203	1-216-069-00	RES, CHIP	6.8K	5%	1/10W	
R204	1-216-069-00	RES, CHIP	6.8K	5%	1/10W	
R206	1-216-049-91	RES, CHIP	1K	5%	1/10W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R207	1-216-295-91	SHORT (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)				
R208	1-216-049-91	RES, CHIP	1K	5%	1/10W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R209	1-216-069-00	RES, CHIP	6.8K	5%	14W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R210	1-216-069-00	RES, CHIP	6.8K	5%	1/10W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R212	1-249-440-11	CARBON	82K	5%	1/4W	
R213	1-216-065-91	RES, CHIP	4.7K	5%	1/10W	
R214	1-216-065-91	RES, CHIP	4.7K	5%	1/10W	
R215	1-249-413-11	CARBON	470	5%	1/4W	
R216	1-216-025-91	RES, CHIP	100	5%	1/10W	
R217	1-216-025-91	RES, CHIP	100	5%	1/10W	
R218	1-216-025-91	RES, CHIP	100	5%	1/10W	
R219	1-216-065-91	RES, CHIP	4.7K	5%	1/10W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R220	1-216-065-91	RES, CHIP	4.7K	5%	1/10W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R221	1-249-413-11	CARBON	470	5%	1/4W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R222	1-216-025-91	RES, CHIP	100	5%	1/10W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R223	1-216-025-91	RES, CHIP	100	5%	1/10W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R224	1-216-025-91	RES, CHIP	100	5%	1/10W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R225	1-247-815-91	CARBON	220	5%	1/4W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R226	1-247-815-91	CARBON	220	5%	1/4W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R227	1-249-440-11	CARBON	82K	5%	1/4W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R228	1-216-033-00	RES, CHIP	220	5%	1/10W	
R229	1-216-025-91	RES, CHIP	100	5%	1/10W	
R230	1-216-033-00	RES, CHIP	220	5%	1/10W	
R231	1-216-022-00	RES, CHIP	75	5%	1/10W	
R232	1-216-022-00	RES, CHIP	75	5%	1/10W	
R233	1-216-065-91	RES, CHIP	4.7K	5%	1/10W	
R234	1-216-022-00	RES, CHIP	75	5%	1/10W	
R235	1-216-113-00	RES, CHIP	470K	5%	1/10W	



COMPLETE PARTS LISTING

REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
R236	1-216-065-91	RES, CHIP	4.7K 5% 1/10W	R275	1-249-425-11	CARBON 4.7K 5% 1/4W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R237	1-216-113-00	RES, CHIP	470K 5% 1/10W	R276	1-249-425-11	CARBON 4.7K 5% 1/4W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R238	1-216-065-91	RES, CHIP	4.7K 5% 1/10W	R277	1-216-049-91	RES, CHIP 1K 5% 1/10W	
R239	1-216-022-00	RES, CHIP	75 5% 1/10W	R278	1-249-413-11	CARBON 470 5% 1/4W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R240	1-216-113-00	RES, CHIP	470K 5% 1/10W	R279	1-216-025-91	RES, CHIP 100 5% 1/10W	
R241	1-216-065-91	RES, CHIP	4.7K 5% 1/10W	R280	1-216-033-00	RES, CHIP 220 5% 1/10W	
R242	1-216-113-00	RES, CHIP	470K 5% 1/10W	R281	1-216-033-00	RES, CHIP 220 5% 1/10W	
R243	1-216-065-91	RES, CHIP	4.7K 5% 1/10W	R282	1-216-025-91	RES, CHIP 100 5% 1/10W	
R244	1-216-113-00	RES, CHIP	470K 5% 1/10W	R283	1-216-025-91	RES, CHIP 100 5% 1/10W	
R245	1-249-417-11	CARBON	1K 5% 1/4W	R284	1-216-065-91	RES, CHIP 4.7K 5% 1/10W	
R246	1-216-113-00	RES, CHIP	470K 5% 1/10W	R285	1-216-065-91	RES, CHIP 4.7K 5% 1/10W	
R247	1-249-417-11	CARBON	1K 5% 1/4W	R286	1-216-049-91	RES, CHIP 1K 5% 1/10W	
R248	1-216-021-00	RES, CHIP	68 5% 1/10W	R288	1-247-815-91	CARBON 220 5% 1/4W	
R249	1-216-113-00	RES, CHIP	470K 5% 1/10W	R289	1-247-815-91	CARBON 220 5% 1/4W	
R250	1-216-113-00	RES, CHIP	470K 5% 1/10W	R290	1-247-815-91	CARBON 220 5% 1/4W	
R251	1-216-113-00	RES, CHIP	470K 5% 1/10W	R291	1-216-025-91	RES, CHIP 100 5% 1/10W	
R252	1-216-019-00	RES, CHIP	56 5% 1/10W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	R292	1-216-025-91	RES, CHIP 100 5% 1/10W (KV-32V40 only)	
R253	1-216-113-00	RES, CHIP	470K 5% 1/10W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	R293	1-216-025-91	RES, CHIP 100 5% 1/10W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R254	1-216-113-00	RES, CHIP	470K 5% 1/10W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	R294	1-216-049-91	RES, CHIP 1K 5% 1/10W	
R255	1-216-113-00	RES, CHIP	470K 5% 1/10W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	R902	1-249-405-11	CARBON 100 5% 1/4W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R256	1-216-069-00	RES, CHIP	6.8K 5% 1/10W	R919	1-216-295-91	SHORT (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R258	1-216-069-00	RES, CHIP	6.8K 5% 1/10W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	R920	1-249-405-11	CARBON 100 5% 1/4W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R259	1-216-065-91	RES, CHIP	4.7K 5% 1/10W	R921	1-249-405-11	CARBON 100 5% 1/4W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R260	1-247-807-31	CARBON	100 5% 1/4W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	R922	1-216-049-91	RES, CHIP 1K 5% 1/10W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R261	1-216-009-00	RES, CHIP	22 5% 1/10W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	R923	1-216-049-91	RES, CHIP 1K 5% 1/10W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R264	1-247-815-91	CARBON	220 5% 1/4W	R924	1-216-049-91	RES, CHIP 1K 5% 1/10W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)	
R265	1-247-815-91	CARBON	220 5% 1/4W				
R266	1-216-043-91	RES, CHIP	560 5% 1/10W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)				
R267	1-249-415-11	CARBON	680 5% 1/4W (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C only)				
R268	1-216-025-91	RES, CHIP	100 5% 1/10W				
R269	1-216-025-91	RES, CHIP	100 5% 1/10W				
R270	1-216-041-00	RES, CHIP	470 5% 1/10W				
R271	1-249-415-11	CARBON	680 5% 1/4W				
R272	1-249-417-11	CARBON	1K 5% 1/4W				
R274	1-249-413-11	CARBON	470 5% 1/4W				

REF.NO.	PART NO.	DESCRIPTION	REMARK		
<div>WA</div>					
* A-1372-462-A WA BOARD, COMPLETE (KV-35S40/35S45/37SL45/35V65CND/37VL65/37VL65C only)					
4-382-854-11 SCREW (M3X10), P, SW (+)					
CAPACITOR					
C941	1-126-935-11	ELECT	470MF	20%	16V
C944	1-163-021-91	CERAMIC CHIP	0.01MF	10%	50V
C945	1-163-001-11	CERAMIC CHIP	220PF	10%	50V
C946	1-126-933-11	ELECT	100MF	20%	16V
C949	1-161-830-00	CERAMIC CHIP	0.0047MF		500V
C950	1-126-933-11	ELECT	100MF	20%	16V
C951	1-107-638-11	ELECT	33MF	20%	160V
C952	1-104-999-11	MYLAR	0.1MF	10%	200V
C953	1-106-383-00	MYLAR	0.047MF	10%	200V
C954	1-137-364-11	FILM	0.001MF	5%	50V
C955	1-107-667-11	ELECT	2.2MF	20%	160V
C956	1-137-364-11	FILM	0.001MF	5%	50V
C957	1-106-383-00	MYLAR	0.047MF	10%	200V
C958	1-126-933-11	ELECT	100MF	20%	16V
C961	1-163-251-11	CERAMIC CHIP	100PF	5%	50V
C962	1-163-021-91	CERAMIC CHIP	0.01MF	10%	50V
C965	1-163-035-00	CERAMIC CHIP	0.047MF		50V
C966	1-163-009-11	CERAMIC CHIP	0.001MF	10%	50V
C967	1-129-718-00	FILM	0.022MF	5%	630V
C968	1-137-579-11	FILM	0.068MF	5%	100V
C969	1-163-035-00	CERAMIC CHIP	0.047MF		50V
C981	1-126-941-11	ELECT	470MF	20%	25V
C983	1-137-366-11	FILM	0.0022MF	5%	50V
CONNECTOR					
CN941	1-564-511-11	PLUG, CONNECTOR 8P			
CN961 *	1-770-723-11	CONNECTOR, BOARD TO BOARD 8P			
CN981 *	1-564-506-11	PLUG, CONNECTOR 3P			
DIODE					
D941	8-719-991-33	DIODE 1SS133T-77			
D946	8-719-110-88	DIODE RD39ESB2			
D947	8-719-110-88	DIODE RD39ESB2			
D961	8-719-109-89	DIODE RD5.6ESB2			
D962	8-719-991-33	DIODE 1SS133T-77			
D964	8-719-302-43	DIODE EL1Z			

REF.NO.	PART NO.	DESCRIPTION	REMARK			
<u>IC</u>						
IC961	8-759-700-07	IC NJM2903M				
IC981	8-759-603-37	IC M5216P				
<u>COIL</u>						
L942	1-215-863-11	METAL OXIDE	100	5%	1W F	
L962	1-406-989-21	INDUCTOR				
L963	1-406-675-11	INDUCTOR				
<u>JUMPER WIRE</u>						
JW919	1-136-165-00	FILM	0.1MF	5%	50V	
<u>TRANSISTOR</u>						
Q943	8-729-422-27	TRANSISTOR 2SD601A-Q				
Q944	8-729-422-27	TRANSISTOR 2SD601A-Q				
Q945	8-729-422-27	TRANSISTOR 2SD601A-Q				
Q946	8-729-017-05	TRANSISTOR 2SA1837				
Q947	8-729-017-06	TRANSISTOR 2SC4793				
Q962	8-729-931-45	TRANSISTOR IRF614				
Q963	8-729-216-22	TRANSISTOR 2SA1162-G				
Q965	8-729-422-27	TRANSISTOR 2SD601A-Q				
Q966	8-729-216-22	TRANSISTOR 2SA1162-G				
Q981	8-729-422-27	TRANSISTOR 2SD601A-Q				
<u>RESISTOR</u>						
R943	1-216-025-91	RES, CHIP	100	5%	1/10W	
R948	1-216-049-91	RES, CHIP	1K	5%	1/10W	
R949	1-216-049-91	RES, CHIP	1K	5%	1/10W	
R950	1-216-049-91	RES, CHIP	1K	5%	1/10W	
R951	1-216-049-91	RES, CHIP	1K	5%	1/10W	
R952	1-216-037-00	RES, CHIP	330	5%	1/10W	
R953	1-216-021-00	RES, CHIP	68	5%	1/10W	
R954	1-216-033-00	RES, CHIP	220	5%	1/10W	
R955	1-216-047-91	RES, CHIP	820	5%	1/10W	
R956	1-216-295-91	SHORT				
R957	1-216-073-00	RES, CHIP	10K	5%	1/10W	
R958	1-216-295-91	SHORT				
R959	1-216-021-00	RES, CHIP	68	5%	1/10W	
R960	1-216-689-11	RES, CHIP	39K	5%	1/10W	
R961	1-216-073-00	RES, CHIP	10K	5%	1/10W	
R962	1-216-057-00	RES, CHIP	2.2K	5%	1/10W	
R963	1-216-097-91	RES, CHIP	100K	5%	1/10W	
R964	1-216-073-00	RES, CHIP	10K	5%	1/10W	
R965	1-216-073-00	RES, CHIP	10K	5%	1/10W	
R966	1-216-097-91	RES, CHIP	100K	5%	1/10W	



COMPLETE PARTS LISTING

<u>REF.NO.</u>	<u>PART NO.</u>	<u>DESCRIPTION</u>			<u>REMARK</u>	
R967	1-216-065-91	RES, CHIP	4.7K	5%	1/10W	
R968	1-216-083-00	RES, CHIP	27K	5%	1/10W	
R969	1-216-295-91	SHORT				
R970	1-216-033-00	RES, CHIP	220	5%	1/10W	
R971	1-247-899-11	CARBON	680K	5%	1/4W	
R972	1-216-073-00	RES, CHIP	10K	5%	1/10W	
R973	1-216-121-91	RES, CHIP	1M	5%	1/10W	
R974	1-216-073-00	RES, CHIP	10K	5%	1/10W	
R975	1-216-446-00	METAL OXIDE	18	5%	2W	F
R976	1-216-423-11	METAL OXIDE	27	5%	1W	F
R979	1-216-017-91	RES, CHIP	47	5%	1/10W	
R981	1-216-081-00	RES, CHIP	22K	5%	1/10W	
R982	1-216-081-00	RES, CHIP	22K	5%	1/10W	
R983	1-216-081-00	RES, CHIP	22K	5%	1/10W	
R984	1-216-081-00	RES, CHIP	22K	5%	1/10W	
R987	1-216-049-91	RES, CHIP	1K	5%	1/10W	
R988	1-216-295-91	SHORT				
R989	1-216-304-11	RES, CHIP	3.3	5%	1/10W	
R992	1-216-073-00	RES, CHIP	10K	5%	1/10W	
R1941	1-260-311-11	CARBON	39	5%	1/2W	
R1942	1-249-384-11	CARBON	1.8	5%	1/4W	F
R1943	1-249-414-11	CARBON	560	5%	1/4W	F
R1944	1-249-432-11	CARBON	18K	5%	1/4W	
R1945	1-216-476-11	METAL OXIDE	180	5%	3W	F
R1946	1-249-417-11	CARBON	1K	5%	1/4W	F
R1947	1-249-432-11	CARBON	18K	5%	1/4W	
R1948	1-249-414-11	CARBON	560	5%	1/4W	
R1949	1-249-384-11	CARBON	1.8	5%	1/4W	F
R1950	1-249-400-11	CARBON	39	5%	1/4W	F

REF.NO.	PART NO.	DESCRIPTION	REMARK			
<div>WB</div>						
* A-1372-508-A WB BOARD, COMPLETE (KV-32V40/34VL65C/32V65CND/34VL65/32S40/ 34SL40/34SL40C/32S45/34SL45 only)						
4-382-854-11 SCREW (M3X10), P, SW (+)						
CAPACITOR						
C2941	1-126-935-11	ELECT	470MF	20%	16V	
C2944	1-163-021-91	CERAMIC CHIP	0.01MF	10%	50V	
C2946	1-126-933-11	ELECT	100MF	20%	16V	
C2949	1-161-830-00	CERAMIC CHIP	0.0047MF		500V	
C2950	1-126-933-11	ELECT	100MF	20%	16V	
C2951	1-107-638-11	ELECT	33MF	20%	160V	
C2952	1-104-999-11	MYLAR	0.1MF	10%	200V	
C2953	1-106-383-00	MYLAR	0.047MF	10%	200V	
C2954	1-137-364-11	FILM	0.001MF	5%	50V	
C2955	1-107-667-11	ELECT	2.2MF	20%	160V	
C2956	1-137-364-11	FILM	0.001MF	5%	50V	
C2957	1-106-383-00	MYLAR	0.047MF	10%	200V	
C2958	1-126-933-11	ELECT	100MF	20%	16V	
C2975	1-163-001-11	CERAMIC CHIP	220PF	10%	50V	
CONNECTOR						
CN2941*	1-564-508-11	PLUG, CONNECTOR 5P				
DIODE						
D2941	8-719-991-33	DIODE 1SS133T-77				
D2946	8-719-110-88	DIODE RD39ESB2				
D2947	8-719-110-88	DIODE RD39ESB2				
COIL						
L2942	1-215-863-11	METAL OXIDE	100	5%	1W	F
TRANSISTOR						
Q2943	8-729-422-27	TRANSISTOR 2SD601A-Q				
Q2944	8-729-422-27	TRANSISTOR 2SD601A-Q				
Q2945	8-729-422-27	TRANSISTOR 2SD601A-Q				
Q2946	8-729-017-05	TRANSISTOR 2SA1837				
Q2947	8-729-017-06	TRANSISTOR 2SC4793				
Q2965	8-729-422-27	TRANSISTOR 2SD601A-Q				
Q2966	8-729-216-22	TRANSISTOR 2SA1162-G				

REF.NO.	PART NO.	DESCRIPTION	REMARK			
RESISTOR						
R2943	1-216-025-91	RES,CHIP	100	5%	1/10W	
R2948	1-216-049-91	RES,CHIP	1K	5%	1/10W	
R2949	1-216-049-91	RES,CHIP	1K	5%	1/10W	
R2950	1-216-049-91	RES,CHIP	1K	5%	1/10W	
R2951	1-216-049-91	RES,CHIP	1K	5%	1/10W	
R2952	1-216-037-00	RES,CHIP	330	5%	1/10W	
R2953	1-216-021-00	RES,CHIP	68	5%	1/10W	
R2954	1-216-033-00	RES,CHIP	220	5%	1/10W	
R2955	1-216-047-91	RES,CHIP	820	5%	1/10W	
R2956	1-216-295-91	SHORT				
R2957	1-216-073-00	RES,CHIP	10K	5%	1/10W	
R2958	1-216-295-91	SHORT				
R2959	1-216-021-00	RES,CHIP	68	5%	1/10W	
R2979	1-216-017-91	RES,CHIP	47	5%	1/10W	
R4941	1-260-311-11	CARBON	39	5%	1/2W	
R4942	1-249-384-11	CARBON	1.8	5%	1/4W	F
R4943	1-249-414-11	CARBON	560	5%	1/4W	F
R4944	1-249-432-11	CARBON	18K	5%	1/4W	
R4945	1-216-476-11	METAL OXIDE	180	5%	3W	F
R4946	1-249-417-11	CARBON	1K	5%	1/4W	F
R4947	1-249-432-11	CARBON	18K	5%	1/4W	
R4948	1-249-414-11	CARBON	560	5%	1/4W	
R4949	1-249-384-11	CARBON	1.8	5%	1/4W	F
R4950	1-249-400-11	CARBON	39	5%	1/4W	F

ACCESSORIES AND PACKING MATERIALS

REF.NO.	PART NO.	DESCRIPTION	REMARK
<u>S SERIES</u>			
<u>ACCESSORIES AND PACKING MATERIALS</u>			
4-041-259-01 *		BAG, PROTECTION (KV-32S40/34SL40/34SL40C/32S45/34SL45/34SL40T)	
4-053-658-01 *		BAG, PROTECTION (KV-35S40/35S45/37SL45)	
4-063-179-01 *		CARTON, INDIVIDUAL (KV-32S40/32S45/34SL40T)	
4-056-782-01 *		CARTON, INDIVIDUAL (KV-35S40/35S45/37SL45)	
4-065-233-01 *		CARTON, INDIVIDUAL (KV-34SL40/34SL40C/34SL45)	
4-056-783-01 *		CUSHION, UPPER ASSY (KV-35S40/35S45/37SL45)	
4-063-180-01 *		CUSHION, UPPER ASSY (KV-32S40/34SL40/34SL40C/32S45/34SL45/34SL40T)	
4-056-784-01 *		CUSHION, LOWER ASSY (KV-35S40/35S45/37SL45)	
4-063-181-01 *		CUSHION, LOWER ASSY (KV-32S40/34SL40/34SL40C/32S45/34SL45/34SL40T)	
3-862-568-21		MANUAL, INSTRUCTION (KV-32S40/32S45/35S40/35S45)	
3-862-708-41		MANUAL, INSTRUCTION (KV-34SL40/34SL40C/34SL45/37SL45)	
3-864-098-71		MANUAL, INSTRUCTION (KV-34SL40T)	
<u>REMOTE COMMANDER</u>			
1-475-801-11		REMOTE COMMANDER (RM-Y165) (KV-32S40/34SL40/34SL40C/32S45/35S40/34SL40T)	
4-978-977-01		BATTERY COVER (FOR REMOTE) (KV-32S40/34SL40/34SL40C/32S45/35S40/34SL40T)	
1-475-802-11		REMOTE COMMANDER (RM-Y167) (KV-34SL45/35S45/37SL45)	
4-978-977-01		BATTERY COVER (FOR REMOTE) (KV-34SL45/35S45/37SL45)	

REF.NO.	PART NO.	DESCRIPTION	REMARK
<u>V SERIES</u>			
<u>ACCESSORIES AND PACKING MATERIALS</u>			
4-041-259-01 *		BAG, PROTECTION (KV-32V40/34VL65C/32V65/34VL65)	
4-053-658-01 *		BAG, PROTECTION (KV-35V65/35VL65/35V65C)	
4-065-159-01 *		INDIVIDUAL CARTON (KV-34VL65C/34VL65)	
4-053-276-01 *		INDIVIDUAL CARTON (KV-35V65/35VL65/35V65C)	
4-054-073-12 *		INDIVIDUAL CARTON (KV-32V40/32V65)	
4-053-277-01 *		CUSHION, UPPER ASSY (KV-35V65/35VL65/35V65C)	
4-054-067-01 *		CUSHION, UPPER ASSY (KV-32V40/34VL65C/32V65/34VL65)	
4-054-070-01 *		CUSHION, LOWER ASSY (KV-32V40/34VL65C/32V65/34VL65)	
4-053-278-01 *		CUSHION, LOWER ASSY (KV-35V65/35VL65/35V65C)	
3-862-568-21		MANUAL, INSTRUCTION (KV-32V40)	
3-862-568-31		MANUAL, INSTRUCTION (KV-32V40CND/32V65CND/35V65CND)	
3-862-708-41		MANUAL, INSTRUCTION (KV-34VL65C/34VL65/37VL65C/37VL65)	
<u>REMOTE COMMANDER</u>			
1-475-801-11		REMOTE COMMANDER (RM-Y165) (KV-32V40)	
4-978-977-01		BATTERY COVER (FOR REMOTE) (KV-32V40)	
1-475-802-11		REMOTE COMMANDER (RM-Y167) (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C)	
4-978-977-01		BATTERY COVER (FOR REMOTE) (KV-34VL65C/32V65CND/34VL65/35V65CND/37VL65/37VL65C)	

9-965-843-01

Sony Corporation
Sony Technology Center
Product Quality Division
Service Promotion Department

English
98EJ74429-1
Printed in U.S.A.
© 1998.5

SERVICE MANUAL

AA-2D CHASSIS

<u>MODEL</u>	<u>DEST.</u>	<u>COMMANDER</u>	<u>CHASSIS NO.</u>
KV-32S40	US	RM-Y165	SCC-S07A-A
KV-32S40	CND	RM-Y165	SCC-S08A-A
KV-32S45	US	RM-Y167	SCC-S07B-A
KV-32S45	CND	RM-Y167	SCC-S08B-A
KV-34SL40T	TAIWAN	RM-Y165	SCC-S16A-A
KV-34SL40C	E	RM-Y165	SCC-S09A-A
KV-34SL40	E	RM-Y165	SCC-S09B-A
KV-34SL45	E	RM-Y167	SCC-S09C-A
KV-35S40	US	RM-Y165	SCC-S07D-A
KV-35S40	CND	RM-Y165	SCC-S08E-A
KV-35S45	US	RM-Y167	SCC-S07E-A
KV-35S45	CND	RM-Y167	SCC-S08F-A
KV-37SL45	E	RM-Y167	SCC-S09F-A
KV-32V40	US	RM-Y165	SCC-S07C-A
KV-32V40	CND	RM-Y165	SCC-S08C-A
KV-32V65	US	RM-Y167	SCC-S07P-A
KV-32V65	CND	RM-Y167	SCC-S08D-A
KV-34VL65	E	RM-Y167	SCC-S09E-A
KV-34VL65C	E	RM-Y167	SCC-S09D-A
KV-35V65	US	RM-Y167	SCC-S07Q-A
KV-35V65	CND	RM-Y167	SCC-S08G-A
KV-37VL65	E	RM-Y167	SCC-S09G-A
KV-37VL65C	E	RM-Y167	SCC-S09H-A

SUPPLEMENT-1


SUBJECT: A Board Schematic and Parts List

Correct the service manual as shown.
File this Supplement with the service manual.

TRINITRON® COLOR TV
SONY®

Section 6: A Board Schematic Diagram (S series) (Page 40)
A Board Schematic Diagram (V series) (Page 44)

✎: Added Item



Old

New

Ref.No.	Part No.	Description
C534	Not Listed ---->	Needs to be added
D536	Not Listed ---->	Needs to be added

Ref.No.	Part No.	Description
✎ C534	1-126-967-11	ELECT 47μF 20% 50V
✎ D536	8-719-302-43	DIODE ELIZ